

NVIDIA Performance Primitives (NPP)
Version 8.0

January 28, 2016

Contents

1	NVIDIA Performance Primitives	1
1.1	What is NPP?	2
1.2	Documentation	2
1.3	Technical Specifications	3
1.4	Files	3
1.4.1	Header Files	3
1.4.2	Library Files	3
1.5	Supported NVIDIA Hardware	4
2	General API Conventions	5
2.1	Memory Management	6
2.1.1	Scratch Buffer and Host Pointer	6
2.2	Function Naming	7
2.3	Integer Result Scaling	7
2.4	Rounding Modes	8
2.4.1	Rounding Mode Parameter	8
3	Signal-Processing Specific API Conventions	9
3.1	Signal Data	10
3.1.1	Parameter Names for Signal Data	10
3.1.1.1	Source Signal Pointer	10
3.1.1.2	Destination Signal Pointer	10
3.1.1.3	In-Place Signal Pointer	10
3.1.2	Signal Data Alignment Requirements	11
3.1.3	Signal Data Related Error Codes	11
3.2	Signal Length	11
3.2.1	Length Related Error Codes	11
4	Imaging-Processing Specific API Conventions	13

4.1	Function Naming	14
4.2	Image Data	14
4.2.1	Line Step	15
4.2.2	Parameter Names for Image Data	15
4.2.2.1	Passing Source-Image Data	15
4.2.2.2	Passing Destination-Image Data	16
4.2.2.3	Passing In-Place Image Data	18
4.2.2.4	Passing Mask-Image Data	18
4.2.2.5	Passing Channel-of-Interest Data	18
4.2.3	Image Data Alignment Requirements	18
4.2.4	Image Data Related Error Codes	19
4.3	Region-of-Interest (ROI)	19
4.3.1	ROI Related Error Codes	19
4.4	Masked Operation	20
4.5	Channel-of-Interest API	20
4.5.1	Select-Channel Source-Image Pointer	20
4.5.2	Select-Channel Source-Image	20
4.5.3	Select-Channel Destination-Image Pointer	20
4.6	Source-Image Sampling	21
4.6.1	Point-Wise Operations	21
4.6.2	Neighborhood Operations	21
4.6.2.1	Mask-Size Parameter	21
4.6.2.2	Anchor-Point Parameter	22
4.6.2.3	Sampling Beyond Image Boundaries	22
5	Module Index	23
5.1	Modules	23
6	Data Structure Index	25
6.1	Data Structures	25
7	Module Documentation	27
7.1	NPP Core	27
7.1.1	Detailed Description	28
7.1.2	Function Documentation	28
7.1.2.1	nppGetGpuComputeCapability	28
7.1.2.2	nppGetGpuDeviceProperties	28
7.1.2.3	nppGetGpuName	28

7.1.2.4	nppGetGpuNumSMs	28
7.1.2.5	nppGetLibVersion	29
7.1.2.6	nppGetMaxThreadsPerBlock	29
7.1.2.7	nppGetMaxThreadsPerSM	29
7.1.2.8	nppGetStream	29
7.1.2.9	nppGetStreamMaxThreadsPerSM	29
7.1.2.10	nppGetStreamNumSMs	29
7.1.2.11	nppSetStream	30
7.2	NPP Type Definitions and Constants	31
7.2.1	Define Documentation	37
7.2.1.1	NPP_MAX_16S	37
7.2.1.2	NPP_MAX_16U	37
7.2.1.3	NPP_MAX_32S	37
7.2.1.4	NPP_MAX_32U	37
7.2.1.5	NPP_MAX_64S	37
7.2.1.6	NPP_MAX_64U	37
7.2.1.7	NPP_MAX_8S	37
7.2.1.8	NPP_MAX_8U	37
7.2.1.9	NPP_MAXABS_32F	37
7.2.1.10	NPP_MAXABS_64F	37
7.2.1.11	NPP_MIN_16S	38
7.2.1.12	NPP_MIN_16U	38
7.2.1.13	NPP_MIN_32S	38
7.2.1.14	NPP_MIN_32U	38
7.2.1.15	NPP_MIN_64S	38
7.2.1.16	NPP_MIN_64U	38
7.2.1.17	NPP_MIN_8S	38
7.2.1.18	NPP_MIN_8U	38
7.2.1.19	NPP_MINABS_32F	38
7.2.1.20	NPP_MINABS_64F	38
7.2.2	Enumeration Type Documentation	38
7.2.2.1	NppCmpOp	38
7.2.2.2	NppGpuComputeCapability	39
7.2.2.3	NppHintAlgorithm	39
7.2.2.4	NppiAlphaOp	39
7.2.2.5	NppiAxis	40

7.2.2.6	NppiBayerGridPosition	40
7.2.2.7	NppiBorderType	40
7.2.2.8	NppiDifferentialKernel	40
7.2.2.9	NppiHuffmanTableType	41
7.2.2.10	NppiInterpolationMode	41
7.2.2.11	NppiMaskSize	41
7.2.2.12	NppiNorm	42
7.2.2.13	NppRoundMode	42
7.2.2.14	NppStatus	43
7.2.2.15	NppsZCType	45
7.3	Basic NPP Data Types	46
7.3.1	Typedef Documentation	47
7.3.1.1	Npp16s	47
7.3.1.2	Npp16u	47
7.3.1.3	Npp32f	47
7.3.1.4	Npp32fc	47
7.3.1.5	Npp32s	47
7.3.1.6	Npp32sc	48
7.3.1.7	Npp32u	48
7.3.1.8	Npp32uc	48
7.3.1.9	Npp64f	48
7.3.1.10	Npp64fc	48
7.3.1.11	Npp64s	48
7.3.1.12	Npp64sc	48
7.3.1.13	Npp64u	48
7.3.1.14	Npp8s	48
7.3.1.15	Npp8u	48
7.3.2	Function Documentation	48
7.3.2.1	__align__	48
7.3.2.2	__align__	49
7.3.3	Variable Documentation	49
7.3.3.1	Npp16sc	49
7.3.3.2	Npp16uc	49
7.3.3.3	Npp8uc	49
7.4	Threshold and Compare Operations	50
7.4.1	Detailed Description	50

7.5	Threshold Operations	51
7.5.1	Detailed Description	65
7.5.2	Function Documentation	65
7.5.2.1	nppiThreshold_16s_AC4IR	65
7.5.2.2	nppiThreshold_16s_AC4R	65
7.5.2.3	nppiThreshold_16s_C1IR	66
7.5.2.4	nppiThreshold_16s_C1R	66
7.5.2.5	nppiThreshold_16s_C3IR	67
7.5.2.6	nppiThreshold_16s_C3R	67
7.5.2.7	nppiThreshold_16u_AC4IR	68
7.5.2.8	nppiThreshold_16u_AC4R	68
7.5.2.9	nppiThreshold_16u_C1IR	69
7.5.2.10	nppiThreshold_16u_C1R	69
7.5.2.11	nppiThreshold_16u_C3IR	69
7.5.2.12	nppiThreshold_16u_C3R	70
7.5.2.13	nppiThreshold_32f_AC4IR	70
7.5.2.14	nppiThreshold_32f_AC4R	71
7.5.2.15	nppiThreshold_32f_C1IR	71
7.5.2.16	nppiThreshold_32f_C1R	72
7.5.2.17	nppiThreshold_32f_C3IR	72
7.5.2.18	nppiThreshold_32f_C3R	73
7.5.2.19	nppiThreshold_8u_AC4IR	73
7.5.2.20	nppiThreshold_8u_AC4R	74
7.5.2.21	nppiThreshold_8u_C1IR	74
7.5.2.22	nppiThreshold_8u_C1R	75
7.5.2.23	nppiThreshold_8u_C3IR	75
7.5.2.24	nppiThreshold_8u_C3R	76
7.5.2.25	nppiThreshold_GT_16s_AC4IR	76
7.5.2.26	nppiThreshold_GT_16s_AC4R	76
7.5.2.27	nppiThreshold_GT_16s_C1IR	77
7.5.2.28	nppiThreshold_GT_16s_C1R	77
7.5.2.29	nppiThreshold_GT_16s_C3IR	78
7.5.2.30	nppiThreshold_GT_16s_C3R	78
7.5.2.31	nppiThreshold_GT_16u_AC4IR	78
7.5.2.32	nppiThreshold_GT_16u_AC4R	79
7.5.2.33	nppiThreshold_GT_16u_C1IR	79

7.5.2.34	nppiThreshold_GT_16u_C1R	80
7.5.2.35	nppiThreshold_GT_16u_C3IR	80
7.5.2.36	nppiThreshold_GT_16u_C3R	80
7.5.2.37	nppiThreshold_GT_32f_AC4IR	81
7.5.2.38	nppiThreshold_GT_32f_AC4R	81
7.5.2.39	nppiThreshold_GT_32f_C1IR	82
7.5.2.40	nppiThreshold_GT_32f_C1R	82
7.5.2.41	nppiThreshold_GT_32f_C3IR	82
7.5.2.42	nppiThreshold_GT_32f_C3R	83
7.5.2.43	nppiThreshold_GT_8u_AC4IR	83
7.5.2.44	nppiThreshold_GT_8u_AC4R	84
7.5.2.45	nppiThreshold_GT_8u_C1IR	84
7.5.2.46	nppiThreshold_GT_8u_C1R	84
7.5.2.47	nppiThreshold_GT_8u_C3IR	85
7.5.2.48	nppiThreshold_GT_8u_C3R	85
7.5.2.49	nppiThreshold_GTVVal_16s_AC4IR	86
7.5.2.50	nppiThreshold_GTVVal_16s_AC4R	86
7.5.2.51	nppiThreshold_GTVVal_16s_C1IR	86
7.5.2.52	nppiThreshold_GTVVal_16s_C1R	87
7.5.2.53	nppiThreshold_GTVVal_16s_C3IR	87
7.5.2.54	nppiThreshold_GTVVal_16s_C3R	88
7.5.2.55	nppiThreshold_GTVVal_16u_AC4IR	88
7.5.2.56	nppiThreshold_GTVVal_16u_AC4R	88
7.5.2.57	nppiThreshold_GTVVal_16u_C1IR	89
7.5.2.58	nppiThreshold_GTVVal_16u_C1R	89
7.5.2.59	nppiThreshold_GTVVal_16u_C3IR	90
7.5.2.60	nppiThreshold_GTVVal_16u_C3R	90
7.5.2.61	nppiThreshold_GTVVal_32f_AC4IR	91
7.5.2.62	nppiThreshold_GTVVal_32f_AC4R	91
7.5.2.63	nppiThreshold_GTVVal_32f_C1IR	91
7.5.2.64	nppiThreshold_GTVVal_32f_C1R	92
7.5.2.65	nppiThreshold_GTVVal_32f_C3IR	92
7.5.2.66	nppiThreshold_GTVVal_32f_C3R	93
7.5.2.67	nppiThreshold_GTVVal_8u_AC4IR	93
7.5.2.68	nppiThreshold_GTVVal_8u_AC4R	93
7.5.2.69	nppiThreshold_GTVVal_8u_C1IR	94

7.5.2.70	nppiThreshold_GTVal_8u_C1R	94
7.5.2.71	nppiThreshold_GTVal_8u_C3IR	95
7.5.2.72	nppiThreshold_GTVal_8u_C3R	95
7.5.2.73	nppiThreshold_LT_16s_AC4IR	96
7.5.2.74	nppiThreshold_LT_16s_AC4R	96
7.5.2.75	nppiThreshold_LT_16s_C1IR	96
7.5.2.76	nppiThreshold_LT_16s_C1R	97
7.5.2.77	nppiThreshold_LT_16s_C3IR	97
7.5.2.78	nppiThreshold_LT_16s_C3R	98
7.5.2.79	nppiThreshold_LT_16u_AC4IR	98
7.5.2.80	nppiThreshold_LT_16u_AC4R	98
7.5.2.81	nppiThreshold_LT_16u_C1IR	99
7.5.2.82	nppiThreshold_LT_16u_C1R	99
7.5.2.83	nppiThreshold_LT_16u_C3IR	100
7.5.2.84	nppiThreshold_LT_16u_C3R	100
7.5.2.85	nppiThreshold_LT_32f_AC4IR	100
7.5.2.86	nppiThreshold_LT_32f_AC4R	101
7.5.2.87	nppiThreshold_LT_32f_C1IR	101
7.5.2.88	nppiThreshold_LT_32f_C1R	102
7.5.2.89	nppiThreshold_LT_32f_C3IR	102
7.5.2.90	nppiThreshold_LT_32f_C3R	102
7.5.2.91	nppiThreshold_LT_8u_AC4IR	103
7.5.2.92	nppiThreshold_LT_8u_AC4R	103
7.5.2.93	nppiThreshold_LT_8u_C1IR	104
7.5.2.94	nppiThreshold_LT_8u_C1R	104
7.5.2.95	nppiThreshold_LT_8u_C3IR	104
7.5.2.96	nppiThreshold_LT_8u_C3R	105
7.5.2.97	nppiThreshold_LTVAl_16s_AC4IR	105
7.5.2.98	nppiThreshold_LTVAl_16s_AC4R	106
7.5.2.99	nppiThreshold_LTVAl_16s_C1IR	106
7.5.2.100	nppiThreshold_LTVAl_16s_C1R	106
7.5.2.101	nppiThreshold_LTVAl_16s_C3IR	107
7.5.2.102	nppiThreshold_LTVAl_16s_C3R	107
7.5.2.103	nppiThreshold_LTVAl_16u_AC4IR	108
7.5.2.104	nppiThreshold_LTVAl_16u_AC4R	108
7.5.2.105	nppiThreshold_LTVAl_16u_C1IR	109

7.5.2.106	nppiThreshold_LTVVal_16u_C1R	109
7.5.2.107	nppiThreshold_LTVVal_16u_C3IR	109
7.5.2.108	nppiThreshold_LTVVal_16u_C3R	110
7.5.2.109	nppiThreshold_LTVVal_32f_AC4IR	110
7.5.2.110	nppiThreshold_LTVVal_32f_AC4R	111
7.5.2.111	nppiThreshold_LTVVal_32f_C1IR	111
7.5.2.112	nppiThreshold_LTVVal_32f_C1R	111
7.5.2.113	nppiThreshold_LTVVal_32f_C3IR	112
7.5.2.114	nppiThreshold_LTVVal_32f_C3R	112
7.5.2.115	nppiThreshold_LTVVal_8u_AC4IR	113
7.5.2.116	nppiThreshold_LTVVal_8u_AC4R	113
7.5.2.117	nppiThreshold_LTVVal_8u_C1IR	114
7.5.2.118	nppiThreshold_LTVVal_8u_C1R	114
7.5.2.119	nppiThreshold_LTVVal_8u_C3IR	114
7.5.2.120	nppiThreshold_LTVVal_8u_C3R	115
7.5.2.121	nppiThreshold_LTVValGTVal_16s_AC4IR	115
7.5.2.122	nppiThreshold_LTVValGTVal_16s_AC4R	116
7.5.2.123	nppiThreshold_LTVValGTVal_16s_C1IR	116
7.5.2.124	nppiThreshold_LTVValGTVal_16s_C1R	117
7.5.2.125	nppiThreshold_LTVValGTVal_16s_C3IR	117
7.5.2.126	nppiThreshold_LTVValGTVal_16s_C3R	118
7.5.2.127	nppiThreshold_LTVValGTVal_16u_AC4IR	118
7.5.2.128	nppiThreshold_LTVValGTVal_16u_AC4R	119
7.5.2.129	nppiThreshold_LTVValGTVal_16u_C1IR	119
7.5.2.130	nppiThreshold_LTVValGTVal_16u_C1R	120
7.5.2.131	nppiThreshold_LTVValGTVal_16u_C3IR	120
7.5.2.132	nppiThreshold_LTVValGTVal_16u_C3R	121
7.5.2.133	nppiThreshold_LTVValGTVal_32f_AC4IR	121
7.5.2.134	nppiThreshold_LTVValGTVal_32f_AC4R	122
7.5.2.135	nppiThreshold_LTVValGTVal_32f_C1IR	122
7.5.2.136	nppiThreshold_LTVValGTVal_32f_C1R	123
7.5.2.137	nppiThreshold_LTVValGTVal_32f_C3IR	123
7.5.2.138	nppiThreshold_LTVValGTVal_32f_C3R	124
7.5.2.139	nppiThreshold_LTVValGTVal_8u_AC4IR	124
7.5.2.140	nppiThreshold_LTVValGTVal_8u_AC4R	125
7.5.2.141	nppiThreshold_LTVValGTVal_8u_C1IR	125

7.5.2.142	<code>nppiThreshold_LTVaGTVa_8u_C1R</code>	126
7.5.2.143	<code>nppiThreshold_LTVaGTVa_8u_C3IR</code>	126
7.5.2.144	<code>nppiThreshold_LTVaGTVa_8u_C3R</code>	127
7.5.2.145	<code>nppiThreshold_Val_16s_AC4IR</code>	127
7.5.2.146	<code>nppiThreshold_Val_16s_AC4R</code>	128
7.5.2.147	<code>nppiThreshold_Val_16s_C1IR</code>	128
7.5.2.148	<code>nppiThreshold_Val_16s_C1R</code>	129
7.5.2.149	<code>nppiThreshold_Val_16s_C3IR</code>	129
7.5.2.150	<code>nppiThreshold_Val_16s_C3R</code>	130
7.5.2.151	<code>nppiThreshold_Val_16u_AC4IR</code>	130
7.5.2.152	<code>nppiThreshold_Val_16u_AC4R</code>	131
7.5.2.153	<code>nppiThreshold_Val_16u_C1IR</code>	131
7.5.2.154	<code>nppiThreshold_Val_16u_C1R</code>	132
7.5.2.155	<code>nppiThreshold_Val_16u_C3IR</code>	132
7.5.2.156	<code>nppiThreshold_Val_16u_C3R</code>	133
7.5.2.157	<code>nppiThreshold_Val_32f_AC4IR</code>	133
7.5.2.158	<code>nppiThreshold_Val_32f_AC4R</code>	134
7.5.2.159	<code>nppiThreshold_Val_32f_C1IR</code>	134
7.5.2.160	<code>nppiThreshold_Val_32f_C1R</code>	135
7.5.2.161	<code>nppiThreshold_Val_32f_C3IR</code>	135
7.5.2.162	<code>nppiThreshold_Val_32f_C3R</code>	136
7.5.2.163	<code>nppiThreshold_Val_8u_AC4IR</code>	136
7.5.2.164	<code>nppiThreshold_Val_8u_AC4R</code>	137
7.5.2.165	<code>nppiThreshold_Val_8u_C1IR</code>	137
7.5.2.166	<code>nppiThreshold_Val_8u_C1R</code>	138
7.5.2.167	<code>nppiThreshold_Val_8u_C3IR</code>	138
7.5.2.168	<code>nppiThreshold_Val_8u_C3R</code>	139
7.6	Compare Operations	140
7.6.1	Detailed Description	143
7.6.2	Function Documentation	143
7.6.2.1	<code>nppiCompare_16s_AC4R</code>	143
7.6.2.2	<code>nppiCompare_16s_C1R</code>	144
7.6.2.3	<code>nppiCompare_16s_C3R</code>	144
7.6.2.4	<code>nppiCompare_16s_C4R</code>	145
7.6.2.5	<code>nppiCompare_16u_AC4R</code>	145
7.6.2.6	<code>nppiCompare_16u_C1R</code>	146

7.6.2.7	nppiCompare_16u_C3R	146
7.6.2.8	nppiCompare_16u_C4R	147
7.6.2.9	nppiCompare_32f_AC4R	147
7.6.2.10	nppiCompare_32f_C1R	148
7.6.2.11	nppiCompare_32f_C3R	148
7.6.2.12	nppiCompare_32f_C4R	149
7.6.2.13	nppiCompare_8u_AC4R	149
7.6.2.14	nppiCompare_8u_C1R	150
7.6.2.15	nppiCompare_8u_C3R	150
7.6.2.16	nppiCompare_8u_C4R	151
7.6.2.17	nppiCompareC_16s_AC4R	151
7.6.2.18	nppiCompareC_16s_C1R	151
7.6.2.19	nppiCompareC_16s_C3R	152
7.6.2.20	nppiCompareC_16s_C4R	152
7.6.2.21	nppiCompareC_16u_AC4R	153
7.6.2.22	nppiCompareC_16u_C1R	153
7.6.2.23	nppiCompareC_16u_C3R	154
7.6.2.24	nppiCompareC_16u_C4R	154
7.6.2.25	nppiCompareC_32f_AC4R	154
7.6.2.26	nppiCompareC_32f_C1R	155
7.6.2.27	nppiCompareC_32f_C3R	155
7.6.2.28	nppiCompareC_32f_C4R	156
7.6.2.29	nppiCompareC_8u_AC4R	156
7.6.2.30	nppiCompareC_8u_C1R	157
7.6.2.31	nppiCompareC_8u_C3R	157
7.6.2.32	nppiCompareC_8u_C4R	157
7.6.2.33	nppiCompareEqualEps_32f_AC4R	158
7.6.2.34	nppiCompareEqualEps_32f_C1R	158
7.6.2.35	nppiCompareEqualEps_32f_C3R	159
7.6.2.36	nppiCompareEqualEps_32f_C4R	159
7.6.2.37	nppiCompareEqualEpsC_32f_AC4R	160
7.6.2.38	nppiCompareEqualEpsC_32f_C1R	160
7.6.2.39	nppiCompareEqualEpsC_32f_C3R	161
7.6.2.40	nppiCompareEqualEpsC_32f_C4R	161
8	Data Structure Documentation	163
8.1	NPP_ALIGN_16 Struct Reference	163

8.1.1	Detailed Description	163
8.1.2	Field Documentation	163
8.1.2.1	im	163
8.1.2.2	im	164
8.1.2.3	re	164
8.1.2.4	re	164
8.2	NPP_ALIGN_8 Struct Reference	165
8.2.1	Detailed Description	165
8.2.2	Field Documentation	165
8.2.2.1	im	165
8.2.2.2	im	165
8.2.2.3	im	165
8.2.2.4	re	166
8.2.2.5	re	166
8.2.2.6	re	166
8.3	NppiHaarBuffer Struct Reference	167
8.3.1	Field Documentation	167
8.3.1.1	haarBuffer	167
8.3.1.2	haarBufferSize	167
8.4	NppiHaarClassifier_32f Struct Reference	168
8.4.1	Field Documentation	168
8.4.1.1	classifiers	168
8.4.1.2	classifierSize	168
8.4.1.3	classifierStep	168
8.4.1.4	counterDevice	168
8.4.1.5	numClassifiers	168
8.5	NppiPoint Struct Reference	169
8.5.1	Detailed Description	169
8.5.2	Field Documentation	169
8.5.2.1	x	169
8.5.2.2	y	169
8.6	NppiRect Struct Reference	170
8.6.1	Detailed Description	170
8.6.2	Field Documentation	170
8.6.2.1	height	170
8.6.2.2	width	170

8.6.2.3	x	170
8.6.2.4	y	170
8.7	NppiSize Struct Reference	171
8.7.1	Detailed Description	171
8.7.2	Field Documentation	171
8.7.2.1	height	171
8.7.2.2	width	171
8.8	NppLibraryVersion Struct Reference	172
8.8.1	Field Documentation	172
8.8.1.1	build	172
8.8.1.2	major	172
8.8.1.3	minor	172

Chapter 1

NVIDIA Performance Primitives

Note: Starting with release 6.5, NPP is also provided as a static library (`libnppc_static.a`, `libnppi_static.a`, and `libnpps_static.a`) on Linux, Android, and Mac OSes in addition to being provided as a shared library. The static NPP libraries depend on a common thread abstraction layer library called `cuLIBOS` (`libculibos.a`) that is now distributed as part of the toolkit. Consequently, `cuLIBOS` must be provided to the linker when the static library is being linked against. The `libnppi` library is becoming quite large so to minimize library loading and CUDA runtime startup times it is recommended to use the static library(s) whenever possible. To improve loading and runtime performance when using dynamic libraries NPP 8.0 now includes the full set of `nppi` sub-libraries in addition to the full sized `nppi` library itself. Linking to only the sub-libraries that contain functions that your application uses can significantly improve load time and runtime startup performance. Some `nppi` functions make calls to other `nppi` and/or `npps` functions internally so you may need to link to a few extra libraries depending on what function calls your application makes. The `nppi` sub-libraries are split into sections corresponding to the way that `nppi` header files are split. There are also static versions of each of the new sub-libraries. The full sized `nppi` library will be deprecated in the next CUDA release. This list of sub-libraries is as follows:

```
nppial arithmetic and logical operation functions in nppi_arithmetic_and_logical_operations.h
nppicc color conversion and sampling functions in nppi_color_conversion.h
nppicom JPEG compression and decompression functions in nppi_compression_functions.h
nppidei data exchange and initialization functions in nppi_data_exchange_and_initialization.h
nppif filtering and computer vision functions in nppi_filter_functions.h
nppig geometry transformation functions found in nppi_geometry_transforms.h
nppim morphological operation functions found in nppi_morphological_operations.h
nppist statistics and linear transform in nppi_statistics_functions.h and nppi_linear_transforms.h
nppisu memory support functions in nppi_support_functions.h
nppitc threshold and compare operation functions in nppi_threshold_and_compare_operations.h
```

For example, on Linux, to compile a small application `foo` using NPP against the dynamic library, the following command can be used:

```
nvcc foo.c -lnppi -o foo
```

Whereas to compile against the static NPP library, the following command has to be used:

```
nvcc foo.c -lnppi_static -lculibos -o foo
```

It is also possible to use the native host C++ compiler. Depending on the host operating system, some additional libraries like `pthread` or `dl` might be needed on the linking line. The following command on Linux is suggested:

```
g++ foo.c -lnppi_static -lculibos -lcudart_static -lpthread -ldl
-I <cuda-toolkit-path>/include -L <cuda-toolkit-path>/lib64 -o foo
```

NPP is a stateless API, as of NPP 6.5 the ONLY state that NPP remembers between function calls is the current stream ID, i.e. the stream ID that was set in the most recent `nppSetStream` call. The default stream ID is 0. If an application intends to use NPP with multiple streams then it is the responsibility of the application to call `nppSetStream` whenever it wishes to change stream IDs. Several NPP functions may call other NPP functions internally to complete their functionality. For this reason it is recommended that `cudaDeviceSynchronize` be called before making an `nppSetStream` call to change to a new stream ID. This will insure that any internal function calls that have not yet occurred will be completed using the current stream ID before it changes to a new ID. Calling `cudaDeviceSynchronize` frequently call kill performance so minimizing the frequency of these calls is critical for good performance. It is not necessary to call `cudaDeviceSynchronize` for stream management while the same stream ID is used for multiple NPP calls. All NPP functions should be thread safe except for the following functions:

```
nppiGraphcut_32s8u - this function has been deprecated in NPP 8.0
nppiGraphcut_32f8u - this function has been deprecated in NPP 8.0
nppiGraphcut8_32s8u - this function has been deprecated in NPP 8.0
nppiGraphcut8_32f8u - this function has been deprecated in NPP 8.0
nppiDCTQuantFwd8x8LS_JPEG_8u16s_C1R
nppiDCTQuantInv8x8LS_JPEG_16s8u_C1R
```

As of NPP version 5.0 and beyond a few parameters for a few pre-5.0 existing image LUT functions have changed from host memory pointers to device memory pointers. Your application will fail (crash or report an error) if you use these functions with host memory pointers. The functions are the `nppiLUT_Linear_8u_xxx` functions.

Also, pre-5.0 function `nppiMeanStdDev8uC1RGetBufferHostSize` has been renamed `nppiMeanStdDevGetBufferHostSize_8u_C1R`.

1.1 What is NPP?

NVIDIA NPP is a library of functions for performing CUDA accelerated processing. The initial set of functionality in the library focuses on imaging and video processing and is widely applicable for developers in these areas. NPP will evolve over time to encompass more of the compute heavy tasks in a variety of problem domains. The NPP library is written to maximize flexibility, while maintaining high performance.

NPP can be used in one of two ways:

- A stand-alone library for adding GPU acceleration to an application with minimal effort. Using this route allows developers to add GPU acceleration to their applications in a matter of hours.
- A cooperative library for interoperating with a developer's GPU code efficiently.

Either route allows developers to harness the massive compute resources of NVIDIA GPUs, while simultaneously reducing development times.

1.2 Documentation

- [General API Conventions](#)

- [Signal-Processing Specific API Conventions](#)
- [Imaging-Processing Specific API Conventions](#)

1.3 Technical Specifications

Supported Platforms:

- Microsoft Windows 7, 8, and 10 (64-bit and 32-bit)
- Microsoft Windows Vista (64-bit and 32-bit)
- Linux (Centos, Ubuntu, and several others) (64-bit and 32-bit)
- Mac OS X (64-bit)
- Android on Arm (32-bit and 64-bit)

1.4 Files

NPP is comprised of the following files:

1.4.1 Header Files

- [nppdefs.h](#)
- [nppcore.h](#)
- `nppi.h`
- `npps.h`
- [nppversion.h](#)
- `npp.h`

All these header files are located in the CUDA Toolkit's

```
/include/
```

directory.

1.4.2 Library Files

Starting with Version 5.5 NPP's functionality is now split up into 3 distinct libraries:

- A core library (NPPC) containing basic functionality from the `npp.h` header files as well as functionality shared by the other two libraries.
- The image processing library NPPI. Any functions from the `nppi.h` header file (or the various header files named "nppi_XXX.h") are bundled into the NPPI library.

- The signal processing library NPPS. Any function from the npps.h header file (or the various header files named "npps_XXX.h" are bundled into the NPPS library.

On the Windows platform the NPP stub libraries are found in the CUDA Toolkit's library directory:

```
/lib/nppc.lib
```

```
/lib/nppi.lib
```

```
/lib/npps.lib
```

The matching DLLs are located in the CUDA Toolkit's binary directory. Example

```
/bin/nppi64_55_<build_no>.dll // Dynamic image-processing library for 64-bit Windows.
```

On Linux and Mac platforms the dynamic libraries are located in the lib directory

```
/lib/libnppc32.so.5.5.<build_no> // NPP 32-bit dynamic core library for Linux
```

```
/lib/libnpps32.5.5.dylib // NPP 32-bit dynamic signal processing library for Mac
```

1.5 Supported NVIDIA Hardware

NPP runs on all CUDA capable NVIDIA hardware. For details please see http://www.nvidia.com/object/cuda_learn_products.html

Chapter 2

General API Conventions

2.1 Memory Management

The design of all the NPP functions follows the same guidelines as other NVIDIA CUDA libraries like cuFFT and cuBLAS. That is that all pointer arguments in those APIs are device pointers.

This convention enables the individual developer to make smart choices about memory management that minimize the number of memory transfers. It also allows the user the maximum flexibility regarding which of the various memory transfer mechanisms offered by the CUDA runtime is used, e.g. synchronous or asynchronous memory transfers, zero-copy and pinned memory, etc.

The most basic steps involved in using NPP for processing data is as follows:

1. Transfer input data from the host to device using

```
cudaMemcpy(...)
```

2. Process data using one or several NPP functions or custom CUDA kernels

3. Transfer the result data from the device to the host using

```
cudaMemcpy(...)
```

2.1.1 Scratch Buffer and Host Pointer

Some primitives of NPP require additional device memory buffers (scratch buffers) for calculations, e.g. signal and image reductions (Sum, Max, Min, MinMax, etc.). In order to give the NPP user maximum control regarding memory allocations and performance, it is the user's responsibility to allocate and delete those temporary buffers. For one this has the benefit that the library will not allocate memory unbeknownst to the user. It also allows developers who invoke the same primitive repeatedly to allocate the scratch only once, improving performance and potential device-memory fragmentation.

Scratch-buffer memory is unstructured and may be passed to the primitive in uninitialized form. This allows for reuse of the same scratch buffers with any primitive require scratch memory, as long as it is sufficiently sized.

The minimum scratch-buffer size for a given primitive (e.g. `nppsSum_32f()`) can be obtained by a companion function (e.g. `nppsSumGetBufferSize_32f()`). The buffer size is returned via a host pointer as allocation of the scratch-buffer is performed via CUDA runtime host code.

An example to invoke signal sum primitive and allocate and free the necessary scratch memory:

```
// pSrc, pSum, pDeviceBuffer are all device pointers.
Npp32f * pSrc;
Npp32f * pSum;
Npp8u * pDeviceBuffer;
int nLength = 1024;

// Allocate the device memroy.
cudaMalloc((void **)(&pSrc), sizeof(Npp32f) * nLength);
nppsSet_32f(1.0f, pSrc, nLength);
cudaMalloc((void **)(&pSum), sizeof(Npp32f) * 1);

// Compute the appropriate size of the scratch-memory buffer
int nBufferSize;
nppsSumGetBufferSize_32f(nLength, &nBufferSize);
// Allocate the scratch buffer
cudaMalloc((void **)(&pDeviceBuffer), nBufferSize);

// Call the primitive with the scratch buffer
```

```

nppsSum_32f(pSrc, nLength, pSum, pDeviceBuffer);
Npp32f nSumHost;
cudaMemcpy(&nSumHost, pSum, sizeof(Npp32f) * 1, cudaMemcpyDeviceToHost);
printf("sum = %f\n", nSumHost); // nSumHost = 1024.0f;

// Free the device memory
cudaFree(pSrc);
cudaFree(pDeviceBuffer);
cudaFree(pSum);

```

2.2 Function Naming

Since NPP is a C API and therefore does not allow for function overloading for different data-types the NPP naming convention addresses the need to differentiate between different flavors of the same algorithm or primitive function but for various data types. This disambiguation of different flavors of a primitive is done via a suffix containing data type and other disambiguating information.

In addition to the flavor suffix, all NPP functions are prefixed with by the letters "npp". Primitives belonging to NPP's image-processing module add the letter "i" to the npp prefix, i.e. are prefixed by "nppi". Similarly signal-processing primitives are prefixed with "npps".

The general naming scheme is:

```
npp<module info><PrimitiveName>_<data-type info>[_<additional flavor info>](<parameter list>)
```

The data-type information uses the same names as the [Basic NPP Data Types](#). For example the data-type information "8u" would imply that the primitive operates on [Npp8u](#) data.

If a primitive consumes different type data from what it produces, both types will be listed in the order of consumed to produced data type.

Details about the "additional flavor information" is provided for each of the NPP modules, since each problem domain uses different flavor information suffixes.

2.3 Integer Result Scaling

NPP signal processing and imaging primitives often operate on integer data. This integer data is usually a fixed point fractional representation of some physical magnitue (e.g. luminance). Because of this fixed-point nature of the representation many numerical operations (e.g. addition or multiplication) tend to produce results exceeding the original fixed-point range if treated as regular integers.

In cases where the results exceed the original range, these functions clamp the result values back to the valid range. E.g. the maximum positive value for a 16-bit unsigned integer is 32767. A multiplication operation of $4 * 10000 = 40000$ would exceed this range. The result would be clamped to be 32767.

To avoid the level of lost information due to clamping most integer primitives allow for result scaling. Primitives with result scaling have the "Sfs" suffix in their name and provide a parameter "nScaleFactor" that controls the amount of scaling. Before the results of an operation are clamped to the valid output-data range by multiplying them with $2^{-nScaleFactor}$.

Example: The primitive `nppsSqr_8u_Sfs()` computes the square of 8-bit unsigned sample values in a signal (1D array of values). The maximum value of a 8-bit value is 255. The square of $255^2 = 65025$ which would be clamped to 255 if no result scaling is performed. In order to map the maximum value of 255 to 255 in the result, one would specify an integer result scaling factor of 8, i.e. multiply each result with $2^{-8} = \frac{1}{2^8} = \frac{1}{256}$. The final result for a signal value of 255 being squared and scaled would be:

$$255^2 \cdot 2^{-8} = 254.00390625$$

which would be rounded to a final result of 254.

A medium gray value of 128 would result in

$$128^2 * 2^{-8} = 64$$

2.4 Rounding Modes

Many NPP functions require converting floating-point values to integers. The [NppRoundMode](#) enum lists NPP's supported rounding modes. Not all primitives in NPP that perform rounding as part of their functionality allow the user to specify the round-mode used. Instead they use NPP's default rounding mode, which is [NPP_RND_FINANCIAL](#).

2.4.1 Rounding Mode Parameter

A subset of NPP functions performing rounding as part of their functionality do allow the user to specify which rounding mode is used through a parameter of the [NppRoundMode](#) type.

Chapter 3

Signal-Processing Specific API Conventions

3.1 Signal Data

Signal data is passed to and from NPPS primitives via a pointer to the signal's data type.

The general idea behind this fairly low-level way of passing signal data is ease-of-adoption into existing software projects:

- Passing the data pointer rather than a higher-level signal struct allows for easy adoption by not requiring a specific signal representation (that could include total signal size offset, or other additional information). This avoids awkward packing and unpacking of signal data from the host application to an NPP specific signal representation.

3.1.1 Parameter Names for Signal Data

There are three general cases of image-data passing throughout NPP detailed in the following sections.

Those are signals consumed by the algorithm.

3.1.1.1 Source Signal Pointer

The source signal data is generally passed via a pointer named

```
pSrc
```

The source signal pointer is generally defined constant, enforcing that the primitive does not change any image data pointed to by that pointer. E.g.

```
nppsPrimitive_32s(const Npp32s * pSrc, ...)
```

In case the primitive consumes multiple signals as inputs the source pointers are numbered like this:

```
pSrc1, pSrc2, ...
```

3.1.1.2 Destination Signal Pointer

The destination signal data is generally passed via a pointer named

```
pDst
```

In case the primitive consumes multiple signals as inputs the source pointers are numbered like this:

```
pDst1, pDst2, ...
```

3.1.1.3 In-Place Signal Pointer

In the case of in-place processing, source and destination are served by the same pointer and thus pointers to in-place signal data are called:

```
pSrcDst
```

3.1.2 Signal Data Alignment Requirements

NPP requires signal sample data to be naturally aligned, i.e. any pointer

```
NppType * p;
```

to a sample in a signal needs to fulfill:

```
assert(p % sizeof(p) == 0);
```

3.1.3 Signal Data Related Error Codes

All NPPI primitives operating on signal data validate the signal-data pointer for proper alignment and test that the point is not null.

Failed validation results in one of the following error codes being returned and the primitive not being executed:

- [NPP_NULL_POINTER_ERROR](#) is returned if the image-data pointer is 0 (NULL).
- [NPP_ALIGNMENT_ERROR](#) if the signal-data pointer address is not a multiple of the signal's data-type size.

3.2 Signal Length

The vast majority of NPPS functions take a

```
nLength
```

parameter that tells the primitive how many of the signal's samples starting from the given data pointer are to be processed.

3.2.1 Length Related Error Codes

All NPPS primitives taking a length parameter validate this input.

Failed validation results in the following error code being returned and the primitive not being executed:

- [NPP_SIZE_ERROR](#) is returned if the length is negative.

Chapter 4

Imaging-Processing Specific API Conventions

4.1 Function Naming

Image processing related functions use a number of suffixes to indicate various different flavors of a primitive beyond just different data types. The flavor suffix uses the following abbreviations:

- "A" if the image is a 4 channel image this indicates the result alpha channel is not affected by the primitive.
- "Cn" the image consists of n channel packed pixels, where n can be 1, 2, 3 or 4.
- "Pn" the image consists of n separate image planes, where n can be 1, 2, 3 or 4.
- "C" (following the channel information) indicates that the primitive only operates on one of the color channels, the "channel-of-interest". All other output channels are not affected by the primitive.
- "I" indicates that the primitive works "in-place". In this case the image-data pointer is usually named "pSrcDst" to indicate that the image data serves as source and destination at the same time.
- "M" indicates "masked operation". These types of primitives have an additional "mask image" as input. Each pixel in the destination image corresponds to a pixel in the mask image. Only pixels with a corresponding non-zero mask pixel are being processed.
- "R" indicates the primitive operates only on a rectangular "region-of-interest" or "ROI". All ROI primitives take an additional input parameter of type [NppiSize](#), which specifies the width and height of the rectangular region that the primitive should process. For details on how primitives operate on ROIs see: [Region-of-Interest \(ROI\)](#).
- "Sfs" indicates the result values are processed by fixed scaling and saturation before they're written out.

The suffixes above always appear in alphabetical order. E.g. a 4 channel primitive not affecting the alpha channel with masked operation, in place and with scaling/saturation and ROI would have the postfix: "AC4IMRSfs".

4.2 Image Data

Image data is passed to and from NPPI primitives via a pair of parameters:

1. A pointer to the image's underlying data type.
2. A line step in bytes (also sometimes called line stride).

The general idea behind this fairly low-level way of passing image data is ease-of-adoption into existing software projects:

- Passing a raw pointer to the underlying pixel data type, rather than structured (by color) channel pixel data allows usage of the function in a wide variety of situations avoiding risky type cast or expensive image data copies.
- Passing the data pointer and line step individually rather than a higher-level image struct again allows for easy adoption by not requiring a specific image representation and thus avoiding awkward packing and unpacking of image data from the host application to an NPP specific image representation.

4.2.1 Line Step

The line step (also called "line stride" or "row step") allows lines of oddly sized images to start on well-aligned addresses by adding a number of unused bytes at the ends of the lines. This type of line padding has been common practice in digital image processing for a long time and is not particular to GPU image processing.

The line step is the number of bytes in a line **including the padding**. An other way to interpret this number is to say that it is the number of bytes between the first pixel of successive rows in the image, or generally the number of bytes between two neighboring pixels in any column of pixels.

The general reason for the existence of the line step it is that uniformly aligned rows of pixel enable optimizations of memory-access patterns.

Even though all functions in NPP will work with arbitrarily aligned images, best performance can only be achieved with well aligned image data. Any image data allocated with the NPP image allocators or the 2D memory allocators in the CUDA runtime, is well aligned.

Particularly on older CUDA capable GPUs it is likely that the performance decrease for misaligned data is substantial (orders of magnitude).

All image data passed to NPPI primitives requires a line step to be provided. It is important to keep in mind that this line step is always specified in terms of bytes, not pixels.

4.2.2 Parameter Names for Image Data

There are three general cases of image-data passing throughout NPP detailed in the following sections.

4.2.2.1 Passing Source-Image Data

Those are images consumed by the algorithm.

4.2.2.1.1 Source-Image Pointer

The source image data is generally passed via a pointer named

```
pSrc
```

The source image pointer is generally defined constant, enforcing that the primitive does not change any image data pointed to by that pointer. E.g.

```
nppiPrimitive_32s_C1R(const Npp32s * pSrc, ...)
```

In case the primitive consumes multiple images as inputs the source pointers are numbered like this:

```
pSrc1, pSrc2, ...
```

4.2.2.1.2 Source-Planar-Image Pointer Array

The planar source image data is generally passed via an array of pointers named

```
pSrc[]
```

The planar source image pointer array is generally defined a constant array of constant pointers, enforcing that the primitive does not change any image data pointed to by those pointers. E.g.

```
nppiPrimitive_8u_P3R(const Npp8u * const pSrc[3], ...)
```

Each pointer in the array points to a different image plane.

4.2.2.1.3 Source-Planar-Image Pointer

The multiple plane source image data is passed via a set of pointers named

```
pSrc1, pSrc2, ...
```

The planar source image pointer is generally defined as one of a set of constant pointers with each pointer pointing to a different input image plane.

4.2.2.1.4 Source-Image Line Step

The source image line step is the number of bytes between successive rows in the image. The source image line step parameter is

```
nSrcStep
```

or in the case of multiple source images

```
nSrcStep1, nSrcStep2, ...
```

4.2.2.1.5 Source-Planar-Image Line Step Array

The source planar image line step array is an array where each element of the array contains the number of bytes between successive rows for a particular plane in the input image. The source planar image line step array parameter is

```
rSrcStep[]
```

4.2.2.1.6 Source-Planar-Image Line Step

The source planar image line step is the number of bytes between successive rows in a particular plane of the multiplane input image. The source planar image line step parameter is

```
nSrcStep1, nSrcStep2, ...
```

4.2.2.2 Passing Destination-Image Data

Those are images produced by the algorithm.

4.2.2.2.1 Destination-Image Pointer

The destination image data is generally passed via a pointer named

```
pDst
```

In case the primitive generates multiple images as outputs the destination pointers are numbered like this:

```
pDst1, pDst2, ...
```

4.2.2.2.2 Destination-Planar-Image Pointer Array

The planar destination image data pointers are generally passed via an array of pointers named

```
pDst[]
```

Each pointer in the array points to a different image plane.

4.2.2.2.3 Destination-Planar-Image Pointer

The destination planar image data is generally passed via a pointer to each plane of a multiplane output image named

```
pDst1, pDst2, ...
```

4.2.2.2.4 Destination-Image Line Step

The destination image line step parameter is

```
nDstStep
```

or in the case of multiple destination images

```
nDstStep1, nDstStep2, ...
```

4.2.2.2.5 Destination-Planar-Image Line Step Array

The destination planar image line step array is an array where each element of the array contains the number of bytes between successive rows for a particular plane in the output image. The destination planar image line step array parameter is

```
rDstStep[]
```

4.2.2.2.6 Destination-Planar-Image Line Step

The destination planar image line step is the number of bytes between successive rows for a particular plane in a multiplane output image. The destination planar image line step parameter is

```
nDstStep1, nDstStep2, ...
```

4.2.2.3 Passing In-Place Image Data

4.2.2.3.1 In-Place Image Pointer

In the case of in-place processing, source and destination are served by the same pointer and thus pointers to in-place image data are called:

```
pSrcDst
```

4.2.2.3.2 In-Place-Image Line Step

The in-place line step parameter is

```
nSrcDstStep
```

4.2.2.4 Passing Mask-Image Data

Some image processing primitives have variants supporting [Masked Operation](#).

4.2.2.4.1 Mask-Image Pointer

The mask-image data is generally passed via a pointer named

```
pMask
```

4.2.2.4.2 Mask-Image Line Step

The mask-image line step parameter is

```
nMaskStep
```

4.2.2.5 Passing Channel-of-Interest Data

Some image processing primitives support [Channel-of-Interest API](#).

4.2.2.5.1 Channel_of_Interest Number

The channel-of-interest data is generally an integer (either 1, 2, or 3):

```
nCOI
```

4.2.3 Image Data Alignment Requirements

NPP requires pixel data to adhere to certain alignment constraints: For 2 and 4 channel images the following alignment requirement holds: `data_pointer % (#channels * sizeof(channel type)) == 0`. E.g. a 4 channel image with underlying type [Npp8u](#) (8-bit unsigned) would require all pixels to fall on addresses that are multiples of 4 (4 channels * 1 byte size).

As a logical consequence of all pixels being aligned to their natural size the image line steps of 2 and 4 channel images also need to be multiples of the pixel size.

1 and 3 channel images only require that pixel pointers are aligned to the underlying data type, i.e. `pData % sizeof(data type) == 0`. And consequentially line steps are also held to this requirement.

4.2.4 Image Data Related Error Codes

All NPPI primitives operating on image data validate the image-data pointer for proper alignment and test that the point is not null. They also validate the line stride for proper alignment and guard against the step being less or equal to 0. Failed validation results in one of the following error codes being returned and the primitive not being executed:

- `NPP_STEP_ERROR` is returned if the data step is 0 or negative.
- `NPP_NOT_EVEN_STEP_ERROR` is returned if the line step is not a multiple of the pixel size for 2 and 4 channel images.
- `NPP_NULL_POINTER_ERROR` is returned if the image-data pointer is 0 (NULL).
- `NPP_ALIGNMENT_ERROR` if the image-data pointer address is not a multiple of the pixel size for 2 and 4 channel images.

4.3 Region-of-Interest (ROI)

In practice processing a rectangular sub-region of an image is often more common than processing complete images. The vast majority of NPPI's image-processing primitives allow for processing of such sub regions also referred to as regions-of-interest or ROIs.

All primitives supporting ROI processing are marked by a "R" in their name suffix. In most cases the ROI is passed as a single `NppiSize` struct, which provides the width and height of the ROI. This raises the question how the primitive knows where in the image this rectangle of (width, height) is located. The "start pixel" of the ROI is implicitly given by the image-data pointer. I.e. instead of explicitly passing a pixel coordinate for the upper-left corner (lowest memory address), the user simply offsets the image-data pointers to point to the first pixel of the ROI.

In practice this means that for an image (`pSrc`, `nSrcStep`) and the start-pixel of the ROI being at location (`x`, `y`), one would pass

```
pSrcOffset = pSrc + y * nSrcStep + x * PixelSize;
```

as the image-data source to the primitive. `PixelSize` is typically computed as

```
PixelSize = NumberOfColorChannels * sizeof(PixelDataType).
```

E.g. for a primitive like `nppiSet_16s_C4R()` we would have

- `NumberOfColorChannels == 4;`
- `sizeof(Npp16s) == 2;`
- and thus `PixelSize = 4 * 2 = 8;`

4.3.1 ROI Related Error Codes

All NPPI primitives operating on ROIs of image data validate the ROI size and image's step size. Failed validation results in one of the following error codes being returned and the primitive not being executed:

- `NPP_SIZE_ERROR` is returned if either the ROI width or ROI height are negative.
- `NPP_STEP_ERROR` is returned if the ROI width exceeds the image's line step. In mathematical terms $(\text{widthROI} * \text{PixelSize}) > \text{nLinStep}$ indicates an error.

4.4 Masked Operation

Some primitive support masked operation. An "M" in the suffix of those variants indicates masked operation. Primitives supporting masked operation consume an additional input image provided via a [Mask-Image Pointer](#) and [Mask-Image Line Step](#). The mask image is interpreted by these primitives as a boolean image. The values of type `Npp8u` are interpreted as boolean values where a values of 0 indicates false, any non-zero values true.

Unless otherwise indicated the operation is only performed on pixels where its spatially corresponding mask pixel is true (non-zero). E.g. a masked copy operation would only copy those pixels in the ROI that have corresponding non-zero mask pixels.

4.5 Channel-of-Interest API

Some primitives allow restricting operations to a single channel of interest within a multi-channel image. These primitives are suffixed with the letter "C" (after the channel information, e.g. `nppiCopy_8u_C3CR(...)`). The channel-of-interest is generally selected by offsetting the image-data pointer to point directly to the channel- of-interest rather than the base of the first pixel in the ROI. Some primitives also explicitly specify the selected channel number and pass it via an integer, e.g. `nppiMean_StdDev_8u_C3CR(...)`.

4.5.1 Select-Channel Source-Image Pointer

This is a pointer to the channel-of-interest within the first pixel of the source image. E.g. if `pSrc` is the pointer to the first pixel inside the ROI of a three channel image. Using the appropriate select-channel copy primitive one could copy the second channel of this source image into the first channel of a destination image given by `pDst` by offsetting the pointer by one:

```
nppiCopy_8u_C3CR(pSrc + 1, nSrcStep, pDst, nDstStep, oSizeROI);
```

4.5.2 Select-Channel Source-Image

Some primitives allow the user to select the channel-of-interest by specifying the channel number (`nCOI`). This approach is typically used in the image statistical functions. For example,

```
nppiMean_StdDev_8u_C3CR(pSrc, nSrcStep, oSizeROI, nCOI, pDeviceBuffer, pMean, pStdDev );
```

The channel-of-interest number can be either 1, 2, or 3.

4.5.3 Select-Channel Destination-Image Pointer

This is a pointer to the channel-of-interest within the first pixel of the destination image. E.g. if `pDst` is the pointer to the first pixel inside the ROI of a three channel image. Using the appropriate select-channel

copy primitive one could copy data into the second channel of this destination image from the first channel of a source image given by pSrc by offsetting the destination pointer by one:

```
nppiCopy_8u_C3CR(pSrc, nSrcStep, pDst + 1, nDstStep, oSizeROI);
```

4.6 Source-Image Sampling

A large number of NPP image-processing functions consume at least one source image and produce an output image (e.g. `nppiAddC_8u_C1RSfs()` or `nppiFilterBox_8u_C1R()`). All NPP functions falling into this category also operate on ROIs (see [Region-of-Interest \(ROI\)](#)) which for these functions should be considered to describe the destination ROI. In other words the ROI describes a rectangular region in the destination image and all pixels inside of this region are being written by the function in question.

In order to use such functions successfully it is important to understand how the user defined destination ROI affects which pixels in the input image(s) are being read by the algorithms. To simplify the discussion of ROI propagation (i.e. given a destination ROI, what are the ROIs in the source(s)), it makes sense to distinguish two major cases:

1. Point-Wise Operations: These are primitives like `nppiAddC_8u_C1RSfs()`. Each output pixel requires exactly one input pixel to be read.
2. Neighborhood Operations: These are primitives like `nppiFilterBox_8u_C1R()`, which require a group of pixels from the source image(s) to be read in order to produce a single output.

4.6.1 Point-Wise Operations

As mentioned above, point-wise operations consume a single pixel from the input image (or a single pixel from each input image, if the operation in question has more than one input image) in order to produce a single output pixel.

4.6.2 Neighborhood Operations

In the case of neighborhood operations a number of input pixels (a "neighborhood" of pixels) is read in the input image (or images) in order to compute a single output pixel. All of the functions for `image_filtering_functions` and `image_morphological_operations` are neighborhood operations.

Most of these functions have parameters that affect the size and relative location of the neighborhood: a mask-size structure and an anchor-point structure. Both parameters are described in more detail in the next subsections.

4.6.2.1 Mask-Size Parameter

Many NPP neighborhood operations allow the user to specify the size of the neighborhood via a parameter usually named `oMaskSize` of type `NppiSize`. In those cases the neighborhood of pixels read from the source(s) is exactly the size of the mask. Assuming the mask is anchored at location (0, 0) (see [Anchor-Point Parameter](#) below) and has a size of (w, h), i.e.

```
assert(oMaskSize.w == w);
assert(oMaskSize.h == h);
assert(oAnchor.x == 0);
assert(oAnchor.y == 0);
```

a neighborhood operation would read the following source pixels in order to compute destination pixel $D_{i,j}$:

$$\begin{array}{cccc} S_{i,j} & S_{i,j+1} & \cdots & S_{i,j+w-1} \\ S_{i+1,j} & S_{i+1,j+1} & \cdots & S_{i+1,j+w-1} \\ \vdots & \vdots & \ddots & \vdots \\ S_{i+h-1,j} & S_{i+h-1,j+1} & \cdots & S_{i+h-1,j+w-1} \end{array}$$

4.6.2.2 Anchor-Point Parameter

Many NPP primitives performing neighborhood operations allow the user to specify the relative location of the neighborhood via a parameter usually named `oAnchor` of type [NppiPoint](#). Using the anchor a developer can choose the position of the mask (see [Mask-Size Parameter](#)) relative to current pixel index.

Using the same example as in [Mask-Size Parameter](#), but this time with an anchor position of (a, b):

```
assert(oMaskSize.w == w);
assert(oMaskSize.h == h);
assert(oAnchor.x == a);
assert(oAnchor.y == b);
```

the following pixels from the source image would be read:

$$\begin{array}{cccc} S_{i-a,j-b} & S_{i-a,j-b+1} & \cdots & S_{i-a,j-b+w-1} \\ S_{i-a+1,j-b} & S_{i-a+1,j-b+1} & \cdots & S_{i-a+1,j-b+w-1} \\ \vdots & \vdots & \ddots & \vdots \\ S_{i-a+h-1,j-b} & S_{i-a+h-1,j-b+1} & \cdots & S_{i-a+h-1,j-b+w-1} \end{array}$$

4.6.2.3 Sampling Beyond Image Boundaries

NPP primitives in general and NPP neighborhood operations in particular require that all pixel locations read and written are valid and within the boundaries of the respective images. Sampling outside of the defined image data regions results in undefined behavior and may lead to system instability.

This poses a problem in practice: when processing full-size images one cannot choose the destination ROI to be the same size as the source image. Because neighborhood operations read pixels from an enlarged source ROI, the destination ROI must be shrunk so that the expanded source ROI does not exceed the source image's size.

For cases where this "shrinking" of the destination image size is unacceptable, NPP provides a set of border-expanding Copy primitives. E.g. `nppiCopyConstBorder_8u_C1R()`, `nppiCopyReplicateBorder_8u_C1R()` and `nppiCopyWrapBorder_8u_C1R()`. The user can use these primitives to "expand" the source image's size using one of the three expansion modes. The expanded image can then be safely passed to a neighborhood operation producing a full-size result.

Chapter 5

Module Index

5.1 Modules

Here is a list of all modules:

NPP Core	27
NPP Type Definitions and Constants	31
Basic NPP Data Types	46
Threshold and Compare Operations	50
Threshold Operations	51
Compare Operations	140

Chapter 6

Data Structure Index

6.1 Data Structures

Here are the data structures with brief descriptions:

NPP_ALIGN_16 (Complex Number This struct represents a long long complex number)	163
NPP_ALIGN_8 (Complex Number This struct represents an unsigned int complex number) . .	165
NppiHaarBuffer	167
NppiHaarClassifier_32f	168
NppiPoint (2D Point)	169
NppiRect (2D Rectangle This struct contains position and size information of a rectangle in two space)	170
NppiSize (2D Size This struct typically represents the size of a a rectangular region in two space)	171
NppLibraryVersion	172

Chapter 7

Module Documentation

7.1 NPP Core

Basic functions for library management, in particular library version and device property query functions.

Functions

- const [NppLibraryVersion](#) * [nppGetLibVersion](#) (void)
Get the NPP library version.
- [NppGpuComputeCapability](#) [nppGetGpuComputeCapability](#) (void)
What CUDA compute model is supported by the active CUDA device?
- int [nppGetGpuNumSMs](#) (void)
Get the number of Streaming Multiprocessors (SM) on the active CUDA device.
- int [nppGetMaxThreadsPerBlock](#) (void)
Get the maximum number of threads per block on the active CUDA device.
- int [nppGetMaxThreadsPerSM](#) (void)
Get the maximum number of threads per SM for the active GPU.
- int [nppGetGpuDeviceProperties](#) (int *pMaxThreadsPerSM, int *pMaxThreadsPerBlock, int *pNumberOfSMs)
Get the maximum number of threads per SM, maximum threads per block, and number of SMs for the active GPU.
- const char * [nppGetGpuName](#) (void)
Get the name of the active CUDA device.
- cudaStream_t [nppGetStream](#) (void)
Get the NPP CUDA stream.
- unsigned int [nppGetStreamNumSMs](#) (void)
Get the number of SMs on the device associated with the current NPP CUDA stream.

- unsigned int `nppGetStreamMaxThreadsPerSM` (void)
Get the maximum number of threads per SM on the device associated with the current NPP CUDA stream.
- void `nppSetStream` (cudaStream_t hStream)
Set the NPP CUDA stream.

7.1.1 Detailed Description

Basic functions for library management, in particular library version and device property query functions.

7.1.2 Function Documentation

7.1.2.1 `NppGpuComputeCapability nppGetGpuComputeCapability` (void)

What CUDA compute model is supported by the active CUDA device?

Before trying to call any NPP functions, the user should make a call this function to ensure that the current machine has a CUDA capable device.

Returns:

An enum value representing if a CUDA capable device was found and what level of compute capabilities it supports.

7.1.2.2 `int nppGetGpuDeviceProperties` (int * *pMaxThreadsPerSM*, int * *pMaxThreadsPerBlock*, int * *pNumberOfSMs*)

Get the maximum number of threads per SM, maximum threads per block, and number of SMs for the active GPU.

Returns:

cudaSuccess for success, -1 for failure

7.1.2.3 `const char* nppGetGpuName` (void)

Get the name of the active CUDA device.

Returns:

Name string of the active graphics-card/compute device in a system.

7.1.2.4 `int nppGetGpuNumSMs` (void)

Get the number of Streaming Multiprocessors (SM) on the active CUDA device.

Returns:

Number of SMs of the default CUDA device.

7.1.2.5 const NppLibraryVersion* nppGetLibVersion (void)

Get the NPP library version.

Returns:

A struct containing separate values for major and minor revision and build number.

7.1.2.6 int nppGetMaxThreadsPerBlock (void)

Get the maximum number of threads per block on the active CUDA device.

Returns:

Maximum number of threads per block on the active CUDA device.

7.1.2.7 int nppGetMaxThreadsPerSM (void)

Get the maximum number of threads per SM for the active GPU.

Returns:

Maximum number of threads per SM for the active GPU

7.1.2.8 cudaStream_t nppGetStream (void)

Get the NPP CUDA stream.

NPP enables concurrent device tasks via a global stream state variable. The NPP stream by default is set to stream 0, i.e. non-concurrent mode. A user can set the NPP stream to any valid CUDA stream. All CUDA commands issued by NPP (e.g. kernels launched by the NPP library) are then issued to that NPP stream.

7.1.2.9 unsigned int nppGetStreamMaxThreadsPerSM (void)

Get the maximum number of threads per SM on the device associated with the current NPP CUDA stream.

NPP enables concurrent device tasks via a global stream state variable. The NPP stream by default is set to stream 0, i.e. non-concurrent mode. A user can set the NPP stream to any valid CUDA stream. All CUDA commands issued by NPP (e.g. kernels launched by the NPP library) are then issued to that NPP stream. This call avoids a cudaGetDeviceProperties() call.

7.1.2.10 unsigned int nppGetStreamNumSMs (void)

Get the number of SMs on the device associated with the current NPP CUDA stream.

NPP enables concurrent device tasks via a global stream state variable. The NPP stream by default is set to stream 0, i.e. non-concurrent mode. A user can set the NPP stream to any valid CUDA stream. All CUDA commands issued by NPP (e.g. kernels launched by the NPP library) are then issued to that NPP stream. This call avoids a cudaGetDeviceProperties() call.

7.1.2.11 void nppSetStream (cudaStream_t *hStream*)

Set the NPP CUDA stream.

See also:

[nppGetStream\(\)](#)

7.2 NPP Type Definitions and Constants

Data Structures

- struct [NppLibraryVersion](#)
- struct [NppiPoint](#)
2D Point
- struct [NppiSize](#)
2D Size This struct typically represents the size of a rectangular region in two space.
- struct [NppiRect](#)
2D Rectangle This struct contains position and size information of a rectangle in two space.
- struct [NppiHaarClassifier_32f](#)
- struct [NppiHaarBuffer](#)

Modules

- [Basic NPP Data Types](#)

Defines

- #define [NPP_MIN_8U](#) (0)
Minimum 8-bit unsigned integer.
- #define [NPP_MAX_8U](#) (255)
Maximum 8-bit unsigned integer.
- #define [NPP_MIN_16U](#) (0)
Minimum 16-bit unsigned integer.
- #define [NPP_MAX_16U](#) (65535)
Maximum 16-bit unsigned integer.
- #define [NPP_MIN_32U](#) (0)
Minimum 32-bit unsigned integer.
- #define [NPP_MAX_32U](#) (4294967295U)
Maximum 32-bit unsigned integer.
- #define [NPP_MIN_64U](#) (0)
Minimum 64-bit unsigned integer.
- #define [NPP_MAX_64U](#) (18446744073709551615ULL)
Maximum 64-bit unsigned integer.
- #define [NPP_MIN_8S](#) (-127 - 1)
Minimum 8-bit signed integer.

- #define `NPP_MAX_8S` (127)
Maximum 8-bit signed integer.
- #define `NPP_MIN_16S` (-32767 - 1)
Minimum 16-bit signed integer.
- #define `NPP_MAX_16S` (32767)
Maximum 16-bit signed integer.
- #define `NPP_MIN_32S` (-2147483647 - 1)
Minimum 32-bit signed integer.
- #define `NPP_MAX_32S` (2147483647)
Maximum 32-bit signed integer.
- #define `NPP_MAX_64S` (9223372036854775807LL)
Maximum 64-bit signed integer.
- #define `NPP_MIN_64S` (-9223372036854775807LL - 1)
Minimum 64-bit signed integer.
- #define `NPP_MINABS_32F` (1.175494351e-38f)
Smallest positive 32-bit floating point value.
- #define `NPP_MAXABS_32F` (3.402823466e+38f)
Largest positive 32-bit floating point value.
- #define `NPP_MINABS_64F` (2.2250738585072014e-308)
Smallest positive 64-bit floating point value.
- #define `NPP_MAXABS_64F` (1.7976931348623158e+308)
Largest positive 64-bit floating point value.

Enumerations

- enum `NppiInterpolationMode` {
`NPPI_INTER_UNDEFINED` = 0,
`NPPI_INTER_NN` = 1,
`NPPI_INTER_LINEAR` = 2,
`NPPI_INTER_CUBIC` = 4,
`NPPI_INTER_CUBIC2P_BSPLINE`,
`NPPI_INTER_CUBIC2P_CATMULLROM`,
`NPPI_INTER_CUBIC2P_B05C03`,
`NPPI_INTER_SUPER` = 8,
`NPPI_INTER_LANCZOS` = 16,
`NPPI_INTER_LANCZOS3_ADVANCED` = 17,
`NPPI_SMOOTH_EDGE` = (1 << 31) }

Filtering methods.

- enum `NppiBayerGridPosition` {
`NPPI_BAYER_BGGR` = 0,
`NPPI_BAYER_RGGB` = 1,
`NPPI_BAYER_GBRG` = 2,
`NPPI_BAYER_GRBG` = 3 }

Bayer Grid Position Registration.

- enum `NppiMaskSize` {
`NPP_MASK_SIZE_1_X_3`,
`NPP_MASK_SIZE_1_X_5`,
`NPP_MASK_SIZE_3_X_1` = 100,
`NPP_MASK_SIZE_5_X_1`,
`NPP_MASK_SIZE_3_X_3` = 200,
`NPP_MASK_SIZE_5_X_5`,
`NPP_MASK_SIZE_7_X_7` = 400,
`NPP_MASK_SIZE_9_X_9` = 500,
`NPP_MASK_SIZE_11_X_11` = 600,
`NPP_MASK_SIZE_13_X_13` = 700,
`NPP_MASK_SIZE_15_X_15` = 800 }

Fixed filter-kernel sizes.

- enum `NppiDifferentialKernel` {
`NPP_FILTER_SOBEL`,
`NPP_FILTER_SCHARR` }

Differential Filter types.

- enum `NppStatus` {
`NPP_NOT_SUPPORTED_MODE_ERROR` = -9999,
`NPP_INVALID_HOST_POINTER_ERROR` = -1032,
`NPP_INVALID_DEVICE_POINTER_ERROR` = -1031,
`NPP_LUT_PALETTE_BITSIZE_ERROR` = -1030,
`NPP_ZC_MODE_NOT_SUPPORTED_ERROR` = -1028,
`NPP_NOT_SUFFICIENT_COMPUTE_CAPABILITY` = -1027,
`NPP_TEXTURE_BIND_ERROR` = -1024,
`NPP_WRONG_INTERSECTION_ROI_ERROR` = -1020,
`NPP_HAAR_CLASSIFIER_PIXEL_MATCH_ERROR` = -1006,
`NPP_MEMFREE_ERROR` = -1005,
`NPP_MEMSET_ERROR` = -1004,
`NPP_MEMCPY_ERROR` = -1003,
`NPP_ALIGNMENT_ERROR` = -1002,
`NPP_CUDA_KERNEL_EXECUTION_ERROR` = -1000,

NPP_ROUND_MODE_NOT_SUPPORTED_ERROR = -213,
NPP_QUALITY_INDEX_ERROR = -210,
NPP_RESIZE_NO_OPERATION_ERROR = -201,
NPP_OVERFLOW_ERROR = -109,
NPP_NOT_EVEN_STEP_ERROR = -108,
NPP_HISTOGRAM_NUMBER_OF_LEVELS_ERROR = -107,
NPP_LUT_NUMBER_OF_LEVELS_ERROR = -106,
NPP_CORRUPTED_DATA_ERROR = -61,
NPP_CHANNEL_ORDER_ERROR = -60,
NPP_ZERO_MASK_VALUE_ERROR = -59,
NPP_QUADRANGLE_ERROR = -58,
NPP_RECTANGLE_ERROR = -57,
NPP_COEFFICIENT_ERROR = -56,
NPP_NUMBER_OF_CHANNELS_ERROR = -53,
NPP_COI_ERROR = -52,
NPP_DIVISOR_ERROR = -51,
NPP_CHANNEL_ERROR = -47,
NPP_STRIDE_ERROR = -37,
NPP_ANCHOR_ERROR = -34,
NPP_MASK_SIZE_ERROR = -33,
NPP_RESIZE_FACTOR_ERROR = -23,
NPP_INTERPOLATION_ERROR = -22,
NPP_MIRROR_FLIP_ERROR = -21,
NPP_MOMENT_00_ZERO_ERROR = -20,
NPP_THRESHOLD_NEGATIVE_LEVEL_ERROR = -19,
NPP_THRESHOLD_ERROR = -18,
NPP_CONTEXT_MATCH_ERROR = -17,
NPP_FFT_FLAG_ERROR = -16,
NPP_FFT_ORDER_ERROR = -15,
NPP_STEP_ERROR = -14,
NPP_SCALE_RANGE_ERROR = -13,
NPP_DATA_TYPE_ERROR = -12,
NPP_OUT_OFF_RANGE_ERROR = -11,
NPP_DIVIDE_BY_ZERO_ERROR = -10,
NPP_MEMORY_ALLOCATION_ERR = -9,
NPP_NULL_POINTER_ERROR = -8,
NPP_RANGE_ERROR = -7,
NPP_SIZE_ERROR = -6,
NPP_BAD_ARGUMENT_ERROR = -5,
NPP_NO_MEMORY_ERROR = -4,
NPP_NOT_IMPLEMENTED_ERROR = -3,

```
NPP_ERROR = -2,  
NPP_ERROR_RESERVED = -1,  
NPP_NO_ERROR = 0,  
NPP_SUCCESS = NPP_NO_ERROR,  
NPP_NO_OPERATION_WARNING = 1,  
NPP_DIVIDE_BY_ZERO_WARNING = 6,  
NPP_AFFINE_QUAD_INCORRECT_WARNING = 28,  
NPP_WRONG_INTERSECTION_ROI_WARNING = 29,  
NPP_WRONG_INTERSECTION_QUAD_WARNING = 30,  
NPP_DOUBLE_SIZE_WARNING = 35,  
NPP_MISALIGNED_DST_ROI_WARNING = 10000 }
```

Error Status Codes.

- enum NppGpuComputeCapability {
NPP_CUDA_UNKNOWN_VERSION = -1,
NPP_CUDA_NOT_CAPABLE = 0,
NPP_CUDA_1_0 = 100,
NPP_CUDA_1_1 = 110,
NPP_CUDA_1_2 = 120,
NPP_CUDA_1_3 = 130,
NPP_CUDA_2_0 = 200,
NPP_CUDA_2_1 = 210,
NPP_CUDA_3_0 = 300,
NPP_CUDA_3_2 = 320,
NPP_CUDA_3_5 = 350,
NPP_CUDA_3_7 = 370,
NPP_CUDA_5_0 = 500,
NPP_CUDA_5_2 = 520,
NPP_CUDA_5_3 = 530,
NPP_CUDA_6_0 = 600 }
- enum NppiAxis {
NPP_HORIZONTAL_AXIS,
NPP_VERTICAL_AXIS,
NPP_BOTH_AXIS }
- enum NppCmpOp {
NPP_CMP_LESS,
NPP_CMP_LESS_EQ,
NPP_CMP_EQ,
NPP_CMP_GREATER_EQ,
NPP_CMP_GREATER }

- enum `NppRoundMode` {
 - `NPP_RND_NEAR`,
 - `NPP_ROUND_NEAREST_TIES_TO_EVEN` = `NPP_RND_NEAR`,
 - `NPP_RND_FINANCIAL`,
 - `NPP_ROUND_NEAREST_TIES_AWAY_FROM_ZERO` = `NPP_RND_FINANCIAL`,
 - `NPP_RND_ZERO`,
 - `NPP_ROUND_TOWARD_ZERO` = `NPP_RND_ZERO` }

Rounding Modes.
- enum `NppiBorderType` {
 - `NPP_BORDER_UNDEFINED` = 0,
 - `NPP_BORDER_NONE` = `NPP_BORDER_UNDEFINED`,
 - `NPP_BORDER_CONSTANT` = 1,
 - `NPP_BORDER_REPLICATE` = 2,
 - `NPP_BORDER_WRAP` = 3,
 - `NPP_BORDER_MIRROR` = 4 }
- enum `NppHintAlgorithm` {
 - `NPP_ALG_HINT_NONE`,
 - `NPP_ALG_HINT_FAST`,
 - `NPP_ALG_HINT_ACCURATE` }
- enum `NppiAlphaOp` {
 - `NPPI_OP_ALPHA_OVER`,
 - `NPPI_OP_ALPHA_IN`,
 - `NPPI_OP_ALPHA_OUT`,
 - `NPPI_OP_ALPHA_ATOP`,
 - `NPPI_OP_ALPHA_XOR`,
 - `NPPI_OP_ALPHA_PLUS`,
 - `NPPI_OP_ALPHA_OVER_PREMUL`,
 - `NPPI_OP_ALPHA_IN_PREMUL`,
 - `NPPI_OP_ALPHA_OUT_PREMUL`,
 - `NPPI_OP_ALPHA_ATOP_PREMUL`,
 - `NPPI_OP_ALPHA_XOR_PREMUL`,
 - `NPPI_OP_ALPHA_PLUS_PREMUL`,
 - `NPPI_OP_ALPHA_PREMUL` }
- enum `NppsZCType` {
 - `nppZCR`,
 - `nppZCXor`,
 - `nppZCC` }
- enum `NppiHuffmanTableType` {
 - `nppiDCTable`,
 - `nppiACTable` }

- enum `NppiNorm` {
 `nppiNormInf` = 0,
 `nppiNormL1` = 1,
 `nppiNormL2` = 2 }

7.2.1 Define Documentation

7.2.1.1 `#define NPP_MAX_16S (32767)`

Maximum 16-bit signed integer.

7.2.1.2 `#define NPP_MAX_16U (65535)`

Maximum 16-bit unsigned integer.

7.2.1.3 `#define NPP_MAX_32S (2147483647)`

Maximum 32-bit signed integer.

7.2.1.4 `#define NPP_MAX_32U (4294967295U)`

Maximum 32-bit unsigned integer.

7.2.1.5 `#define NPP_MAX_64S (9223372036854775807LL)`

Maximum 64-bit signed integer.

7.2.1.6 `#define NPP_MAX_64U (18446744073709551615ULL)`

Maximum 64-bit unsigned integer.

7.2.1.7 `#define NPP_MAX_8S (127)`

Maximum 8-bit signed integer.

7.2.1.8 `#define NPP_MAX_8U (255)`

Maximum 8-bit unsigned integer.

7.2.1.9 `#define NPP_MAXABS_32F (3.402823466e+38f)`

Largest positive 32-bit floating point value.

7.2.1.10 `#define NPP_MAXABS_64F (1.7976931348623158e+308)`

Largest positive 64-bit floating point value.

7.2.1.11 #define NPP_MIN_16S (-32767 - 1)

Minimum 16-bit signed integer.

7.2.1.12 #define NPP_MIN_16U (0)

Minimum 16-bit unsigned integer.

7.2.1.13 #define NPP_MIN_32S (-2147483647 - 1)

Minimum 32-bit signed integer.

7.2.1.14 #define NPP_MIN_32U (0)

Minimum 32-bit unsigned integer.

7.2.1.15 #define NPP_MIN_64S (-9223372036854775807LL - 1)

Minimum 64-bit signed integer.

7.2.1.16 #define NPP_MIN_64U (0)

Minimum 64-bit unsigned integer.

7.2.1.17 #define NPP_MIN_8S (-127 - 1)

Minimum 8-bit signed integer.

7.2.1.18 #define NPP_MIN_8U (0)

Minimum 8-bit unsigned integer.

7.2.1.19 #define NPP_MINABS_32F (1.175494351e-38f)

Smallest positive 32-bit floating point value.

7.2.1.20 #define NPP_MINABS_64F (2.2250738585072014e-308)

Smallest positive 64-bit floating point value.

7.2.2 Enumeration Type Documentation**7.2.2.1 enum NppCmpOp**

Enumerator:

NPP_CMP_LESS

NPP_CMP_LESS_EQ
NPP_CMP_EQ
NPP_CMP_GREATER_EQ
NPP_CMP_GREATER

7.2.2.2 enum NppGpuComputeCapability

Enumerator:

NPP_CUDA_UNKNOWN_VERSION Indicates that the compute-capability query failed.
NPP_CUDA_NOT_CAPABLE Indicates that no CUDA capable device was found.
NPP_CUDA_1_0 Indicates that CUDA 1.0 capable device is machine's default device.
NPP_CUDA_1_1 Indicates that CUDA 1.1 capable device is machine's default device.
NPP_CUDA_1_2 Indicates that CUDA 1.2 capable device is machine's default device.
NPP_CUDA_1_3 Indicates that CUDA 1.3 capable device is machine's default device.
NPP_CUDA_2_0 Indicates that CUDA 2.0 capable device is machine's default device.
NPP_CUDA_2_1 Indicates that CUDA 2.1 capable device is machine's default device.
NPP_CUDA_3_0 Indicates that CUDA 3.0 capable device is machine's default device.
NPP_CUDA_3_2 Indicates that CUDA 3.2 capable device is machine's default device.
NPP_CUDA_3_5 Indicates that CUDA 3.5 capable device is machine's default device.
NPP_CUDA_3_7 Indicates that CUDA 3.7 capable device is machine's default device.
NPP_CUDA_5_0 Indicates that CUDA 5.0 capable device is machine's default device.
NPP_CUDA_5_2 Indicates that CUDA 5.2 capable device is machine's default device.
NPP_CUDA_5_3 Indicates that CUDA 5.3 capable device is machine's default device.
NPP_CUDA_6_0 Indicates that CUDA 6.0 or better is machine's default device.

7.2.2.3 enum NppHintAlgorithm

Enumerator:

NPP_ALG_HINT_NONE
NPP_ALG_HINT_FAST
NPP_ALG_HINT_ACCURATE

7.2.2.4 enum NppiAlphaOp

Enumerator:

NPPI_OP_ALPHA_OVER
NPPI_OP_ALPHA_IN
NPPI_OP_ALPHA_OUT
NPPI_OP_ALPHA_ATOP
NPPI_OP_ALPHA_XOR

NPPI_OP_ALPHA_PLUS
NPPI_OP_ALPHA_OVER_PREMUL
NPPI_OP_ALPHA_IN_PREMUL
NPPI_OP_ALPHA_OUT_PREMUL
NPPI_OP_ALPHA_ATOP_PREMUL
NPPI_OP_ALPHA_XOR_PREMUL
NPPI_OP_ALPHA_PLUS_PREMUL
NPPI_OP_ALPHA_PREMUL

7.2.2.5 enum NppiAxis

Enumerator:

NPP_HORIZONTAL_AXIS
NPP_VERTICAL_AXIS
NPP_BOTH_AXIS

7.2.2.6 enum NppiBayerGridPosition

Bayer Grid Position Registration.

Enumerator:

NPPI_BAYER_BGGR Default registration position.
NPPI_BAYER_RGGB
NPPI_BAYER_GBRG
NPPI_BAYER_GRBG

7.2.2.7 enum NppiBorderType

Enumerator:

NPP_BORDER_UNDEFINED
NPP_BORDER_NONE
NPP_BORDER_CONSTANT
NPP_BORDER_REPLICATE
NPP_BORDER_WRAP
NPP_BORDER_MIRROR

7.2.2.8 enum NppiDifferentialKernel

Differential Filter types.

Enumerator:

NPP_FILTER_SOBEL
NPP_FILTER_SCHARR

7.2.2.9 enum NppiHuffmanTableType

Enumerator:

nppiDCTable DC Table.

nppiACTable AC Table.

7.2.2.10 enum NppiInterpolationMode

Filtering methods.

Enumerator:

NPPI_INTER_UNDEFINED

NPPI_INTER_NN Nearest neighbor filtering.

NPPI_INTER_LINEAR Linear interpolation.

NPPI_INTER_CUBIC Cubic interpolation.

NPPI_INTER_CUBIC2P_BSPLINE Two-parameter cubic filter (B=1, C=0).

NPPI_INTER_CUBIC2P_CATMULLROM Two-parameter cubic filter (B=0, C=1/2).

NPPI_INTER_CUBIC2P_B05C03 Two-parameter cubic filter (B=1/2, C=3/10).

NPPI_INTER_SUPER Super sampling.

NPPI_INTER_LANCZOS Lanczos filtering.

NPPI_INTER_LANCZOS3_ADVANCED Generic Lanczos filtering with order 3.

NPPI_SMOOTH_EDGE Smooth edge filtering.

7.2.2.11 enum NppiMaskSize

Fixed filter-kernel sizes.

Enumerator:

NPP_MASK_SIZE_1_X_3

NPP_MASK_SIZE_1_X_5

NPP_MASK_SIZE_3_X_1

NPP_MASK_SIZE_5_X_1

NPP_MASK_SIZE_3_X_3

NPP_MASK_SIZE_5_X_5

NPP_MASK_SIZE_7_X_7

NPP_MASK_SIZE_9_X_9

NPP_MASK_SIZE_11_X_11

NPP_MASK_SIZE_13_X_13

NPP_MASK_SIZE_15_X_15

7.2.2.12 enum NppiNorm

Enumerator:

- nppiNormInf* maximum
- nppiNormL1* sum
- nppiNormL2* square root of sum of squares

7.2.2.13 enum NppRoundMode

Rounding Modes.

The enumerated rounding modes are used by a large number of NPP primitives to allow the user to specify the method by which fractional values are converted to integer values. Also see [Rounding Modes](#).

For NPP release 5.5 new names for the three rounding modes are introduced that are based on the naming conventions for rounding modes set forth in the IEEE-754 floating-point standard. Developers are encouraged to use the new, longer names to be future proof as the legacy names will be deprecated in subsequent NPP releases.

Enumerator:

NPP_RND_NEAR Round to the nearest even integer.

All fractional numbers are rounded to their nearest integer. The ambiguous cases (i.e. $\langle \text{integer} \rangle.5$) are rounded to the closest even integer. E.g.

- `roundNear(0.5) = 0`
- `roundNear(0.6) = 1`
- `roundNear(1.5) = 2`
- `roundNear(-1.5) = -2`

NPP_ROUND_NEAREST_TIES_TO_EVEN Alias name for [NPP_RND_NEAR](#).

NPP_RND_FINANCIAL Round according to financial rule.

All fractional numbers are rounded to their nearest integer. The ambiguous cases (i.e. $\langle \text{integer} \rangle.5$) are rounded away from zero. E.g.

- `roundFinancial(0.4) = 0`
- `roundFinancial(0.5) = 1`
- `roundFinancial(-1.5) = -2`

NPP_ROUND_NEAREST_TIES_AWAY_FROM_ZERO Alias name for [NPP_RND_FINANCIAL](#).

NPP_RND_ZERO Round towards zero (truncation).

All fractional numbers of the form $\langle \text{integer} \rangle.\langle \text{decimals} \rangle$ are truncated to $\langle \text{integer} \rangle$.

- `roundZero(1.5) = 1`
- `roundZero(1.9) = 1`
- `roundZero(-2.5) = -2`

NPP_ROUND_TOWARD_ZERO Alias name for [NPP_RND_ZERO](#).

7.2.2.14 enum NppStatus

Error Status Codes.

Almost all NPP function return error-status information using these return codes. Negative return codes indicate errors, positive return codes indicate warnings, a return code of 0 indicates success.

Enumerator:

NPP_NOT_SUPPORTED_MODE_ERROR

NPP_INVALID_HOST_POINTER_ERROR

NPP_INVALID_DEVICE_POINTER_ERROR

NPP_LUT_PALETTE_BITSIZE_ERROR

NPP_ZC_MODE_NOT_SUPPORTED_ERROR ZeroCrossing mode not supported.

NPP_NOT_SUFFICIENT_COMPUTE_CAPABILITY

NPP_TEXTURE_BIND_ERROR

NPP_WRONG_INTERSECTION_ROI_ERROR

NPP_HAAR_CLASSIFIER_PIXEL_MATCH_ERROR

NPP_MEMFREE_ERROR

NPP_MEMSET_ERROR

NPP_MEMCPY_ERROR

NPP_ALIGNMENT_ERROR

NPP_CUDA_KERNEL_EXECUTION_ERROR

NPP_ROUND_MODE_NOT_SUPPORTED_ERROR Unsupported round mode.

NPP_QUALITY_INDEX_ERROR Image pixels are constant for quality index.

NPP_RESIZE_NO_OPERATION_ERROR One of the output image dimensions is less than 1 pixel.

NPP_OVERFLOW_ERROR Number overflows the upper or lower limit of the data type.

NPP_NOT_EVEN_STEP_ERROR Step value is not pixel multiple.

NPP_HISTOGRAM_NUMBER_OF_LEVELS_ERROR Number of levels for histogram is less than 2.

NPP_LUT_NUMBER_OF_LEVELS_ERROR Number of levels for LUT is less than 2.

NPP_CORRUPTED_DATA_ERROR Processed data is corrupted.

NPP_CHANNEL_ORDER_ERROR Wrong order of the destination channels.

NPP_ZERO_MASK_VALUE_ERROR All values of the mask are zero.

NPP_QUADRANGLE_ERROR The quadrangle is nonconvex or degenerates into triangle, line or point.

NPP_RECTANGLE_ERROR Size of the rectangle region is less than or equal to 1.

NPP_COEFFICIENT_ERROR Unallowable values of the transformation coefficients.

NPP_NUMBER_OF_CHANNELS_ERROR Bad or unsupported number of channels.

NPP_COI_ERROR Channel of interest is not 1, 2, or 3.

NPP_DIVISOR_ERROR Divisor is equal to zero.

NPP_CHANNEL_ERROR Illegal channel index.

NPP_STRIDE_ERROR Stride is less than the row length.

NPP_ANCHOR_ERROR Anchor point is outside mask.

NPP_MASK_SIZE_ERROR Lower bound is larger than upper bound.

NPP_RESIZE_FACTOR_ERROR

NPP_INTERPOLATION_ERROR

NPP_MIRROR_FLIP_ERROR

NPP_MOMENT_00_ZERO_ERROR

NPP_THRESHOLD_NEGATIVE_LEVEL_ERROR

NPP_THRESHOLD_ERROR

NPP_CONTEXT_MATCH_ERROR

NPP_FFT_FLAG_ERROR

NPP_FFT_ORDER_ERROR

NPP_STEP_ERROR Step is less or equal zero.

NPP_SCALE_RANGE_ERROR

NPP_DATA_TYPE_ERROR

NPP_OUT_OFF_RANGE_ERROR

NPP_DIVIDE_BY_ZERO_ERROR

NPP_MEMORY_ALLOCATION_ERR

NPP_NULL_POINTER_ERROR

NPP_RANGE_ERROR

NPP_SIZE_ERROR

NPP_BAD_ARGUMENT_ERROR

NPP_NO_MEMORY_ERROR

NPP_NOT_IMPLEMENTED_ERROR

NPP_ERROR

NPP_ERROR_RESERVED

NPP_NO_ERROR Error free operation.

NPP_SUCCESS Successful operation (same as ***NPP_NO_ERROR***).

NPP_NO_OPERATION_WARNING Indicates that no operation was performed.

NPP_DIVIDE_BY_ZERO_WARNING Divisor is zero however does not terminate the execution.

NPP_AFFINE_QUAD_INCORRECT_WARNING Indicates that the quadrangle passed to one of affine warping functions doesn't have necessary properties.

First 3 vertices are used, the fourth vertex discarded.

NPP_WRONG_INTERSECTION_ROI_WARNING The given ROI has no intersection with either the source or destination ROI.

Thus no operation was performed.

NPP_WRONG_INTERSECTION_QUAD_WARNING The given quadrangle has no intersection with either the source or destination ROI.

Thus no operation was performed.

NPP_DOUBLE_SIZE_WARNING Image size isn't multiple of two.

Indicates that in case of 422/411/420 sampling the ROI width/height was modified for proper processing.

NPP_MISALIGNED_DST_ROI_WARNING Speed reduction due to uncoalesced memory accesses warning.

7.2.2.15 enum NppsZCType**Enumerator:**

- nppZCR* sign change
- nppZCxor* sign change XOR
- nppZCC* sign change count_0

7.3 Basic NPP Data Types

Data Structures

- struct [NPP_ALIGN_8](#)
Complex Number This struct represents an unsigned int complex number.
- struct [NPP_ALIGN_16](#)
Complex Number This struct represents a long long complex number.

Typedefs

- typedef unsigned char [Npp8u](#)
8-bit unsigned chars
- typedef signed char [Npp8s](#)
8-bit signed chars
- typedef unsigned short [Npp16u](#)
16-bit unsigned integers
- typedef short [Npp16s](#)
16-bit signed integers
- typedef unsigned int [Npp32u](#)
32-bit unsigned integers
- typedef int [Npp32s](#)
32-bit signed integers
- typedef unsigned long long [Npp64u](#)
64-bit unsigned integers
- typedef long long [Npp64s](#)
64-bit signed integers
- typedef float [Npp32f](#)
32-bit (IEEE) floating-point numbers
- typedef double [Npp64f](#)
64-bit floating-point numbers
- typedef struct [NPP_ALIGN_8](#) [Npp32uc](#)
Complex Number This struct represents an unsigned int complex number.
- typedef struct [NPP_ALIGN_8](#) [Npp32sc](#)
Complex Number This struct represents a signed int complex number.

- typedef struct [NPP_ALIGN_8 Npp32fc](#)
Complex Number This struct represents a single floating-point complex number.
- typedef struct [NPP_ALIGN_16 Npp64sc](#)
Complex Number This struct represents a long long complex number.
- typedef struct [NPP_ALIGN_16 Npp64fc](#)
Complex Number This struct represents a double floating-point complex number.

Functions

- struct [__align__](#) (2)
Complex Number This struct represents an unsigned char complex number.
- struct [__align__](#) (4)
Complex Number This struct represents an unsigned short complex number.

Variables

- [Npp8uc](#)
- [Npp16uc](#)
- [Npp16sc](#)

7.3.1 Typedef Documentation

7.3.1.1 typedef short Npp16s

16-bit signed integers

7.3.1.2 typedef unsigned short Npp16u

16-bit unsigned integers

7.3.1.3 typedef float Npp32f

32-bit (IEEE) floating-point numbers

7.3.1.4 typedef struct NPP_ALIGN_8 Npp32fc

Complex Number This struct represents a single floating-point complex number.

7.3.1.5 typedef int Npp32s

32-bit signed integers

7.3.1.6 typedef struct NPP_ALIGN_8 Npp32sc

Complex Number This struct represents a signed int complex number.

7.3.1.7 typedef unsigned int Npp32u

32-bit unsigned integers

7.3.1.8 typedef struct NPP_ALIGN_8 Npp32uc

Complex Number This struct represents an unsigned int complex number.

7.3.1.9 typedef double Npp64f

64-bit floating-point numbers

7.3.1.10 typedef struct NPP_ALIGN_16 Npp64fc

Complex Number This struct represents a double floating-point complex number.

7.3.1.11 typedef long long Npp64s

64-bit signed integers

7.3.1.12 typedef struct NPP_ALIGN_16 Npp64sc

Complex Number This struct represents a long long complex number.

7.3.1.13 typedef unsigned long long Npp64u

64-bit unsigned integers

7.3.1.14 typedef signed char Npp8s

8-bit signed chars

7.3.1.15 typedef unsigned char Npp8u

8-bit unsigned chars

7.3.2 Function Documentation**7.3.2.1 struct __align__ (4) [read]**

Complex Number This struct represents an unsigned short complex number.

Complex Number This struct represents a short complex number.

< Real part

< Imaginary part

< Real part

< Imaginary part

7.3.2.2 `struct __align__(2)` [read]

Complex Number This struct represents an unsigned char complex number.

< Real part

< Imaginary part

7.3.3 Variable Documentation

7.3.3.1 `Npp16sc`

7.3.3.2 `Npp16uc`

7.3.3.3 `Npp8uc`

7.4 Threshold and Compare Operations

Methods for pixel-wise threshold and compare operations.

Modules

- [Threshold Operations](#)

Threshold image pixels.

- [Compare Operations](#)

Compare the pixels of two images and create a binary result image.

7.4.1 Detailed Description

Methods for pixel-wise threshold and compare operations.

These functions can be found in either the nppi or nppitc libraries. Linking to only the sub-libraries that you use can significantly save link time, application load time, and CUDA runtime startup time when using dynamic libraries.

7.5 Threshold Operations

Threshold image pixels.

Functions

- `NppStatus nppiThreshold_8u_C1R` (const `Npp8u` *pSrc, int nSrcStep, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp8u` nThreshold, `NppCmpOp` eComparisonOperation)
1 channel 8-bit unsigned char threshold.
- `NppStatus nppiThreshold_8u_C1IR` (`Npp8u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp8u` nThreshold, `NppCmpOp` eComparisonOperation)
1 channel 8-bit unsigned char in place threshold.
- `NppStatus nppiThreshold_16u_C1R` (const `Npp16u` *pSrc, int nSrcStep, `Npp16u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16u` nThreshold, `NppCmpOp` eComparisonOperation)
1 channel 16-bit unsigned short threshold.
- `NppStatus nppiThreshold_16u_C1IR` (`Npp16u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16u` nThreshold, `NppCmpOp` eComparisonOperation)
1 channel 16-bit unsigned short in place threshold.
- `NppStatus nppiThreshold_16s_C1R` (const `Npp16s` *pSrc, int nSrcStep, `Npp16s` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16s` nThreshold, `NppCmpOp` eComparisonOperation)
1 channel 16-bit signed short threshold.
- `NppStatus nppiThreshold_16s_C1IR` (`Npp16s` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16s` nThreshold, `NppCmpOp` eComparisonOperation)
1 channel 16-bit signed short in place threshold.
- `NppStatus nppiThreshold_32f_C1R` (const `Npp32f` *pSrc, int nSrcStep, `Npp32f` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp32f` nThreshold, `NppCmpOp` eComparisonOperation)
1 channel 32-bit floating point threshold.
- `NppStatus nppiThreshold_32f_C1IR` (`Npp32f` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp32f` nThreshold, `NppCmpOp` eComparisonOperation)
1 channel 32-bit floating point in place threshold.
- `NppStatus nppiThreshold_8u_C3R` (const `Npp8u` *pSrc, int nSrcStep, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholds[3], `NppCmpOp` eComparisonOperation)
3 channel 8-bit unsigned char threshold.
- `NppStatus nppiThreshold_8u_C3IR` (`Npp8u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholds[3], `NppCmpOp` eComparisonOperation)
3 channel 8-bit unsigned char in place threshold.
- `NppStatus nppiThreshold_16u_C3R` (const `Npp16u` *pSrc, int nSrcStep, `Npp16u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16u` rThresholds[3], `NppCmpOp` eComparisonOperation)
3 channel 16-bit unsigned short threshold.

- `NppStatus nppiThreshold_16u_C3IR` (`Npp16u *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16u rThresholds[3]`, `NppCmpOp eComparisonOperation`)
3 channel 16-bit unsigned short in place threshold.
- `NppStatus nppiThreshold_16s_C3R` (`const Npp16s *pSrc`, `int nSrcStep`, `Npp16s *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`, `NppCmpOp eComparisonOperation`)
3 channel 16-bit signed short threshold.
- `NppStatus nppiThreshold_16s_C3IR` (`Npp16s *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`, `NppCmpOp eComparisonOperation`)
3 channel 16-bit signed short in place threshold.
- `NppStatus nppiThreshold_32f_C3R` (`const Npp32f *pSrc`, `int nSrcStep`, `Npp32f *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholds[3]`, `NppCmpOp eComparisonOperation`)
3 channel 32-bit floating point threshold.
- `NppStatus nppiThreshold_32f_C3IR` (`Npp32f *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholds[3]`, `NppCmpOp eComparisonOperation`)
3 channel 32-bit floating point in place threshold.
- `NppStatus nppiThreshold_8u_AC4R` (`const Npp8u *pSrc`, `int nSrcStep`, `Npp8u *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp8u rThresholds[3]`, `NppCmpOp eComparisonOperation`)
4 channel 8-bit unsigned char image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_8u_AC4IR` (`Npp8u *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp8u rThresholds[3]`, `NppCmpOp eComparisonOperation`)
4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_16u_AC4R` (`const Npp16u *pSrc`, `int nSrcStep`, `Npp16u *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp16u rThresholds[3]`, `NppCmpOp eComparisonOperation`)
4 channel 16-bit unsigned short image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_16u_AC4IR` (`Npp16u *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16u rThresholds[3]`, `NppCmpOp eComparisonOperation`)
4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_16s_AC4R` (`const Npp16s *pSrc`, `int nSrcStep`, `Npp16s *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`, `NppCmpOp eComparisonOperation`)
4 channel 16-bit signed short image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_16s_AC4IR` (`Npp16s *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`, `NppCmpOp eComparisonOperation`)
4 channel 16-bit signed short in place image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_32f_AC4R` (`const Npp32f *pSrc`, `int nSrcStep`, `Npp32f *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholds[3]`, `NppCmpOp eComparisonOperation`)
4 channel 32-bit floating point image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_32f_AC4IR` (`Npp32f *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholds[3]`, `NppCmpOp eComparisonOperation`)
4 channel 32-bit floating point in place image threshold, not affecting Alpha.

- `NppStatus nppiThreshold_GT_8u_C1R` (const `Npp8u` *pSrc, int nSrcStep, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp8u` nThreshold)
1 channel 8-bit unsigned char threshold.
- `NppStatus nppiThreshold_GT_8u_C1IR` (`Npp8u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp8u` nThreshold)
1 channel 8-bit unsigned char in place threshold.
- `NppStatus nppiThreshold_GT_16u_C1R` (const `Npp16u` *pSrc, int nSrcStep, `Npp16u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16u` nThreshold)
1 channel 16-bit unsigned short threshold.
- `NppStatus nppiThreshold_GT_16u_C1IR` (`Npp16u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16u` nThreshold)
1 channel 16-bit unsigned short in place threshold.
- `NppStatus nppiThreshold_GT_16s_C1R` (const `Npp16s` *pSrc, int nSrcStep, `Npp16s` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16s` nThreshold)
1 channel 16-bit signed short threshold.
- `NppStatus nppiThreshold_GT_16s_C1IR` (`Npp16s` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16s` nThreshold)
1 channel 16-bit signed short in place threshold.
- `NppStatus nppiThreshold_GT_32f_C1R` (const `Npp32f` *pSrc, int nSrcStep, `Npp32f` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp32f` nThreshold)
1 channel 32-bit floating point threshold.
- `NppStatus nppiThreshold_GT_32f_C1IR` (`Npp32f` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp32f` nThreshold)
1 channel 32-bit floating point in place threshold.
- `NppStatus nppiThreshold_GT_8u_C3R` (const `Npp8u` *pSrc, int nSrcStep, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholds[3])
3 channel 8-bit unsigned char threshold.
- `NppStatus nppiThreshold_GT_8u_C3IR` (`Npp8u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholds[3])
3 channel 8-bit unsigned char in place threshold.
- `NppStatus nppiThreshold_GT_16u_C3R` (const `Npp16u` *pSrc, int nSrcStep, `Npp16u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16u` rThresholds[3])
3 channel 16-bit unsigned short threshold.
- `NppStatus nppiThreshold_GT_16u_C3IR` (`Npp16u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16u` rThresholds[3])
3 channel 16-bit unsigned short in place threshold.
- `NppStatus nppiThreshold_GT_16s_C3R` (const `Npp16s` *pSrc, int nSrcStep, `Npp16s` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16s` rThresholds[3])

3 channel 16-bit signed short threshold.

- `NppStatus nppiThreshold_GT_16s_C3IR` (`Npp16s *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`)

3 channel 16-bit signed short in place threshold.

- `NppStatus nppiThreshold_GT_32f_C3R` (`const Npp32f *pSrc`, `int nSrcStep`, `Npp32f *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholds[3]`)

3 channel 32-bit floating point threshold.

- `NppStatus nppiThreshold_GT_32f_C3IR` (`Npp32f *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholds[3]`)

3 channel 32-bit floating point in place threshold.

- `NppStatus nppiThreshold_GT_8u_AC4R` (`const Npp8u *pSrc`, `int nSrcStep`, `Npp8u *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp8u rThresholds[3]`)

4 channel 8-bit unsigned char image threshold, not affecting Alpha.

- `NppStatus nppiThreshold_GT_8u_AC4IR` (`Npp8u *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp8u rThresholds[3]`)

4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.

- `NppStatus nppiThreshold_GT_16u_AC4R` (`const Npp16u *pSrc`, `int nSrcStep`, `Npp16u *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp16u rThresholds[3]`)

4 channel 16-bit unsigned short image threshold, not affecting Alpha.

- `NppStatus nppiThreshold_GT_16u_AC4IR` (`Npp16u *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16u rThresholds[3]`)

4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.

- `NppStatus nppiThreshold_GT_16s_AC4R` (`const Npp16s *pSrc`, `int nSrcStep`, `Npp16s *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`)

4 channel 16-bit signed short image threshold, not affecting Alpha.

- `NppStatus nppiThreshold_GT_16s_AC4IR` (`Npp16s *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`)

4 channel 16-bit signed short in place image threshold, not affecting Alpha.

- `NppStatus nppiThreshold_GT_32f_AC4R` (`const Npp32f *pSrc`, `int nSrcStep`, `Npp32f *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholds[3]`)

4 channel 32-bit floating point image threshold, not affecting Alpha.

- `NppStatus nppiThreshold_GT_32f_AC4IR` (`Npp32f *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholds[3]`)

4 channel 32-bit floating point in place image threshold, not affecting Alpha.

- `NppStatus nppiThreshold_LT_8u_C1R` (`const Npp8u *pSrc`, `int nSrcStep`, `Npp8u *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp8u nThreshold`)

1 channel 8-bit unsigned char threshold.

- `NppStatus nppiThreshold_LT_8u_C1R` (`Npp8u *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp8u nThreshold`)
1 channel 8-bit unsigned char in place threshold.
- `NppStatus nppiThreshold_LT_16u_C1R` (`const Npp16u *pSrc`, `int nSrcStep`, `Npp16u *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp16u nThreshold`)
1 channel 16-bit unsigned short threshold.
- `NppStatus nppiThreshold_LT_16u_C1IR` (`Npp16u *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16u nThreshold`)
1 channel 16-bit unsigned short in place threshold.
- `NppStatus nppiThreshold_LT_16s_C1R` (`const Npp16s *pSrc`, `int nSrcStep`, `Npp16s *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp16s nThreshold`)
1 channel 16-bit signed short threshold.
- `NppStatus nppiThreshold_LT_16s_C1IR` (`Npp16s *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16s nThreshold`)
1 channel 16-bit signed short in place threshold.
- `NppStatus nppiThreshold_LT_32f_C1R` (`const Npp32f *pSrc`, `int nSrcStep`, `Npp32f *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp32f nThreshold`)
1 channel 32-bit floating point threshold.
- `NppStatus nppiThreshold_LT_32f_C1IR` (`Npp32f *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp32f nThreshold`)
1 channel 32-bit floating point in place threshold.
- `NppStatus nppiThreshold_LT_8u_C3R` (`const Npp8u *pSrc`, `int nSrcStep`, `Npp8u *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp8u rThresholds[3]`)
3 channel 8-bit unsigned char threshold.
- `NppStatus nppiThreshold_LT_8u_C3IR` (`Npp8u *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp8u rThresholds[3]`)
3 channel 8-bit unsigned char in place threshold.
- `NppStatus nppiThreshold_LT_16u_C3R` (`const Npp16u *pSrc`, `int nSrcStep`, `Npp16u *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp16u rThresholds[3]`)
3 channel 16-bit unsigned short threshold.
- `NppStatus nppiThreshold_LT_16u_C3IR` (`Npp16u *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16u rThresholds[3]`)
3 channel 16-bit unsigned short in place threshold.
- `NppStatus nppiThreshold_LT_16s_C3R` (`const Npp16s *pSrc`, `int nSrcStep`, `Npp16s *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`)
3 channel 16-bit signed short threshold.
- `NppStatus nppiThreshold_LT_16s_C3IR` (`Npp16s *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`)
3 channel 16-bit signed short in place threshold.

- [NppStatus nppiThreshold_LT_32f_C3R](#) (const [Npp32f](#) *pSrc, int nSrcStep, [Npp32f](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, const [Npp32f](#) rThresholds[3])
3 channel 32-bit floating point threshold.
- [NppStatus nppiThreshold_LT_32f_C3IR](#) ([Npp32f](#) *pSrcDst, int nSrcDstStep, [NppiSize](#) oSizeROI, const [Npp32f](#) rThresholds[3])
3 channel 32-bit floating point in place threshold.
- [NppStatus nppiThreshold_LT_8u_AC4R](#) (const [Npp8u](#) *pSrc, int nSrcStep, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, const [Npp8u](#) rThresholds[3])
4 channel 8-bit unsigned char image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_LT_8u_AC4IR](#) ([Npp8u](#) *pSrcDst, int nSrcDstStep, [NppiSize](#) oSizeROI, const [Npp8u](#) rThresholds[3])
4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_LT_16u_AC4R](#) (const [Npp16u](#) *pSrc, int nSrcStep, [Npp16u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, const [Npp16u](#) rThresholds[3])
4 channel 16-bit unsigned short image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_LT_16u_AC4IR](#) ([Npp16u](#) *pSrcDst, int nSrcDstStep, [NppiSize](#) oSizeROI, const [Npp16u](#) rThresholds[3])
4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_LT_16s_AC4R](#) (const [Npp16s](#) *pSrc, int nSrcStep, [Npp16s](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, const [Npp16s](#) rThresholds[3])
4 channel 16-bit signed short image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_LT_16s_AC4IR](#) ([Npp16s](#) *pSrcDst, int nSrcDstStep, [NppiSize](#) oSizeROI, const [Npp16s](#) rThresholds[3])
4 channel 16-bit signed short in place image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_LT_32f_AC4R](#) (const [Npp32f](#) *pSrc, int nSrcStep, [Npp32f](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, const [Npp32f](#) rThresholds[3])
4 channel 32-bit floating point image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_LT_32f_AC4IR](#) ([Npp32f](#) *pSrcDst, int nSrcDstStep, [NppiSize](#) oSizeROI, const [Npp32f](#) rThresholds[3])
4 channel 32-bit floating point in place image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_Val_8u_C1R](#) (const [Npp8u](#) *pSrc, int nSrcStep, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, const [Npp8u](#) nThreshold, const [Npp8u](#) nValue, [NppCmpOp](#) eComparisonOperation)
1 channel 8-bit unsigned char threshold.
- [NppStatus nppiThreshold_Val_8u_C1IR](#) ([Npp8u](#) *pSrcDst, int nSrcDstStep, [NppiSize](#) oSizeROI, const [Npp8u](#) nThreshold, const [Npp8u](#) nValue, [NppCmpOp](#) eComparisonOperation)
1 channel 8-bit unsigned char in place threshold.

- `NppStatus nppiThreshold_Val_16u_C1R` (const `Npp16u` *pSrc, int nSrcStep, `Npp16u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16u` nThreshold, const `Npp16u` nValue, `NppCmpOp` eComparisonOperation)
1 channel 16-bit unsigned short threshold.
- `NppStatus nppiThreshold_Val_16u_C1IR` (`Npp16u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16u` nThreshold, const `Npp16u` nValue, `NppCmpOp` eComparisonOperation)
1 channel 16-bit unsigned short in place threshold.
- `NppStatus nppiThreshold_Val_16s_C1R` (const `Npp16s` *pSrc, int nSrcStep, `Npp16s` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16s` nThreshold, const `Npp16s` nValue, `NppCmpOp` eComparisonOperation)
1 channel 16-bit signed short threshold.
- `NppStatus nppiThreshold_Val_16s_C1IR` (`Npp16s` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16s` nThreshold, const `Npp16s` nValue, `NppCmpOp` eComparisonOperation)
1 channel 16-bit signed short in place threshold.
- `NppStatus nppiThreshold_Val_32f_C1R` (const `Npp32f` *pSrc, int nSrcStep, `Npp32f` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp32f` nThreshold, const `Npp32f` nValue, `NppCmpOp` eComparisonOperation)
1 channel 32-bit floating point threshold.
- `NppStatus nppiThreshold_Val_32f_C1IR` (`Npp32f` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp32f` nThreshold, const `Npp32f` nValue, `NppCmpOp` eComparisonOperation)
1 channel 32-bit floating point in place threshold.
- `NppStatus nppiThreshold_Val_8u_C3R` (const `Npp8u` *pSrc, int nSrcStep, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholds[3], const `Npp8u` rValues[3], `NppCmpOp` eComparisonOperation)
3 channel 8-bit unsigned char threshold.
- `NppStatus nppiThreshold_Val_8u_C3IR` (`Npp8u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholds[3], const `Npp8u` rValues[3], `NppCmpOp` eComparisonOperation)
3 channel 8-bit unsigned char in place threshold.
- `NppStatus nppiThreshold_Val_16u_C3R` (const `Npp16u` *pSrc, int nSrcStep, `Npp16u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16u` rThresholds[3], const `Npp16u` rValues[3], `NppCmpOp` eComparisonOperation)
3 channel 16-bit unsigned short threshold.
- `NppStatus nppiThreshold_Val_16u_C3IR` (`Npp16u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16u` rThresholds[3], const `Npp16u` rValues[3], `NppCmpOp` eComparisonOperation)
3 channel 16-bit unsigned short in place threshold.
- `NppStatus nppiThreshold_Val_16s_C3R` (const `Npp16s` *pSrc, int nSrcStep, `Npp16s` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16s` rThresholds[3], const `Npp16s` rValues[3], `NppCmpOp` eComparisonOperation)
3 channel 16-bit signed short threshold.

- `NppStatus nppiThreshold_Val_16s_C3IR` (`Npp16s *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`, `const Npp16s rValues[3]`, `NppCmpOp eComparisonOperation`)
3 channel 16-bit signed short in place threshold.
- `NppStatus nppiThreshold_Val_32f_C3R` (`const Npp32f *pSrc`, `int nSrcStep`, `Npp32f *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholds[3]`, `const Npp32f rValues[3]`, `NppCmpOp eComparisonOperation`)
3 channel 32-bit floating point threshold.
- `NppStatus nppiThreshold_Val_32f_C3IR` (`Npp32f *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholds[3]`, `const Npp32f rValues[3]`, `NppCmpOp eComparisonOperation`)
3 channel 32-bit floating point in place threshold.
- `NppStatus nppiThreshold_Val_8u_AC4R` (`const Npp8u *pSrc`, `int nSrcStep`, `Npp8u *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp8u rThresholds[3]`, `const Npp8u rValues[3]`, `NppCmpOp eComparisonOperation`)
4 channel 8-bit unsigned char image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_Val_8u_AC4IR` (`Npp8u *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp8u rThresholds[3]`, `const Npp8u rValues[3]`, `NppCmpOp eComparisonOperation`)
4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_Val_16u_AC4R` (`const Npp16u *pSrc`, `int nSrcStep`, `Npp16u *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp16u rThresholds[3]`, `const Npp16u rValues[3]`, `NppCmpOp eComparisonOperation`)
4 channel 16-bit unsigned short image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_Val_16u_AC4IR` (`Npp16u *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16u rThresholds[3]`, `const Npp16u rValues[3]`, `NppCmpOp eComparisonOperation`)
4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_Val_16s_AC4R` (`const Npp16s *pSrc`, `int nSrcStep`, `Npp16s *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`, `const Npp16s rValues[3]`, `NppCmpOp eComparisonOperation`)
4 channel 16-bit signed short image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_Val_16s_AC4IR` (`Npp16s *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`, `const Npp16s rValues[3]`, `NppCmpOp eComparisonOperation`)
4 channel 16-bit signed short in place image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_Val_32f_AC4R` (`const Npp32f *pSrc`, `int nSrcStep`, `Npp32f *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholds[3]`, `const Npp32f rValues[3]`, `NppCmpOp eComparisonOperation`)
4 channel 32-bit floating point image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_Val_32f_AC4IR` (`Npp32f *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholds[3]`, `const Npp32f rValues[3]`, `NppCmpOp eComparisonOperation`)
4 channel 32-bit floating point in place image threshold, not affecting Alpha.

- `NppStatus nppiThreshold_GTVal_8u_C1R` (const `Npp8u` *pSrc, int nSrcStep, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp8u` nThreshold, const `Npp8u` nValue)
1 channel 8-bit unsigned char threshold.
- `NppStatus nppiThreshold_GTVal_8u_C1IR` (`Npp8u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp8u` nThreshold, const `Npp8u` nValue)
1 channel 8-bit unsigned char in place threshold.
- `NppStatus nppiThreshold_GTVal_16u_C1R` (const `Npp16u` *pSrc, int nSrcStep, `Npp16u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16u` nThreshold, const `Npp16u` nValue)
1 channel 16-bit unsigned short threshold.
- `NppStatus nppiThreshold_GTVal_16u_C1IR` (`Npp16u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16u` nThreshold, const `Npp16u` nValue)
1 channel 16-bit unsigned short in place threshold.
- `NppStatus nppiThreshold_GTVal_16s_C1R` (const `Npp16s` *pSrc, int nSrcStep, `Npp16s` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16s` nThreshold, const `Npp16s` nValue)
1 channel 16-bit signed short threshold.
- `NppStatus nppiThreshold_GTVal_16s_C1IR` (`Npp16s` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16s` nThreshold, const `Npp16s` nValue)
1 channel 16-bit signed short in place threshold.
- `NppStatus nppiThreshold_GTVal_32f_C1R` (const `Npp32f` *pSrc, int nSrcStep, `Npp32f` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp32f` nThreshold, const `Npp32f` nValue)
1 channel 32-bit floating point threshold.
- `NppStatus nppiThreshold_GTVal_32f_C1IR` (`Npp32f` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp32f` nThreshold, const `Npp32f` nValue)
1 channel 32-bit floating point in place threshold.
- `NppStatus nppiThreshold_GTVal_8u_C3R` (const `Npp8u` *pSrc, int nSrcStep, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholds[3], const `Npp8u` rValues[3])
3 channel 8-bit unsigned char threshold.
- `NppStatus nppiThreshold_GTVal_8u_C3IR` (`Npp8u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholds[3], const `Npp8u` rValues[3])
3 channel 8-bit unsigned char in place threshold.
- `NppStatus nppiThreshold_GTVal_16u_C3R` (const `Npp16u` *pSrc, int nSrcStep, `Npp16u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16u` rThresholds[3], const `Npp16u` rValues[3])
3 channel 16-bit unsigned short threshold.
- `NppStatus nppiThreshold_GTVal_16u_C3IR` (`Npp16u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16u` rThresholds[3], const `Npp16u` rValues[3])
3 channel 16-bit unsigned short in place threshold.
- `NppStatus nppiThreshold_GTVal_16s_C3R` (const `Npp16s` *pSrc, int nSrcStep, `Npp16s` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16s` rThresholds[3], const `Npp16s` rValues[3])
3 channel 16-bit signed short threshold.

- [NppStatus nppiThreshold_GTVal_16s_C3IR](#) ([Npp16s](#) *pSrcDst, int nSrcDstStep, [NppiSize](#) oSizeROI, const [Npp16s](#) rThresholds[3], const [Npp16s](#) rValues[3])
3 channel 16-bit signed short in place threshold.
- [NppStatus nppiThreshold_GTVal_32f_C3R](#) (const [Npp32f](#) *pSrc, int nSrcStep, [Npp32f](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, const [Npp32f](#) rThresholds[3], const [Npp32f](#) rValues[3])
3 channel 32-bit floating point threshold.
- [NppStatus nppiThreshold_GTVal_32f_C3IR](#) ([Npp32f](#) *pSrcDst, int nSrcDstStep, [NppiSize](#) oSizeROI, const [Npp32f](#) rThresholds[3], const [Npp32f](#) rValues[3])
3 channel 32-bit floating point in place threshold.
- [NppStatus nppiThreshold_GTVal_8u_AC4R](#) (const [Npp8u](#) *pSrc, int nSrcStep, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, const [Npp8u](#) rThresholds[3], const [Npp8u](#) rValues[3])
4 channel 8-bit unsigned char image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_GTVal_8u_AC4IR](#) ([Npp8u](#) *pSrcDst, int nSrcDstStep, [NppiSize](#) oSizeROI, const [Npp8u](#) rThresholds[3], const [Npp8u](#) rValues[3])
4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_GTVal_16u_AC4R](#) (const [Npp16u](#) *pSrc, int nSrcStep, [Npp16u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, const [Npp16u](#) rThresholds[3], const [Npp16u](#) rValues[3])
4 channel 16-bit unsigned short image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_GTVal_16u_AC4IR](#) ([Npp16u](#) *pSrcDst, int nSrcDstStep, [NppiSize](#) oSizeROI, const [Npp16u](#) rThresholds[3], const [Npp16u](#) rValues[3])
4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_GTVal_16s_AC4R](#) (const [Npp16s](#) *pSrc, int nSrcStep, [Npp16s](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, const [Npp16s](#) rThresholds[3], const [Npp16s](#) rValues[3])
4 channel 16-bit signed short image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_GTVal_16s_AC4IR](#) ([Npp16s](#) *pSrcDst, int nSrcDstStep, [NppiSize](#) oSizeROI, const [Npp16s](#) rThresholds[3], const [Npp16s](#) rValues[3])
4 channel 16-bit signed short in place image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_GTVal_32f_AC4R](#) (const [Npp32f](#) *pSrc, int nSrcStep, [Npp32f](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, const [Npp32f](#) rThresholds[3], const [Npp32f](#) rValues[3])
4 channel 32-bit floating point image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_GTVal_32f_AC4IR](#) ([Npp32f](#) *pSrcDst, int nSrcDstStep, [NppiSize](#) oSizeROI, const [Npp32f](#) rThresholds[3], const [Npp32f](#) rValues[3])
4 channel 32-bit floating point in place image threshold, not affecting Alpha.
- [NppStatus nppiThreshold_LTVal_8u_C1R](#) (const [Npp8u](#) *pSrc, int nSrcStep, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, const [Npp8u](#) nThreshold, const [Npp8u](#) nValue)
1 channel 8-bit unsigned char threshold.
- [NppStatus nppiThreshold_LTVal_8u_C1IR](#) ([Npp8u](#) *pSrcDst, int nSrcDstStep, [NppiSize](#) oSizeROI, const [Npp8u](#) nThreshold, const [Npp8u](#) nValue)

1 channel 8-bit unsigned char in place threshold.

- `NppStatus nppiThreshold_LTVal_16u_C1R` (const `Npp16u` *pSrc, int nSrcStep, `Npp16u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16u` nThreshold, const `Npp16u` nValue)

1 channel 16-bit unsigned short threshold.

- `NppStatus nppiThreshold_LTVal_16u_C1IR` (`Npp16u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16u` nThreshold, const `Npp16u` nValue)

1 channel 16-bit unsigned short in place threshold.

- `NppStatus nppiThreshold_LTVal_16s_C1R` (const `Npp16s` *pSrc, int nSrcStep, `Npp16s` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16s` nThreshold, const `Npp16s` nValue)

1 channel 16-bit signed short threshold.

- `NppStatus nppiThreshold_LTVal_16s_C1IR` (`Npp16s` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16s` nThreshold, const `Npp16s` nValue)

1 channel 16-bit signed short in place threshold.

- `NppStatus nppiThreshold_LTVal_32f_C1R` (const `Npp32f` *pSrc, int nSrcStep, `Npp32f` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp32f` nThreshold, const `Npp32f` nValue)

1 channel 32-bit floating point threshold.

- `NppStatus nppiThreshold_LTVal_32f_C1IR` (`Npp32f` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp32f` nThreshold, const `Npp32f` nValue)

1 channel 32-bit floating point in place threshold.

- `NppStatus nppiThreshold_LTVal_8u_C3R` (const `Npp8u` *pSrc, int nSrcStep, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholds[3], const `Npp8u` rValues[3])

3 channel 8-bit unsigned char threshold.

- `NppStatus nppiThreshold_LTVal_8u_C3IR` (`Npp8u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholds[3], const `Npp8u` rValues[3])

3 channel 8-bit unsigned char in place threshold.

- `NppStatus nppiThreshold_LTVal_16u_C3R` (const `Npp16u` *pSrc, int nSrcStep, `Npp16u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16u` rThresholds[3], const `Npp16u` rValues[3])

3 channel 16-bit unsigned short threshold.

- `NppStatus nppiThreshold_LTVal_16u_C3IR` (`Npp16u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16u` rThresholds[3], const `Npp16u` rValues[3])

3 channel 16-bit unsigned short in place threshold.

- `NppStatus nppiThreshold_LTVal_16s_C3R` (const `Npp16s` *pSrc, int nSrcStep, `Npp16s` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16s` rThresholds[3], const `Npp16s` rValues[3])

3 channel 16-bit signed short threshold.

- `NppStatus nppiThreshold_LTVal_16s_C3IR` (`Npp16s` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16s` rThresholds[3], const `Npp16s` rValues[3])

3 channel 16-bit signed short in place threshold.

- `NppStatus nppiThreshold_LTVal_32f_C3R` (const `Npp32f *pSrc`, int `nSrcStep`, `Npp32f *pDst`, int `nDstStep`, `NppiSize oSizeROI`, const `Npp32f rThresholds[3]`, const `Npp32f rValues[3]`)
3 channel 32-bit floating point threshold.
- `NppStatus nppiThreshold_LTVal_32f_C3IR` (`Npp32f *pSrcDst`, int `nSrcDstStep`, `NppiSize oSizeROI`, const `Npp32f rThresholds[3]`, const `Npp32f rValues[3]`)
3 channel 32-bit floating point in place threshold.
- `NppStatus nppiThreshold_LTVal_8u_AC4R` (const `Npp8u *pSrc`, int `nSrcStep`, `Npp8u *pDst`, int `nDstStep`, `NppiSize oSizeROI`, const `Npp8u rThresholds[3]`, const `Npp8u rValues[3]`)
4 channel 8-bit unsigned char image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_LTVal_8u_AC4IR` (`Npp8u *pSrcDst`, int `nSrcDstStep`, `NppiSize oSizeROI`, const `Npp8u rThresholds[3]`, const `Npp8u rValues[3]`)
4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_LTVal_16u_AC4R` (const `Npp16u *pSrc`, int `nSrcStep`, `Npp16u *pDst`, int `nDstStep`, `NppiSize oSizeROI`, const `Npp16u rThresholds[3]`, const `Npp16u rValues[3]`)
4 channel 16-bit unsigned short image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_LTVal_16u_AC4IR` (`Npp16u *pSrcDst`, int `nSrcDstStep`, `NppiSize oSizeROI`, const `Npp16u rThresholds[3]`, const `Npp16u rValues[3]`)
4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_LTVal_16s_AC4R` (const `Npp16s *pSrc`, int `nSrcStep`, `Npp16s *pDst`, int `nDstStep`, `NppiSize oSizeROI`, const `Npp16s rThresholds[3]`, const `Npp16s rValues[3]`)
4 channel 16-bit signed short image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_LTVal_16s_AC4IR` (`Npp16s *pSrcDst`, int `nSrcDstStep`, `NppiSize oSizeROI`, const `Npp16s rThresholds[3]`, const `Npp16s rValues[3]`)
4 channel 16-bit signed short in place image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_LTVal_32f_AC4R` (const `Npp32f *pSrc`, int `nSrcStep`, `Npp32f *pDst`, int `nDstStep`, `NppiSize oSizeROI`, const `Npp32f rThresholds[3]`, const `Npp32f rValues[3]`)
4 channel 32-bit floating point image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_LTVal_32f_AC4IR` (`Npp32f *pSrcDst`, int `nSrcDstStep`, `NppiSize oSizeROI`, const `Npp32f rThresholds[3]`, const `Npp32f rValues[3]`)
4 channel 32-bit floating point in place image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_LTValGTVal_8u_C1R` (const `Npp8u *pSrc`, int `nSrcStep`, `Npp8u *pDst`, int `nDstStep`, `NppiSize oSizeROI`, const `Npp8u nThresholdLT`, const `Npp8u nValueLT`, const `Npp8u nThresholdGT`, const `Npp8u nValueGT`)
1 channel 8-bit unsigned char threshold.
- `NppStatus nppiThreshold_LTValGTVal_8u_C1IR` (`Npp8u *pSrcDst`, int `nSrcDstStep`, `NppiSize oSizeROI`, const `Npp8u nThresholdLT`, const `Npp8u nValueLT`, const `Npp8u nThresholdGT`, const `Npp8u nValueGT`)
1 channel 8-bit unsigned char in place threshold.

- `NppStatus nppiThreshold_LTValGTVal_16u_C1R` (const `Npp16u` *pSrc, int nSrcStep, `Npp16u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16u` nThresholdLT, const `Npp16u` nValueLT, const `Npp16u` nThresholdGT, const `Npp16u` nValueGT)

1 channel 16-bit unsigned short threshold.
- `NppStatus nppiThreshold_LTValGTVal_16u_C1IR` (`Npp16u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16u` nThresholdLT, const `Npp16u` nValueLT, const `Npp16u` nThresholdGT, const `Npp16u` nValueGT)

1 channel 16-bit unsigned short in place threshold.
- `NppStatus nppiThreshold_LTValGTVal_16s_C1R` (const `Npp16s` *pSrc, int nSrcStep, `Npp16s` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16s` nThresholdLT, const `Npp16s` nValueLT, const `Npp16s` nThresholdGT, const `Npp16s` nValueGT)

1 channel 16-bit signed short threshold.
- `NppStatus nppiThreshold_LTValGTVal_16s_C1IR` (`Npp16s` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16s` nThresholdLT, const `Npp16s` nValueLT, const `Npp16s` nThresholdGT, const `Npp16s` nValueGT)

1 channel 16-bit signed short in place threshold.
- `NppStatus nppiThreshold_LTValGTVal_32f_C1R` (const `Npp32f` *pSrc, int nSrcStep, `Npp32f` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp32f` nThresholdLT, const `Npp32f` nValueLT, const `Npp32f` nThresholdGT, const `Npp32f` nValueGT)

1 channel 32-bit floating point threshold.
- `NppStatus nppiThreshold_LTValGTVal_32f_C1IR` (`Npp32f` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp32f` nThresholdLT, const `Npp32f` nValueLT, const `Npp32f` nThresholdGT, const `Npp32f` nValueGT)

1 channel 32-bit floating point in place threshold.
- `NppStatus nppiThreshold_LTValGTVal_8u_C3R` (const `Npp8u` *pSrc, int nSrcStep, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholdsLT[3], const `Npp8u` rValuesLT[3], const `Npp8u` rThresholdsGT[3], const `Npp8u` rValuesGT[3])

3 channel 8-bit unsigned char threshold.
- `NppStatus nppiThreshold_LTValGTVal_8u_C3IR` (`Npp8u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholdsLT[3], const `Npp8u` rValuesLT[3], const `Npp8u` rThresholdsGT[3], const `Npp8u` rValuesGT[3])

3 channel 8-bit unsigned char in place threshold.
- `NppStatus nppiThreshold_LTValGTVal_16u_C3R` (const `Npp16u` *pSrc, int nSrcStep, `Npp16u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16u` rThresholdsLT[3], const `Npp16u` rValuesLT[3], const `Npp16u` rThresholdsGT[3], const `Npp16u` rValuesGT[3])

3 channel 16-bit unsigned short threshold.
- `NppStatus nppiThreshold_LTValGTVal_16u_C3IR` (`Npp16u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16u` rThresholdsLT[3], const `Npp16u` rValuesLT[3], const `Npp16u` rThresholdsGT[3], const `Npp16u` rValuesGT[3])

3 channel 16-bit unsigned short in place threshold.

- `NppStatus nppiThreshold_LTValGTVal_16s_C3R` (const `Npp16s` *pSrc, int nSrcStep, `Npp16s` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16s` rThresholdsLT[3], const `Npp16s` rValuesLT[3], const `Npp16s` rThresholdsGT[3], const `Npp16s` rValuesGT[3])
3 channel 16-bit signed short threshold.
- `NppStatus nppiThreshold_LTValGTVal_16s_C3IR` (`Npp16s` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16s` rThresholdsLT[3], const `Npp16s` rValuesLT[3], const `Npp16s` rThresholdsGT[3], const `Npp16s` rValuesGT[3])
3 channel 16-bit signed short in place threshold.
- `NppStatus nppiThreshold_LTValGTVal_32f_C3R` (const `Npp32f` *pSrc, int nSrcStep, `Npp32f` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp32f` rThresholdsLT[3], const `Npp32f` rValuesLT[3], const `Npp32f` rThresholdsGT[3], const `Npp32f` rValuesGT[3])
3 channel 32-bit floating point threshold.
- `NppStatus nppiThreshold_LTValGTVal_32f_C3IR` (`Npp32f` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp32f` rThresholdsLT[3], const `Npp32f` rValuesLT[3], const `Npp32f` rThresholdsGT[3], const `Npp32f` rValuesGT[3])
3 channel 32-bit floating point in place threshold.
- `NppStatus nppiThreshold_LTValGTVal_8u_AC4R` (const `Npp8u` *pSrc, int nSrcStep, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholdsLT[3], const `Npp8u` rValuesLT[3], const `Npp8u` rThresholdsGT[3], const `Npp8u` rValuesGT[3])
4 channel 8-bit unsigned char image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_LTValGTVal_8u_AC4IR` (`Npp8u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp8u` rThresholdsLT[3], const `Npp8u` rValuesLT[3], const `Npp8u` rThresholdsGT[3], const `Npp8u` rValuesGT[3])
4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_LTValGTVal_16u_AC4R` (const `Npp16u` *pSrc, int nSrcStep, `Npp16u` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16u` rThresholdsLT[3], const `Npp16u` rValuesLT[3], const `Npp16u` rThresholdsGT[3], const `Npp16u` rValuesGT[3])
4 channel 16-bit unsigned short image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_LTValGTVal_16u_AC4IR` (`Npp16u` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16u` rThresholdsLT[3], const `Npp16u` rValuesLT[3], const `Npp16u` rThresholdsGT[3], const `Npp16u` rValuesGT[3])
4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_LTValGTVal_16s_AC4R` (const `Npp16s` *pSrc, int nSrcStep, `Npp16s` *pDst, int nDstStep, `NppiSize` oSizeROI, const `Npp16s` rThresholdsLT[3], const `Npp16s` rValuesLT[3], const `Npp16s` rThresholdsGT[3], const `Npp16s` rValuesGT[3])
4 channel 16-bit signed short image threshold, not affecting Alpha.
- `NppStatus nppiThreshold_LTValGTVal_16s_AC4IR` (`Npp16s` *pSrcDst, int nSrcDstStep, `NppiSize` oSizeROI, const `Npp16s` rThresholdsLT[3], const `Npp16s` rValuesLT[3], const `Npp16s` rThresholdsGT[3], const `Npp16s` rValuesGT[3])
4 channel 16-bit signed short in place image threshold, not affecting Alpha.

- `NppStatus nppiThreshold_LTValGTVal_32f_AC4R` (`const Npp32f *pSrc`, `int nSrcStep`, `Npp32f *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholdsLT[3]`, `const Npp32f rValuesLT[3]`, `const Npp32f rThresholdsGT[3]`, `const Npp32f rValuesGT[3]`)

4 channel 32-bit floating point image threshold, not affecting Alpha.

- `NppStatus nppiThreshold_LTValGTVal_32f_AC4IR` (`Npp32f *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp32f rThresholdsLT[3]`, `const Npp32f rValuesLT[3]`, `const Npp32f rThresholdsGT[3]`, `const Npp32f rValuesGT[3]`)

4 channel 32-bit floating point in place image threshold, not affecting Alpha.

7.5.1 Detailed Description

Threshold image pixels.

7.5.2 Function Documentation

7.5.2.1 `NppStatus nppiThreshold_16s_AC4IR` (`Npp16s *pSrcDst`, `int nSrcDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`, `NppCmpOp eComparisonOperation`)

4 channel 16-bit signed short in place image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (`sourcePixel.channel OP nThreshold`) is true, the channel value is set to `nThreshold`, otherwise it is set to `sourcePixel`.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: `NPP_CMP_LESS` and `NPP_CMP_GREATER`.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or `NPP_NOT_SUPPORTED_MODE_ERROR` if an invalid comparison operation type is specified.

7.5.2.2 `NppStatus nppiThreshold_16s_AC4R` (`const Npp16s *pSrc`, `int nSrcStep`, `Npp16s *pDst`, `int nDstStep`, `NppiSize oSizeROI`, `const Npp16s rThresholds[3]`, `NppCmpOp eComparisonOperation`)

4 channel 16-bit signed short image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (`sourcePixel.channel OP nThreshold`) is true, the channel value is set to `nThreshold`, otherwise it is set to `sourcePixel`.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.3 NppStatus nppiThreshold_16s_C1IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s nThreshold, NppCmpOp eComparisonOperation)

1 channel 16-bit signed short in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.4 NppStatus nppiThreshold_16s_C1R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s nThreshold, NppCmpOp eComparisonOperation)

1 channel 16-bit signed short threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI [Region-of-Interest \(ROI\)](#).

nThreshold The threshold value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.5 NppStatus nppiThreshold_16s_C3IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], NppCmpOp eComparisonOperation)

3 channel 16-bit signed short in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.6 NppStatus nppiThreshold_16s_C3R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], NppCmpOp eComparisonOperation)

3 channel 16-bit signed short threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or `NPP_NOT_SUPPORTED_MODE_ERROR` if an invalid comparison operation type is specified.

7.5.2.7 `NppStatus nppiThreshold_16u_AC4IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], NppCmpOp eComparisonOperation)`

4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (`sourcePixel.channel OP nThreshold`) is true, the channel value is set to `nThreshold`, otherwise it is set to `sourcePixel`.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: `NPP_CMP_LESS` and `NPP_CMP_GREATER`.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or `NPP_NOT_SUPPORTED_MODE_ERROR` if an invalid comparison operation type is specified.

7.5.2.8 `NppStatus nppiThreshold_16u_AC4R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], NppCmpOp eComparisonOperation)`

4 channel 16-bit unsigned short image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (`sourcePixel.channel OP nThreshold`) is true, the channel value is set to `nThreshold`, otherwise it is set to `sourcePixel`.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: `NPP_CMP_LESS` and `NPP_CMP_GREATER`.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or `NPP_NOT_SUPPORTED_MODE_ERROR` if an invalid comparison operation type is specified.

7.5.2.9 `NppStatus nppiThreshold_16u_C1IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u nThreshold, NppCmpOp eComparisonOperation)`

1 channel 16-bit unsigned short in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.10 `NppStatus nppiThreshold_16u_C1R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u nThreshold, NppCmpOp eComparisonOperation)`

1 channel 16-bit unsigned short threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.11 `NppStatus nppiThreshold_16u_C3IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], NppCmpOp eComparisonOperation)`

3 channel 16-bit unsigned short in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.12 `NppStatus nppiThreshold_16u_C3R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], NppCmpOp eComparisonOperation)`

3 channel 16-bit unsigned short threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.13 `NppStatus nppiThreshold_32f_AC4IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], NppCmpOp eComparisonOperation)`

4 channel 32-bit floating point in place image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (sourcePixel.channel OP nThreshold) is true, the channel value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.14 NppStatus nppiThreshold_32f_AC4R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], NppCmpOp eComparisonOperation)

4 channel 32-bit floating point image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (sourcePixel.channel OP nThreshold) is true, the channel value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.15 NppStatus nppiThreshold_32f_C1IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f nThreshold, NppCmpOp eComparisonOperation)

1 channel 32-bit floating point in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

nThreshold The threshold value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or `NPP_NOT_SUPPORTED_MODE_ERROR` if an invalid comparison operation type is specified.

7.5.2.16 `NppStatus nppiThreshold_32f_C1R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f nThreshold, NppCmpOp eComparisonOperation)`

1 channel 32-bit floating point threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

nThreshold The threshold value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: `NPP_CMP_LESS` and `NPP_CMP_GREATER`.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or `NPP_NOT_SUPPORTED_MODE_ERROR` if an invalid comparison operation type is specified.

7.5.2.17 `NppStatus nppiThreshold_32f_C3IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], NppCmpOp eComparisonOperation)`

3 channel 32-bit floating point in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: `NPP_CMP_LESS` and `NPP_CMP_GREATER`.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or `NPP_NOT_SUPPORTED_MODE_ERROR` if an invalid comparison operation type is specified.

7.5.2.18 NppStatus nppiThreshold_32f_C3R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], NppCmpOp eComparisonOperation)

3 channel 32-bit floating point threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.19 NppStatus nppiThreshold_8u_AC4IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], NppCmpOp eComparisonOperation)

4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (sourcePixel.channel OP nThreshold) is true, the channel value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.20 `NppStatus nppiThreshold_8u_AC4R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], NppCmpOp eComparisonOperation)`

4 channel 8-bit unsigned char image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (sourcePixel.channel OP nThreshold) is true, the channel value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.21 `NppStatus nppiThreshold_8u_C1IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u nThreshold, NppCmpOp eComparisonOperation)`

1 channel 8-bit unsigned char in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

nThreshold The threshold value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.22 `NppStatus nppiThreshold_8u_C1R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u nThreshold, NppCmpOp eComparisonOperation)`

1 channel 8-bit unsigned char threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

nThreshold The threshold value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.23 `NppStatus nppiThreshold_8u_C3IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], NppCmpOp eComparisonOperation)`

3 channel 8-bit unsigned char in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.24 `NppStatus nppiThreshold_8u_C3R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], NppCmpOp eComparisonOperation)`

3 channel 8-bit unsigned char threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.25 `NppStatus nppiThreshold_GT_16s_AC4IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3])`

4 channel 16-bit signed short in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.26 `NppStatus nppiThreshold_GT_16s_AC4R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3])`

4 channel 16-bit signed short image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.27 `NppStatus nppiThreshold_GT_16s_C1IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s nThreshold)`

1 channel 16-bit signed short in place threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nThreshold The threshold value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.28 `NppStatus nppiThreshold_GT_16s_C1R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s nThreshold)`

1 channel 16-bit signed short threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nThreshold The threshold value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.29 **NppStatus nppiThreshold_GT_16s_C3IR** (Npp16s * *pSrcDst*, int *nSrcDstStep*, NppiSize *oSizeROI*, const Npp16s *rThresholds*[3])

3 channel 16-bit signed short in place threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.30 **NppStatus nppiThreshold_GT_16s_C3R** (const Npp16s * *pSrc*, int *nSrcStep*, Npp16s * *pDst*, int *nDstStep*, NppiSize *oSizeROI*, const Npp16s *rThresholds*[3])

3 channel 16-bit signed short threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.31 **NppStatus nppiThreshold_GT_16u_AC4IR** (Npp16u * *pSrcDst*, int *nSrcDstStep*, NppiSize *oSizeROI*, const Npp16u *rThresholds*[3])

4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.32 NppStatus nppiThreshold_GT_16u_AC4R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3])

4 channel 16-bit unsigned short image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.33 NppStatus nppiThreshold_GT_16u_C1IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u nThreshold)

1 channel 16-bit unsigned short in place threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.34 `NppStatus nppiThreshold_GT_16u_C1R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u nThreshold)`

1 channel 16-bit unsigned short threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrc* Source-Image Pointer.
- nSrcStep* Source-Image Line Step.
- pDst* Destination-Image Pointer.
- nDstStep* Destination-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- nThreshold* The threshold value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.35 `NppStatus nppiThreshold_GT_16u_C3IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3])`

3 channel 16-bit unsigned short in place threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrcDst* In-Place Image Pointer.
- nSrcDstStep* In-Place-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- rThresholds* The threshold values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.36 `NppStatus nppiThreshold_GT_16u_C3R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3])`

3 channel 16-bit unsigned short threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrc* Source-Image Pointer.
- nSrcStep* Source-Image Line Step.

pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.37 **NppStatus nppiThreshold_GT_32f_AC4IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3])**

4 channel 32-bit floating point in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.38 **NppStatus nppiThreshold_GT_32f_AC4R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3])**

4 channel 32-bit floating point image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.39 `NppStatus nppiThreshold_GT_32f_C1IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f nThreshold)`

1 channel 32-bit floating point in place threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.40 `NppStatus nppiThreshold_GT_32f_C1R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f nThreshold)`

1 channel 32-bit floating point threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.41 `NppStatus nppiThreshold_GT_32f_C3IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3])`

3 channel 32-bit floating point in place threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.42 `NppStatus nppiThreshold_GT_32f_C3R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3])`

3 channel 32-bit floating point threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.43 `NppStatus nppiThreshold_GT_8u_AC4IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3])`

4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.44 `NppStatus nppiThreshold_GT_8u_AC4R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3])`

4 channel 8-bit unsigned char image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrc* Source-Image Pointer.
- nSrcStep* Source-Image Line Step.
- pDst* Destination-Image Pointer.
- nDstStep* Destination-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- rThresholds* The threshold values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.45 `NppStatus nppiThreshold_GT_8u_C1IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u nThreshold)`

1 channel 8-bit unsigned char in place threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrcDst* In-Place Image Pointer.
- nSrcDstStep* In-Place-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- nThreshold* The threshold value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.46 `NppStatus nppiThreshold_GT_8u_C1R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u nThreshold)`

1 channel 8-bit unsigned char threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrc* Source-Image Pointer.
- nSrcStep* Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.47 NppStatus nppiThreshold_GT_8u_C3IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3])

3 channel 8-bit unsigned char in place threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.48 NppStatus nppiThreshold_GT_8u_C3R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3])

3 channel 8-bit unsigned char threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.49 NppStatus nppiThreshold_GTVal_16s_AC4IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], const Npp16s rValues[3])

4 channel 16-bit signed short in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.50 NppStatus nppiThreshold_GTVal_16s_AC4R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], const Npp16s rValues[3])

4 channel 16-bit signed short image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.51 NppStatus nppiThreshold_GTVal_16s_C11R (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s nThreshold, const Npp16s nValue)

1 channel 16-bit signed short in place threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nThreshold The threshold value.
nValue The threshold replacement value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.52 NppStatus nppiThreshold_GTVVal_16s_C1R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s nThreshold, const Npp16s nValue)

1 channel 16-bit signed short threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nThreshold The threshold value.
nValue The threshold replacement value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.53 NppStatus nppiThreshold_GTVVal_16s_C3IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], const Npp16s rValues[3])

3 channel 16-bit signed short in place threshold.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.
rValues The threshold replacement values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.54 NppStatus nppiThreshold_GTVVal_16s_C3R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], const Npp16s rValues[3])

3 channel 16-bit signed short threshold.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.55 NppStatus nppiThreshold_GTVVal_16u_AC4IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], const Npp16u rValues[3])

4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.56 NppStatus nppiThreshold_GTVVal_16u_AC4R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], const Npp16u rValues[3])

4 channel 16-bit unsigned short image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.
rValues The threshold replacement values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.57 `NppStatus nppiThreshold_GTVVal_16u_C1IR(Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u nThreshold, const Npp16u nValue)`

1 channel 16-bit unsigned short in place threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nThreshold The threshold value.
nValue The threshold replacement value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.58 `NppStatus nppiThreshold_GTVVal_16u_C1R(const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u nThreshold, const Npp16u nValue)`

1 channel 16-bit unsigned short threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

nValue The threshold replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.59 `NppStatus nppiThreshold_GTVVal_16u_C3IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], const Npp16u rValues[3])`

3 channel 16-bit unsigned short in place threshold.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.60 `NppStatus nppiThreshold_GTVVal_16u_C3R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], const Npp16u rValues[3])`

3 channel 16-bit unsigned short threshold.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.61 `NppStatus nppiThreshold_GTVal_32f_AC4IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], const Npp32f rValues[3])`

4 channel 32-bit floating point in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.62 `NppStatus nppiThreshold_GTVal_32f_AC4R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], const Npp32f rValues[3])`

4 channel 32-bit floating point image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.63 `NppStatus nppiThreshold_GTVal_32f_C1IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f nThreshold, const Npp32f nValue)`

1 channel 32-bit floating point in place threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nThreshold The threshold value.
nValue The threshold replacement values.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.64 **NppStatus nppiThreshold_GTVAl_32f_C1R** (const Npp32f * *pSrc*, int *nSrcStep*, Npp32f * *pDst*, int *nDstStep*, NppiSize *oSizeROI*, const Npp32f *nThreshold*, const Npp32f *nValue*)

1 channel 32-bit floating point threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nThreshold The threshold value.
nValue The threshold replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.65 **NppStatus nppiThreshold_GTVAl_32f_C3IR** (Npp32f * *pSrcDst*, int *nSrcDstStep*, NppiSize *oSizeROI*, const Npp32f *rThresholds*[3], const Npp32f *rValues*[3])

3 channel 32-bit floating point in place threshold.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.
rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.66 `NppStatus nppiThreshold_GTVal_32f_C3R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], const Npp32f rValues[3])`

3 channel 32-bit floating point threshold.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.67 `NppStatus nppiThreshold_GTVal_8u_AC4IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], const Npp8u rValues[3])`

4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.68 `NppStatus nppiThreshold_GTVal_8u_AC4R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], const Npp8u rValues[3])`

4 channel 8-bit unsigned char image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.
rValues The threshold replacement values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.69 **NppStatus nppiThreshold_GTVAl_8u_C1IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u nThreshold, const Npp8u nValue)**

1 channel 8-bit unsigned char in place threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nThreshold The threshold value.
nValue The threshold replacement value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.70 **NppStatus nppiThreshold_GTVAl_8u_C1R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u nThreshold, const Npp8u nValue)**

1 channel 8-bit unsigned char threshold.

If for a comparison operations sourcePixel is greater than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nThreshold The threshold value.

nValue The threshold replacement value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.71 NppStatus nppiThreshold_GTVVal_8u_C3IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], const Npp8u rValues[3])

3 channel 8-bit unsigned char in place threshold.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.72 NppStatus nppiThreshold_GTVVal_8u_C3R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], const Npp8u rValues[3])

3 channel 8-bit unsigned char threshold.

If for a comparison operations sourcePixel is greater than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.73 NppStatus nppiThreshold_LT_16s_AC4IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3])

4 channel 16-bit signed short in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrcDst* In-Place Image Pointer.
- nSrcDstStep* In-Place-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- rThresholds* The threshold values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.74 NppStatus nppiThreshold_LT_16s_AC4R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3])

4 channel 16-bit signed short image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrc* Source-Image Pointer.
- nSrcStep* Source-Image Line Step.
- pDst* Destination-Image Pointer.
- nDstStep* Destination-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- rThresholds* The threshold values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.75 NppStatus nppiThreshold_LT_16s_C1IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s nThreshold)

1 channel 16-bit signed short in place threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrcDst* In-Place Image Pointer.
- nSrcDstStep* In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.76 `NppStatus nppiThreshold_LT_16s_C1R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s nThreshold)`

1 channel 16-bit signed short threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.77 `NppStatus nppiThreshold_LT_16s_C3IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3])`

3 channel 16-bit signed short in place threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.78 `NppStatus nppiThreshold_LT_16s_C3R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3])`

3 channel 16-bit signed short threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.79 `NppStatus nppiThreshold_LT_16u_AC4IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3])`

4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.80 `NppStatus nppiThreshold_LT_16u_AC4R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3])`

4 channel 16-bit unsigned short image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.81 **NppStatus nppiThreshold_LT_16u_C1IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u nThreshold)**

1 channel 16-bit unsigned short in place threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nThreshold The threshold value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.82 **NppStatus nppiThreshold_LT_16u_C1R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u nThreshold)**

1 channel 16-bit unsigned short threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nThreshold The threshold value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.83 `NppStatus nppiThreshold_LT_16u_C3IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3])`

3 channel 16-bit unsigned short in place threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrcDst* In-Place Image Pointer.
- nSrcDstStep* In-Place-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- rThresholds* The threshold values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.84 `NppStatus nppiThreshold_LT_16u_C3R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3])`

3 channel 16-bit unsigned short threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrc* Source-Image Pointer.
- nSrcStep* Source-Image Line Step.
- pDst* Destination-Image Pointer.
- nDstStep* Destination-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- rThresholds* The threshold values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.85 `NppStatus nppiThreshold_LT_32f_AC4IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3])`

4 channel 32-bit floating point in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrcDst* In-Place Image Pointer.
- nSrcDstStep* In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.86 NppStatus nppiThreshold_LT_32f_AC4R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3])

4 channel 32-bit floating point image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.87 NppStatus nppiThreshold_LT_32f_C1IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f nThreshold)

1 channel 32-bit floating point in place threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.88 `NppStatus nppiThreshold_LT_32f_C1R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f nThreshold)`

1 channel 32-bit floating point threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrc* Source-Image Pointer.
- nSrcStep* Source-Image Line Step.
- pDst* Destination-Image Pointer.
- nDstStep* Destination-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- nThreshold* The threshold value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.89 `NppStatus nppiThreshold_LT_32f_C3IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3])`

3 channel 32-bit floating point in place threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrcDst* In-Place Image Pointer.
- nSrcDstStep* In-Place-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- rThresholds* The threshold values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.90 `NppStatus nppiThreshold_LT_32f_C3R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3])`

3 channel 32-bit floating point threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

- pSrc* Source-Image Pointer.
- nSrcStep* Source-Image Line Step.

pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.91 **NppStatus nppiThreshold_LT_8u_AC4IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3])**

4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.92 **NppStatus nppiThreshold_LT_8u_AC4R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3])**

4 channel 8-bit unsigned char image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set value is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.93 `NppStatus nppiThreshold_LT_8u_C1IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u nThreshold)`

1 channel 8-bit unsigned char in place threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.94 `NppStatus nppiThreshold_LT_8u_C1R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u nThreshold)`

1 channel 8-bit unsigned char threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.95 `NppStatus nppiThreshold_LT_8u_C3IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3])`

3 channel 8-bit unsigned char in place threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.96 NppStatus nppiThreshold_LT_8u_C3R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3])

3 channel 8-bit unsigned char threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nThreshold, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.97 NppStatus nppiThreshold_LTVAl_16s_AC4IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], const Npp16s rValues[3])

4 channel 16-bit signed short in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.98 NppStatus nppiThreshold_LTVal_16s_AC4R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], const Npp16s rValues[3])

4 channel 16-bit signed short image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.99 NppStatus nppiThreshold_LTVal_16s_C1IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s nThreshold, const Npp16s nValue)

1 channel 16-bit signed short in place threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

nValue The threshold replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.100 NppStatus nppiThreshold_LTVal_16s_C1R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s nThreshold, const Npp16s nValue)

1 channel 16-bit signed short threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nThreshold The threshold value.
nValue The threshold replacement value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.101 NppStatus nppiThreshold_LTVal_16s_C3IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], const Npp16s rValues[3])

3 channel 16-bit signed short in place threshold.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.
rValues The threshold replacement values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.102 NppStatus nppiThreshold_LTVal_16s_C3R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], const Npp16s rValues[3])

3 channel 16-bit signed short threshold.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.103 `NppStatus nppiThreshold_LTVal_16u_AC4IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], const Npp16u rValues[3])`

4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.104 `NppStatus nppiThreshold_LTVal_16u_AC4R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], const Npp16u rValues[3])`

4 channel 16-bit unsigned short image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.105 `NppStatus nppiThreshold_LTVal_16u_C1IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u nThreshold, const Npp16u nValue)`

1 channel 16-bit unsigned short in place threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

nValue The threshold replacement value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.106 `NppStatus nppiThreshold_LTVal_16u_C1R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u nThreshold, const Npp16u nValue)`

1 channel 16-bit unsigned short threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

nValue The threshold replacement value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.107 `NppStatus nppiThreshold_LTVal_16u_C3IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], const Npp16u rValues[3])`

3 channel 16-bit unsigned short in place threshold.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.
rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.108 `NppStatus nppiThreshold_LTVVal_16u_C3R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], const Npp16u rValues[3])`

3 channel 16-bit unsigned short threshold.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.
rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.109 `NppStatus nppiThreshold_LTVVal_32f_AC4IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], const Npp32f rValues[3])`

4 channel 32-bit floating point in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.
rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.110 `NppStatus nppiThreshold_LTVal_32f_AC4R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], const Npp32f rValues[3])`

4 channel 32-bit floating point image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.111 `NppStatus nppiThreshold_LTVal_32f_C1IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f nThreshold, const Npp32f nValue)`

1 channel 32-bit floating point in place threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

nValue The threshold replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.112 `NppStatus nppiThreshold_LTVal_32f_C1R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f nThreshold, const Npp32f nValue)`

1 channel 32-bit floating point threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nThreshold The threshold value.
nValue The threshold replacement value.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.113 `NppStatus nppiThreshold_LTVal_32f_C3IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], const Npp32f rValues[3])`

3 channel 32-bit floating point in place threshold.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.
nSrcDstStep In-Place-Image Line Step.
oSizeROI Region-of-Interest (ROI).
rThresholds The threshold values, one per color channel.
rValues The threshold replacement values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.114 `NppStatus nppiThreshold_LTVal_32f_C3R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], const Npp32f rValues[3])`

3 channel 32-bit floating point threshold.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.115 `NppStatus nppiThreshold_LTVal_8u_AC4IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], const Npp8u rValues[3])`

4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.116 `NppStatus nppiThreshold_LTVal_8u_AC4R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], const Npp8u rValues[3])`

4 channel 8-bit unsigned char image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set value is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.117 `NppStatus nppiThreshold_LTVal_8u_C1IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u nThreshold, const Npp8u nValue)`

1 channel 8-bit unsigned char in place threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

nValue The threshold replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.118 `NppStatus nppiThreshold_LTVal_8u_C1R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u nThreshold, const Npp8u nValue)`

1 channel 8-bit unsigned char threshold.

If for a comparison operations sourcePixel is less than nThreshold is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

nValue The threshold replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.119 `NppStatus nppiThreshold_LTVal_8u_C3IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], const Npp8u rValues[3])`

3 channel 8-bit unsigned char in place threshold.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.120 `NppStatus nppiThreshold_LTVal_8u_C3R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], const Npp8u rValues[3])`

3 channel 8-bit unsigned char threshold.

If for a comparison operations sourcePixel is less than rThreshold is true, the pixel is set to rValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

Returns:

Image Data Related Error Codes, ROI Related Error Codes.

7.5.2.121 `NppStatus nppiThreshold_LTValGTVal_16s_AC4IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s rThresholdsLT[3], const Npp16s rValuesLT[3], const Npp16s rThresholdsGT[3], const Npp16s rValuesGT[3])`

4 channel 16-bit signed short in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set value is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.122 `NppStatus nppiThreshold_LTValGTVal_16s_AC4R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s rThresholdsLT[3], const Npp16s rValuesLT[3], const Npp16s rThresholdsGT[3], const Npp16s rValuesGT[3])`

4 channel 16-bit signed short image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set value is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.123 `NppStatus nppiThreshold_LTValGTVal_16s_C1IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s nThresholdLT, const Npp16s nValueLT, const Npp16s nThresholdGT, const Npp16s nValueGT)`

1 channel 16-bit signed short in place threshold.

If for a comparison operations sourcePixel is less than nThresholdLT is true, the pixel is set to nValueLT, else if sourcePixel is greater than nThresholdGT the pixel is set to nValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThresholdLT The thresholdLT value.

nValueLT The thresholdLT replacement value.

nThresholdGT The thresholdGT value.

nValueGT The thresholdGT replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.124 `NppStatus nppiThreshold_LTValGTVal_16s_C1R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s nThresholdLT, const Npp16s nValueLT, const Npp16s nThresholdGT, const Npp16s nValueGT)`

1 channel 16-bit signed short threshold.

If for a comparison operations sourcePixel is less than nThresholdLT is true, the pixel is set to nValueLT, else if sourcePixel is greater than nThresholdGT the pixel is set to nValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThresholdLT The thresholdLT value.

nValueLT The thresholdLT replacement value.

nThresholdGT The thresholdGT value.

nValueGT The thresholdGT replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.125 `NppStatus nppiThreshold_LTValGTVal_16s_C3IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s rThresholdsLT[3], const Npp16s rValuesLT[3], const Npp16s rThresholdsGT[3], const Npp16s rValuesGT[3])`

3 channel 16-bit signed short in place threshold.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.126 `NppStatus nppiThreshold_LTValGTVal_16s_C3R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s rThresholdsLT[3], const Npp16s rValuesLT[3], const Npp16s rThresholdsGT[3], const Npp16s rValuesGT[3])`

3 channel 16-bit signed short threshold.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.127 `NppStatus nppiThreshold_LTValGTVal_16u_AC4IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u rThresholdsLT[3], const Npp16u rValuesLT[3], const Npp16u rThresholdsGT[3], const Npp16u rValuesGT[3])`

4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set value is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.128 `NppStatus nppiThreshold_LTValGTVal_16u_AC4R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholdsLT[3], const Npp16u rValuesLT[3], const Npp16u rThresholdsGT[3], const Npp16u rValuesGT[3])`

4 channel 16-bit unsigned short image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set value is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.129 `NppStatus nppiThreshold_LTValGTVal_16u_C1IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u nThresholdLT, const Npp16u nValueLT, const Npp16u nThresholdGT, const Npp16u nValueGT)`

1 channel 16-bit unsigned short in place threshold.

If for a comparison operations sourcePixel is less than nThresholdLT is true, the pixel is set to nValueLT, else if sourcePixel is greater than nThresholdGT the pixel is set to nValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThresholdLT The thresholdLT value.

nValueLT The thresholdLT replacement value.

nThresholdGT The thresholdGT value.

nValueGT The thresholdGT replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.130 NppStatus nppiThreshold_LTValGTVal_16u_C1R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u nThresholdLT, const Npp16u nValueLT, const Npp16u nThresholdGT, const Npp16u nValueGT)

1 channel 16-bit unsigned short threshold.

If for a comparison operations sourcePixel is less than nThresholdLT is true, the pixel is set to nValueLT, else if sourcePixel is greater than nThresholdGT the pixel is set to nValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

nThresholdLT The thresholdLT value.

nValueLT The thresholdLT replacement value.

nThresholdGT The thresholdGT value.

nValueGT The thresholdGT replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.131 NppStatus nppiThreshold_LTValGTVal_16u_C3IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u rThresholdsLT[3], const Npp16u rValuesLT[3], const Npp16u rThresholdsGT[3], const Npp16u rValuesGT[3])

3 channel 16-bit unsigned short in place threshold.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.132 `NppStatus nppiThreshold_LTValGTVal_16u_C3R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholdsLT[3], const Npp16u rValuesLT[3], const Npp16u rThresholdsGT[3], const Npp16u rValuesGT[3])`

3 channel 16-bit unsigned short threshold.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.133 `NppStatus nppiThreshold_LTValGTVal_32f_AC4IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f rThresholdsLT[3], const Npp32f rValuesLT[3], const Npp32f rThresholdsGT[3], const Npp32f rValuesGT[3])`

4 channel 32-bit floating point in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set value is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.134 `NppStatus nppiThreshold_LTValGTVal_32f_AC4R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholdsLT[3], const Npp32f rValuesLT[3], const Npp32f rThresholdsGT[3], const Npp32f rValuesGT[3])`

4 channel 32-bit floating point image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set value is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.135 `NppStatus nppiThreshold_LTValGTVal_32f_C1IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f nThresholdLT, const Npp32f nValueLT, const Npp32f nThresholdGT, const Npp32f nValueGT)`

1 channel 32-bit floating point in place threshold.

If for a comparison operations sourcePixel is less than nThresholdLT is true, the pixel is set to nValueLT, else if sourcePixel is greater than nThresholdGT the pixel is set to nValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

nThresholdLT The thresholdLT value.

nValueLT The thresholdLT replacement value.
nThresholdGT The thresholdGT value.
nValueGT The thresholdGT replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.136 `NppStatus nppiThreshold_LTValGTVal_32f_C1R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f nThresholdLT, const Npp32f nValueLT, const Npp32f nThresholdGT, const Npp32f nValueGT)`

1 channel 32-bit floating point threshold.

If for a comparison operations sourcePixel is less than nThresholdLT is true, the pixel is set to nValueLT, else if sourcePixel is greater than nThresholdGT the pixel is set to nValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).
nSrcStep [Source-Image Line Step](#).
pDst [Destination-Image Pointer](#).
nDstStep [Destination-Image Line Step](#).
oSizeROI [Region-of-Interest \(ROI\)](#).
nThresholdLT The thresholdLT value.
nValueLT The thresholdLT replacement value.
nThresholdGT The thresholdGT value.
nValueGT The thresholdGT replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.137 `NppStatus nppiThreshold_LTValGTVal_32f_C3IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f rThresholdsLT[3], const Npp32f rValuesLT[3], const Npp32f rThresholdsGT[3], const Npp32f rValuesGT[3])`

3 channel 32-bit floating point in place threshold.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).
nSrcDstStep [In-Place-Image Line Step](#).
oSizeROI [Region-of-Interest \(ROI\)](#).
rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.138 `NppStatus nppiThreshold_LTValGTVal_32f_C3R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholdsLT[3], const Npp32f rValuesLT[3], const Npp32f rThresholdsGT[3], const Npp32f rValuesGT[3])`

3 channel 32-bit floating point threshold.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.139 `NppStatus nppiThreshold_LTValGTVal_8u_AC4IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholdsLT[3], const Npp8u rValuesLT[3], const Npp8u rThresholdsGT[3], const Npp8u rValuesGT[3])`

4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set value is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.140 `NppStatus nppiThreshold_LTValGTVal_8u_AC4R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholdsLT[3], const Npp8u rValuesLT[3], const Npp8u rThresholdsGT[3], const Npp8u rValuesGT[3])`

4 channel 8-bit unsigned char image threshold, not affecting Alpha.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set value is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.141 `NppStatus nppiThreshold_LTValGTVal_8u_C1IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u nThresholdLT, const Npp8u nValueLT, const Npp8u nThresholdGT, const Npp8u nValueGT)`

1 channel 8-bit unsigned char in place threshold.

If for a comparison operations sourcePixel is less than nThresholdLT is true, the pixel is set to nValueLT, else if sourcePixel is greater than nThresholdGT the pixel is set to nValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

nThresholdLT The thresholdLT value.

nValueLT The thresholdLT replacement value.
nThresholdGT The thresholdGT value.
nValueGT The thresholdGT replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.142 `NppStatus nppiThreshold_LTValGTVal_8u_C1R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u nThresholdLT, const Npp8u nValueLT, const Npp8u nThresholdGT, const Npp8u nValueGT)`

1 channel 8-bit unsigned char threshold.

If for a comparison operations sourcePixel is less than nThresholdLT is true, the pixel is set to nValueLT, else if sourcePixel is greater than nThresholdGT the pixel is set to nValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).
nSrcStep [Source-Image Line Step](#).
pDst [Destination-Image Pointer](#).
nDstStep [Destination-Image Line Step](#).
oSizeROI [Region-of-Interest \(ROI\)](#).
nThresholdLT The thresholdLT value.
nValueLT The thresholdLT replacement value.
nThresholdGT The thresholdGT value.
nValueGT The thresholdGT replacement value.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.143 `NppStatus nppiThreshold_LTValGTVal_8u_C3IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholdsLT[3], const Npp8u rValuesLT[3], const Npp8u rThresholdsGT[3], const Npp8u rValuesGT[3])`

3 channel 8-bit unsigned char in place threshold.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [Destination-Image Pointer](#).
nSrcDstStep [Destination-Image Line Step](#).
oSizeROI [Region-of-Interest \(ROI\)](#).
rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.144 `NppStatus nppiThreshold_LTValGTVal_8u_C3R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholdsLT[3], const Npp8u rValuesLT[3], const Npp8u rThresholdsGT[3], const Npp8u rValuesGT[3])`

3 channel 8-bit unsigned char threshold.

If for a comparison operations sourcePixel is less than rThresholdLT is true, the pixel is set to rValueLT, else if sourcePixel is greater than rThresholdGT the pixel is set to rValueGT, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholdsLT The thresholdLT values, one per color channel.

rValuesLT The thresholdLT replacement values, one per color channel.

rThresholdsGT The thresholdGT values, one per channel.

rValuesGT The thresholdGT replacement values, one per color channel.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#).

7.5.2.145 `NppStatus nppiThreshold_Val_16s_AC4IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], const Npp16s rValues[3], NppCmpOp eComparisonOperation)`

4 channel 16-bit signed short in place image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (sourcePixel.channel OP nThreshold) is true, the channel value is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.146 `NppStatus nppiThreshold_Val_16s_AC4R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], const Npp16s rValues[3], NppCmpOp eComparisonOperation)`

4 channel 16-bit signed short image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (sourcePixel.channel OP nThreshold) is true, the channel value is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.147 `NppStatus nppiThreshold_Val_16s_C1IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s nThreshold, const Npp16s nValue, NppCmpOp eComparisonOperation)`

1 channel 16-bit signed short in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

nValue The threshold replacement value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.148 `NppStatus nppiThreshold_Val_16s_C1R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s nThreshold, const Npp16s nValue, NppCmpOp eComparisonOperation)`

1 channel 16-bit signed short threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

nValue The threshold replacement value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.149 `NppStatus nppiThreshold_Val_16s_C3IR (Npp16s * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], const Npp16s rValues[3], NppCmpOp eComparisonOperation)`

3 channel 16-bit signed short in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.150 `NppStatus nppiThreshold_Val_16s_C3R (const Npp16s * pSrc, int nSrcStep, Npp16s * pDst, int nDstStep, NppiSize oSizeROI, const Npp16s rThresholds[3], const Npp16s rValues[3], NppCmpOp eComparisonOperation)`

3 channel 16-bit signed short threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.151 `NppStatus nppiThreshold_Val_16u_AC4IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], const Npp16u rValues[3], NppCmpOp eComparisonOperation)`

4 channel 16-bit unsigned short in place image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (sourcePixel.channel OP nThreshold) is true, the channel value is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.152 `NppStatus nppiThreshold_Val_16u_AC4R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], const Npp16u rValues[3], NppCmpOp eComparisonOperation)`

4 channel 16-bit unsigned short image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (sourcePixel.channel OP nThreshold) is true, the channel value is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.153 `NppStatus nppiThreshold_Val_16u_C1IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u nThreshold, const Npp16u nValue, NppCmpOp eComparisonOperation)`

1 channel 16-bit unsigned short in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

nValue The threshold replacement value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.154 `NppStatus nppiThreshold_Val_16u_C1R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u nThreshold, const Npp16u nValue, NppCmpOp eComparisonOperation)`

1 channel 16-bit unsigned short threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

nThreshold The threshold value.

nValue The threshold replacement value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.155 `NppStatus nppiThreshold_Val_16u_C3IR (Npp16u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], const Npp16u rValues[3], NppCmpOp eComparisonOperation)`

3 channel 16-bit unsigned short in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.156 `NppStatus nppiThreshold_Val_16u_C3R (const Npp16u * pSrc, int nSrcStep, Npp16u * pDst, int nDstStep, NppiSize oSizeROI, const Npp16u rThresholds[3], const Npp16u rValues[3], NppCmpOp eComparisonOperation)`

3 channel 16-bit unsigned short threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.157 `NppStatus nppiThreshold_Val_32f_AC4IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], const Npp32f rValues[3], NppCmpOp eComparisonOperation)`

4 channel 32-bit floating point in place image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (sourcePixel.channel OP nThreshold) is true, the channel value is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.158 `NppStatus nppiThreshold_Val_32f_AC4R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], const Npp32f rValues[3], NppCmpOp eComparisonOperation)`

4 channel 32-bit floating point image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (sourcePixel.channel OP nThreshold) is true, the channel value is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.159 `NppStatus nppiThreshold_Val_32f_C1IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f nThreshold, const Npp32f nValue, NppCmpOp eComparisonOperation)`

1 channel 32-bit floating point in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

nValue The threshold replacement value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.160 `NppStatus nppiThreshold_Val_32f_C1R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f nThreshold, const Npp32f nValue, NppCmpOp eComparisonOperation)`

1 channel 32-bit floating point threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

nValue The threshold replacement value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.161 `NppStatus nppiThreshold_Val_32f_C3IR (Npp32f * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], const Npp32f rValues[3], NppCmpOp eComparisonOperation)`

3 channel 32-bit floating point in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.162 NppStatus nppiThreshold_Val_32f_C3R (const Npp32f * pSrc, int nSrcStep, Npp32f * pDst, int nDstStep, NppiSize oSizeROI, const Npp32f rThresholds[3], const Npp32f rValues[3], NppCmpOp eComparisonOperation)

3 channel 32-bit floating point threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.163 NppStatus nppiThreshold_Val_8u_AC4IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], const Npp8u rValues[3], NppCmpOp eComparisonOperation)

4 channel 8-bit unsigned char in place image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (sourcePixel.channel OP nThreshold) is true, the channel value is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.164 `NppStatus nppiThreshold_Val_8u_AC4R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], const Npp8u rValues[3], NppCmpOp eComparisonOperation)`

4 channel 8-bit unsigned char image threshold, not affecting Alpha.

If for a comparison operations OP the predicate (sourcePixel.channel OP nThreshold) is true, the channel value is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.165 `NppStatus nppiThreshold_Val_8u_C1IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u nThreshold, const Npp8u nValue, NppCmpOp eComparisonOperation)`

1 channel 8-bit unsigned char in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst In-Place Image Pointer.

nSrcDstStep In-Place-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nThreshold The threshold value.

nValue The threshold replacement value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.166 `NppStatus nppiThreshold_Val_8u_C1R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u nThreshold, const Npp8u nValue, NppCmpOp eComparisonOperation)`

1 channel 8-bit unsigned char threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc [Source-Image Pointer](#).

nSrcStep [Source-Image Line Step](#).

pDst [Destination-Image Pointer](#).

nDstStep [Destination-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

nThreshold The threshold value.

nValue The threshold replacement value.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#), or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.167 `NppStatus nppiThreshold_Val_8u_C3IR (Npp8u * pSrcDst, int nSrcDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], const Npp8u rValues[3], NppCmpOp eComparisonOperation)`

3 channel 8-bit unsigned char in place threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrcDst [In-Place Image Pointer](#).

nSrcDstStep [In-Place-Image Line Step](#).

oSizeROI [Region-of-Interest \(ROI\)](#).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.5.2.168 `NppStatus nppiThreshold_Val_8u_C3R (const Npp8u * pSrc, int nSrcStep, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, const Npp8u rThresholds[3], const Npp8u rValues[3], NppCmpOp eComparisonOperation)`

3 channel 8-bit unsigned char threshold.

If for a comparison operations OP the predicate (sourcePixel OP nThreshold) is true, the pixel is set to nValue, otherwise it is set to sourcePixel.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

rThresholds The threshold values, one per color channel.

rValues The threshold replacement values, one per color channel.

eComparisonOperation The type of comparison operation to be used. The only valid values are: NPP_CMP_LESS and NPP_CMP_GREATER.

Returns:

Image Data Related Error Codes, ROI Related Error Codes, or NPP_NOT_SUPPORTED_MODE_ERROR if an invalid comparison operation type is specified.

7.6 Compare Operations

Compare the pixels of two images and create a binary result image.

Functions

- [NppStatus nppiCompare_8u_C1R](#) (const [Npp8u](#) *pSrc1, int nSrc1Step, const [Npp8u](#) *pSrc2, int nSrc2Step, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, [NppCmpOp](#) eComparisonOperation)
1 channel 8-bit unsigned char image compare.
- [NppStatus nppiCompare_8u_C3R](#) (const [Npp8u](#) *pSrc1, int nSrc1Step, const [Npp8u](#) *pSrc2, int nSrc2Step, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, [NppCmpOp](#) eComparisonOperation)
3 channel 8-bit unsigned char image compare.
- [NppStatus nppiCompare_8u_C4R](#) (const [Npp8u](#) *pSrc1, int nSrc1Step, const [Npp8u](#) *pSrc2, int nSrc2Step, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, [NppCmpOp](#) eComparisonOperation)
4 channel 8-bit unsigned char image compare.
- [NppStatus nppiCompare_8u_AC4R](#) (const [Npp8u](#) *pSrc1, int nSrc1Step, const [Npp8u](#) *pSrc2, int nSrc2Step, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, [NppCmpOp](#) eComparisonOperation)
4 channel 8-bit unsigned char image compare, not affecting Alpha.
- [NppStatus nppiCompare_16u_C1R](#) (const [Npp16u](#) *pSrc1, int nSrc1Step, const [Npp16u](#) *pSrc2, int nSrc2Step, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, [NppCmpOp](#) eComparisonOperation)
1 channel 16-bit unsigned short image compare.
- [NppStatus nppiCompare_16u_C3R](#) (const [Npp16u](#) *pSrc1, int nSrc1Step, const [Npp16u](#) *pSrc2, int nSrc2Step, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, [NppCmpOp](#) eComparisonOperation)
3 channel 16-bit unsigned short image compare.
- [NppStatus nppiCompare_16u_C4R](#) (const [Npp16u](#) *pSrc1, int nSrc1Step, const [Npp16u](#) *pSrc2, int nSrc2Step, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, [NppCmpOp](#) eComparisonOperation)
4 channel 16-bit unsigned short image compare.
- [NppStatus nppiCompare_16u_AC4R](#) (const [Npp16u](#) *pSrc1, int nSrc1Step, const [Npp16u](#) *pSrc2, int nSrc2Step, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, [NppCmpOp](#) eComparisonOperation)
4 channel 16-bit unsigned short image compare, not affecting Alpha.
- [NppStatus nppiCompare_16s_C1R](#) (const [Npp16s](#) *pSrc1, int nSrc1Step, const [Npp16s](#) *pSrc2, int nSrc2Step, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, [NppCmpOp](#) eComparisonOperation)
1 channel 16-bit signed short image compare.
- [NppStatus nppiCompare_16s_C3R](#) (const [Npp16s](#) *pSrc1, int nSrc1Step, const [Npp16s](#) *pSrc2, int nSrc2Step, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, [NppCmpOp](#) eComparisonOperation)
3 channel 16-bit signed short image compare.
- [NppStatus nppiCompare_16s_C4R](#) (const [Npp16s](#) *pSrc1, int nSrc1Step, const [Npp16s](#) *pSrc2, int nSrc2Step, [Npp8u](#) *pDst, int nDstStep, [NppiSize](#) oSizeROI, [NppCmpOp](#) eComparisonOperation)
4 channel 16-bit signed short image compare.

- `NppStatus nppiCompare_16s_AC4R` (const `Npp16s` *pSrc1, int nSrc1Step, const `Npp16s` *pSrc2, int nSrc2Step, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)
4 channel 16-bit signed short image compare, not affecting Alpha.
- `NppStatus nppiCompare_32f_C1R` (const `Npp32f` *pSrc1, int nSrc1Step, const `Npp32f` *pSrc2, int nSrc2Step, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)
1 channel 32-bit floating point image compare.
- `NppStatus nppiCompare_32f_C3R` (const `Npp32f` *pSrc1, int nSrc1Step, const `Npp32f` *pSrc2, int nSrc2Step, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)
3 channel 32-bit floating point image compare.
- `NppStatus nppiCompare_32f_C4R` (const `Npp32f` *pSrc1, int nSrc1Step, const `Npp32f` *pSrc2, int nSrc2Step, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)
4 channel 32-bit floating point image compare.
- `NppStatus nppiCompare_32f_AC4R` (const `Npp32f` *pSrc1, int nSrc1Step, const `Npp32f` *pSrc2, int nSrc2Step, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)
4 channel 32-bit signed floating point compare, not affecting Alpha.
- `NppStatus nppiCompareC_8u_C1R` (const `Npp8u` *pSrc, int nSrcStep, const `Npp8u` nConstant, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)
1 channel 8-bit unsigned char image compare with constant value.
- `NppStatus nppiCompareC_8u_C3R` (const `Npp8u` *pSrc, int nSrcStep, const `Npp8u` *pConstants, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)
3 channel 8-bit unsigned char image compare with constant value.
- `NppStatus nppiCompareC_8u_C4R` (const `Npp8u` *pSrc, int nSrcStep, const `Npp8u` *pConstants, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)
4 channel 8-bit unsigned char image compare with constant value.
- `NppStatus nppiCompareC_8u_AC4R` (const `Npp8u` *pSrc, int nSrcStep, const `Npp8u` *pConstants, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)
4 channel 8-bit unsigned char image compare, not affecting Alpha.
- `NppStatus nppiCompareC_16u_C1R` (const `Npp16u` *pSrc, int nSrcStep, const `Npp16u` nConstant, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)
1 channel 16-bit unsigned short image compare with constant value.
- `NppStatus nppiCompareC_16u_C3R` (const `Npp16u` *pSrc, int nSrcStep, const `Npp16u` *pConstants, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)
3 channel 16-bit unsigned short image compare with constant value.
- `NppStatus nppiCompareC_16u_C4R` (const `Npp16u` *pSrc, int nSrcStep, const `Npp16u` *pConstants, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)
4 channel 16-bit unsigned short image compare with constant value.

- `NppStatus nppiCompareC_16u_AC4R` (const `Npp16u` *pSrc, int nSrcStep, const `Npp16u` *pConstants, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)

4 channel 16-bit unsigned short image compare, not affecting Alpha.
- `NppStatus nppiCompareC_16s_C1R` (const `Npp16s` *pSrc, int nSrcStep, const `Npp16s` nConstant, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)

1 channel 16-bit signed short image compare with constant value.
- `NppStatus nppiCompareC_16s_C3R` (const `Npp16s` *pSrc, int nSrcStep, const `Npp16s` *pConstants, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)

3 channel 16-bit signed short image compare with constant value.
- `NppStatus nppiCompareC_16s_C4R` (const `Npp16s` *pSrc, int nSrcStep, const `Npp16s` *pConstants, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)

4 channel 16-bit signed short image compare with constant value.
- `NppStatus nppiCompareC_16s_AC4R` (const `Npp16s` *pSrc, int nSrcStep, const `Npp16s` *pConstants, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)

4 channel 16-bit signed short image compare, not affecting Alpha.
- `NppStatus nppiCompareC_32f_C1R` (const `Npp32f` *pSrc, int nSrcStep, const `Npp32f` nConstant, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)

1 channel 32-bit floating point image compare with constant value.
- `NppStatus nppiCompareC_32f_C3R` (const `Npp32f` *pSrc, int nSrcStep, const `Npp32f` *pConstants, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)

3 channel 32-bit floating point image compare with constant value.
- `NppStatus nppiCompareC_32f_C4R` (const `Npp32f` *pSrc, int nSrcStep, const `Npp32f` *pConstants, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)

4 channel 32-bit floating point image compare with constant value.
- `NppStatus nppiCompareC_32f_AC4R` (const `Npp32f` *pSrc, int nSrcStep, const `Npp32f` *pConstants, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `NppCmpOp` eComparisonOperation)

4 channel 32-bit signed floating point compare, not affecting Alpha.
- `NppStatus nppiCompareEqualEps_32f_C1R` (const `Npp32f` *pSrc1, int nSrc1Step, const `Npp32f` *pSrc2, int nSrc2Step, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `Npp32f` nEpsilon)

1 channel 32-bit floating point image compare whether two images are equal within epsilon.
- `NppStatus nppiCompareEqualEps_32f_C3R` (const `Npp32f` *pSrc1, int nSrc1Step, const `Npp32f` *pSrc2, int nSrc2Step, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `Npp32f` nEpsilon)

3 channel 32-bit floating point image compare whether two images are equal within epsilon.
- `NppStatus nppiCompareEqualEps_32f_C4R` (const `Npp32f` *pSrc1, int nSrc1Step, const `Npp32f` *pSrc2, int nSrc2Step, `Npp8u` *pDst, int nDstStep, `NppiSize` oSizeROI, `Npp32f` nEpsilon)

4 channel 32-bit floating point image compare whether two images are equal within epsilon.

- **NppStatus nppiCompareEqualEps_32f_AC4R** (const **Npp32f** *pSrc1, int nSrc1Step, const **Npp32f** *pSrc2, int nSrc2Step, **Npp8u** *pDst, int nDstStep, **NppiSize** oSizeROI, **Npp32f** nEpsilon)
4 channel 32-bit signed floating point compare whether two images are equal within epsilon, not affecting Alpha.
- **NppStatus nppiCompareEqualEpsC_32f_C1R** (const **Npp32f** *pSrc, int nSrcStep, const **Npp32f** nConstant, **Npp8u** *pDst, int nDstStep, **NppiSize** oSizeROI, **Npp32f** nEpsilon)
1 channel 32-bit floating point image compare whether image and constant are equal within epsilon.
- **NppStatus nppiCompareEqualEpsC_32f_C3R** (const **Npp32f** *pSrc, int nSrcStep, const **Npp32f** *pConstants, **Npp8u** *pDst, int nDstStep, **NppiSize** oSizeROI, **Npp32f** nEpsilon)
3 channel 32-bit floating point image compare whether image and constant are equal within epsilon.
- **NppStatus nppiCompareEqualEpsC_32f_C4R** (const **Npp32f** *pSrc, int nSrcStep, const **Npp32f** *pConstants, **Npp8u** *pDst, int nDstStep, **NppiSize** oSizeROI, **Npp32f** nEpsilon)
4 channel 32-bit floating point image compare whether image and constant are equal within epsilon.
- **NppStatus nppiCompareEqualEpsC_32f_AC4R** (const **Npp32f** *pSrc, int nSrcStep, const **Npp32f** *pConstants, **Npp8u** *pDst, int nDstStep, **NppiSize** oSizeROI, **Npp32f** nEpsilon)
4 channel 32-bit signed floating point compare whether image and constant are equal within epsilon, not affecting Alpha.

7.6.1 Detailed Description

Compare the pixels of two images and create a binary result image.

In case of multi-channel image types, the condition must be fulfilled for all channels, otherwise the comparison is considered false. The "binary" result image is of type 8u_C1. False is represented by 0, true by NPP_MAX_8U.

7.6.2 Function Documentation

7.6.2.1 NppStatus nppiCompare_16s_AC4R (const **Npp16s** *pSrc1, int nSrc1Step, const **Npp16s** *pSrc2, int nSrc2Step, **Npp8u** *pDst, int nDstStep, **NppiSize** oSizeROI, **NppCmpOp** eComparisonOperation)

4 channel 16-bit signed short image compare, not affecting Alpha.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

- pSrc1** Source-Image Pointer.
- nSrc1Step** Source-Image Line Step.
- pSrc2** Source-Image Pointer.
- nSrc2Step** Source-Image Line Step.
- pDst** Destination-Image Pointer.
- nDstStep** Destination-Image Line Step.
- oSizeROI** Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.2 `NppStatus nppiCompare_16s_C1R (const Npp16s * pSrc1, int nSrc1Step, const Npp16s * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)`

1 channel 16-bit signed short image compare.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.3 `NppStatus nppiCompare_16s_C3R (const Npp16s * pSrc1, int nSrc1Step, const Npp16s * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)`

3 channel 16-bit signed short image compare.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.4 NppStatus nppiCompare_16s_C4R (const Npp16s * pSrc1, int nSrc1Step, const Npp16s * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 16-bit signed short image compare.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.5 NppStatus nppiCompare_16u_AC4R (const Npp16u * pSrc1, int nSrc1Step, const Npp16u * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 16-bit unsigned short image compare, not affecting Alpha.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.6 `NppStatus nppiCompare_16u_C1R (const Npp16u * pSrc1, int nSrc1Step, const Npp16u * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)`

1 channel 16-bit unsigned short image compare.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.7 `NppStatus nppiCompare_16u_C3R (const Npp16u * pSrc1, int nSrc1Step, const Npp16u * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)`

3 channel 16-bit unsigned short image compare.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.8 NppStatus nppiCompare_16u_C4R (const Npp16u * pSrc1, int nSrc1Step, const Npp16u * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 16-bit unsigned short image compare.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.9 NppStatus nppiCompare_32f_AC4R (const Npp32f * pSrc1, int nSrc1Step, const Npp32f * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 32-bit signed floating point compare, not affecting Alpha.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.10 NppStatus nppiCompare_32f_C1R (const Npp32f * pSrc1, int nSrc1Step, const Npp32f * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

1 channel 32-bit floating point image compare.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.11 NppStatus nppiCompare_32f_C3R (const Npp32f * pSrc1, int nSrc1Step, const Npp32f * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

3 channel 32-bit floating point image compare.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.12 NppStatus nppiCompare_32f_C4R (const Npp32f * pSrc1, int nSrc1Step, const Npp32f * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 32-bit floating point image compare.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.13 NppStatus nppiCompare_8u_AC4R (const Npp8u * pSrc1, int nSrc1Step, const Npp8u * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 8-bit unsigned char image compare, not affecting Alpha.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.14 `NppStatus nppiCompare_8u_C1R (const Npp8u * pSrc1, int nSrc1Step, const Npp8u * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)`

1 channel 8-bit unsigned char image compare.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.15 `NppStatus nppiCompare_8u_C3R (const Npp8u * pSrc1, int nSrc1Step, const Npp8u * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)`

3 channel 8-bit unsigned char image compare.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.16 NppStatus nppiCompare_8u_C4R (const Npp8u * pSrc1, int nSrc1Step, const Npp8u * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 8-bit unsigned char image compare.

Compare pSrc1's pixels with corresponding pixels in pSrc2.

Parameters:

pSrc1 Source-Image Pointer.

nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.17 NppStatus nppiCompareC_16s_AC4R (const Npp16s * pSrc, int nSrcStep, const Npp16s * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 16-bit signed short image compare, not affecting Alpha.

Compare pSrc's pixels with constant value.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pConstants pointer to a list of constants, one per color channel.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.18 NppStatus nppiCompareC_16s_C1R (const Npp16s * pSrc, int nSrcStep, const Npp16s nConstant, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

1 channel 16-bit signed short image compare with constant value.

Compare pSrc's pixels with constant value.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
nConstant constant value.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.19 **NppStatus nppiCompareC_16s_C3R (const Npp16s * pSrc, int nSrcStep, const Npp16s * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)**

3 channel 16-bit signed short image compare with constant value.

Compare pSrc's pixels with constant value.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pConstants pointer to a list of constants, one per color channel.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.20 **NppStatus nppiCompareC_16s_C4R (const Npp16s * pSrc, int nSrcStep, const Npp16s * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)**

4 channel 16-bit signed short image compare with constant value.

Compare pSrc's pixels with constant value.

Parameters:

pSrc Source-Image Pointer.
nSrcStep Source-Image Line Step.
pConstants pointer to a list of constants, one per color channel.
pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.21 NppStatus nppiCompareC_16u_AC4R (const Npp16u * pSrc, int nSrcStep, const Npp16u * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 16-bit unsigned short image compare, not affecting Alpha.

Compare pSrc's pixels with constant value.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pConstants pointer to a list of constants, one per color channel.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.22 NppStatus nppiCompareC_16u_C1R (const Npp16u * pSrc, int nSrcStep, const Npp16u nConstant, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

1 channel 16-bit unsigned short image compare with constant value.

Compare pSrc's pixels with constant value.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

nConstant constant value

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.23 NppStatus nppiCompareC_16u_C3R (const Npp16u * pSrc, int nSrcStep, const Npp16u * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

3 channel 16-bit unsigned short image compare with constant value.

Compare pSrc's pixels with constant value.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pConstants pointer to a list of constants, one per color channel.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.24 NppStatus nppiCompareC_16u_C4R (const Npp16u * pSrc, int nSrcStep, const Npp16u * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 16-bit unsigned short image compare with constant value.

Compare pSrc's pixels with constant value.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pConstants pointer to a list of constants, one per color channel.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.25 NppStatus nppiCompareC_32f_AC4R (const Npp32f * pSrc, int nSrcStep, const Npp32f * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 32-bit signed floating point compare, not affecting Alpha.

Compare pSrc's pixels with constant value.

Parameters:

- pSrc* Source-Image Pointer.
- nSrcStep* Source-Image Line Step.
- pConstants* pointer to a list of constants, one per color channel.
- pDst* Destination-Image Pointer.
- nDstStep* Destination-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- eComparisonOperation* Specifies the comparison operation to be used in the pixel comparison.

Returns:

Image Data Related Error Codes, ROI Related Error Codes

7.6.2.26 **NppStatus nppiCompareC_32f_C1R (const Npp32f * pSrc, int nSrcStep, const Npp32f nConstant, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)**

1 channel 32-bit floating point image compare with constant value.

Compare pSrc's pixels with constant value.

Parameters:

- pSrc* Source-Image Pointer.
- nSrcStep* Source-Image Line Step.
- nConstant* constant value
- pDst* Destination-Image Pointer.
- nDstStep* Destination-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- eComparisonOperation* Specifies the comparison operation to be used in the pixel comparison.

Returns:

Image Data Related Error Codes, ROI Related Error Codes

7.6.2.27 **NppStatus nppiCompareC_32f_C3R (const Npp32f * pSrc, int nSrcStep, const Npp32f * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)**

3 channel 32-bit floating point image compare with constant value.

Compare pSrc's pixels with constant value.

Parameters:

- pSrc* Source-Image Pointer.
- nSrcStep* Source-Image Line Step.
- pConstants* pointer to a list of constants, one per color channel.
- pDst* Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.28 NppStatus nppiCompareC_32f_C4R (const Npp32f * pSrc, int nSrcStep, const Npp32f * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 32-bit floating point image compare with constant value.

Compare pSrc's pixels with constant value.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pConstants pointer to a list of constants, one per color channel.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.29 NppStatus nppiCompareC_8u_AC4R (const Npp8u * pSrc, int nSrcStep, const Npp8u * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 8-bit unsigned char image compare, not affecting Alpha.

Compare pSrc's pixels with constant value.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pConstants pointer to a list of constants, one per color channel.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.30 NppStatus nppiCompareC_8u_C1R (const Npp8u * pSrc, int nSrcStep, const Npp8u nConstant, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

1 channel 8-bit unsigned char image compare with constant value.

Compare pSrc's pixels with constant value.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

nConstant constant value.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.31 NppStatus nppiCompareC_8u_C3R (const Npp8u * pSrc, int nSrcStep, const Npp8u * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

3 channel 8-bit unsigned char image compare with constant value.

Compare pSrc's pixels with constant value.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pConstants pointer to a list of constant values, one per color channel..

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

eComparisonOperation Specifies the comparison operation to be used in the pixel comparison.

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.32 NppStatus nppiCompareC_8u_C4R (const Npp8u * pSrc, int nSrcStep, const Npp8u * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, NppCmpOp eComparisonOperation)

4 channel 8-bit unsigned char image compare with constant value.

Compare pSrc's pixels with constant value.

Parameters:

- pSrc* Source-Image Pointer.
- nSrcStep* Source-Image Line Step.
- pConstants* pointer to a list of constants, one per color channel.
- pDst* Destination-Image Pointer.
- nDstStep* Destination-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- eComparisonOperation* Specifies the comparison operation to be used in the pixel comparison.

Returns:

Image Data Related Error Codes, ROI Related Error Codes

7.6.2.33 NppStatus nppiCompareEqualEps_32f_AC4R (const Npp32f * pSrc1, int nSrc1Step, const Npp32f * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, Npp32f nEpsilon)

4 channel 32-bit signed floating point compare whether two images are equal within epsilon, not affecting Alpha.

Compare pSrc1's pixels with corresponding pixels in pSrc2 to determine whether they are equal with a difference of epsilon.

Parameters:

- pSrc1* Source-Image Pointer.
- nSrc1Step* Source-Image Line Step.
- pSrc2* Source-Image Pointer.
- nSrc2Step* Source-Image Line Step.
- pDst* Destination-Image Pointer.
- nDstStep* Destination-Image Line Step.
- oSizeROI* Region-of-Interest (ROI).
- nEpsilon* epsilon tolerance value to compare to per color channel pixel absolute differences

Returns:

Image Data Related Error Codes, ROI Related Error Codes

7.6.2.34 NppStatus nppiCompareEqualEps_32f_C1R (const Npp32f * pSrc1, int nSrc1Step, const Npp32f * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, Npp32f nEpsilon)

1 channel 32-bit floating point image compare whether two images are equal within epsilon.

Compare pSrc1's pixels with corresponding pixels in pSrc2 to determine whether they are equal with a difference of epsilon.

Parameters:

- pSrc1* Source-Image Pointer.

nSrc1Step Source-Image Line Step.
pSrc2 Source-Image Pointer.
nSrc2Step Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nEpsilon epsilon tolerance value to compare to pixel absolute differences

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.35 `NppStatus nppiCompareEqualEps_32f_C3R (const Npp32f * pSrc1, int nSrc1Step, const Npp32f * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, Npp32f nEpsilon)`

3 channel 32-bit floating point image compare whether two images are equal within epsilon.

Compare pSrc1's pixels with corresponding pixels in pSrc2 to determine whether they are equal with a difference of epsilon.

Parameters:

pSrc1 Source-Image Pointer.
nSrc1Step Source-Image Line Step.
pSrc2 Source-Image Pointer.
nSrc2Step Source-Image Line Step.
pDst Destination-Image Pointer.
nDstStep Destination-Image Line Step.
oSizeROI Region-of-Interest (ROI).
nEpsilon epsilon tolerance value to compare to per color channel pixel absolute differences

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.36 `NppStatus nppiCompareEqualEps_32f_C4R (const Npp32f * pSrc1, int nSrc1Step, const Npp32f * pSrc2, int nSrc2Step, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, Npp32f nEpsilon)`

4 channel 32-bit floating point image compare whether two images are equal within epsilon.

Compare pSrc1's pixels with corresponding pixels in pSrc2 to determine whether they are equal with a difference of epsilon.

Parameters:

pSrc1 Source-Image Pointer.
nSrc1Step Source-Image Line Step.

pSrc2 Source-Image Pointer.

nSrc2Step Source-Image Line Step.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nEpsilon epsilon tolerance value to compare to per color channel pixel absolute differences

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.37 `NppStatus nppiCompareEqualEpsC_32f_AC4R (const Npp32f * pSrc, int nSrcStep, const Npp32f * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, Npp32f nEpsilon)`

4 channel 32-bit signed floating point compare whether image and constant are equal within epsilon, not affecting Alpha.

Compare pSrc's pixels with constant value to determine whether they are equal within a difference of epsilon.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pConstants pointer to a list of constants, one per color channel.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nEpsilon epsilon tolerance value to compare to per color channel pixel absolute differences

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.38 `NppStatus nppiCompareEqualEpsC_32f_C1R (const Npp32f * pSrc, int nSrcStep, const Npp32f nConstant, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, Npp32f nEpsilon)`

1 channel 32-bit floating point image compare whether image and constant are equal within epsilon.

Compare pSrc's pixels with constant value to determine whether they are equal within a difference of epsilon.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

nConstant constant value

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nEpsilon epsilon tolerance value to compare to pixel absolute differences

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.39 NppStatus nppiCompareEqualEpsC_32f_C3R (const Npp32f * pSrc, int nSrcStep, const Npp32f * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, Npp32f nEpsilon)

3 channel 32-bit floating point image compare whether image and constant are equal within epsilon.

Compare pSrc's pixels with constant value to determine whether they are equal within a difference of epsilon.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pConstants pointer to a list of constants, one per color channel.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nEpsilon epsilon tolerance value to compare to per color channel pixel absolute differences

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

7.6.2.40 NppStatus nppiCompareEqualEpsC_32f_C4R (const Npp32f * pSrc, int nSrcStep, const Npp32f * pConstants, Npp8u * pDst, int nDstStep, NppiSize oSizeROI, Npp32f nEpsilon)

4 channel 32-bit floating point image compare whether image and constant are equal within epsilon.

Compare pSrc's pixels with constant value to determine whether they are equal within a difference of epsilon.

Parameters:

pSrc Source-Image Pointer.

nSrcStep Source-Image Line Step.

pConstants pointer to a list of constants, one per color channel.

pDst Destination-Image Pointer.

nDstStep Destination-Image Line Step.

oSizeROI Region-of-Interest (ROI).

nEpsilon epsilon tolerance value to compare to per color channel pixel absolute differences

Returns:

[Image Data Related Error Codes](#), [ROI Related Error Codes](#)

Chapter 8

Data Structure Documentation

8.1 NPP_ALIGN_16 Struct Reference

Complex Number This struct represents a long long complex number.

```
#include <nppdefs.h>
```

Data Fields

- [Npp64s re](#)
Real part.
- [Npp64s im](#)
Imaginary part.
- [Npp64f re](#)
Real part.
- [Npp64f im](#)
Imaginary part.

8.1.1 Detailed Description

Complex Number This struct represents a long long complex number.

Complex Number This struct represents a double floating-point complex number.

8.1.2 Field Documentation

8.1.2.1 Npp64f NPP_ALIGN_16::im

Imaginary part.

8.1.2.2 Npp64s NPP_ALIGN_16::im

Imaginary part.

8.1.2.3 Npp64f NPP_ALIGN_16::re

Real part.

8.1.2.4 Npp64s NPP_ALIGN_16::re

Real part.

The documentation for this struct was generated from the following file:

- C:/src/sw/rel/gpgpu/toolkit/r8.0/NPP/npp/include/nppdefs.h

8.2 NPP_ALIGN_8 Struct Reference

Complex Number This struct represents an unsigned int complex number.

```
#include <nppdefs.h>
```

Data Fields

- [Npp32u re](#)
Real part.
- [Npp32u im](#)
Imaginary part.
- [Npp32s re](#)
Real part.
- [Npp32s im](#)
Imaginary part.
- [Npp32f re](#)
Real part.
- [Npp32f im](#)
Imaginary part.

8.2.1 Detailed Description

Complex Number This struct represents an unsigned int complex number.

Complex Number This struct represents a single floating-point complex number.

Complex Number This struct represents a signed int complex number.

8.2.2 Field Documentation

8.2.2.1 Npp32f NPP_ALIGN_8::im

Imaginary part.

8.2.2.2 Npp32s NPP_ALIGN_8::im

Imaginary part.

8.2.2.3 Npp32u NPP_ALIGN_8::im

Imaginary part.

8.2.2.4 Npp32f NPP_ALIGN_8::re

Real part.

8.2.2.5 Npp32s NPP_ALIGN_8::re

Real part.

8.2.2.6 Npp32u NPP_ALIGN_8::re

Real part.

The documentation for this struct was generated from the following file:

- C:/src/sw/rel/gpgpu/toolkit/r8.0/NPP/npp/include/nppdefs.h

8.3 NppiHaarBuffer Struct Reference

```
#include <nppdefs.h>
```

Data Fields

- int `haarBufferSize`
size of the buffer
- `Npp32s * haarBuffer`
buffer

8.3.1 Field Documentation

8.3.1.1 `Npp32s* NppiHaarBuffer::haarBuffer`

buffer

8.3.1.2 `int NppiHaarBuffer::haarBufferSize`

size of the buffer

The documentation for this struct was generated from the following file:

- `C:/src/sw/rel/gpgpu/toolkit/r8.0/NPP/npp/include/nppdefs.h`

8.4 NppiHaarClassifier_32f Struct Reference

```
#include <nppdefs.h>
```

Data Fields

- int `numClassifiers`
number of classifiers
- `Npp32s * classifiers`
packed classifier data 40 bytes each
- `size_t classifierStep`
- `NppiSize classifierSize`
- `Npp32s * counterDevice`

8.4.1 Field Documentation

8.4.1.1 `Npp32s* NppiHaarClassifier_32f::classifiers`

packed classifier data 40 bytes each

8.4.1.2 `NppiSize NppiHaarClassifier_32f::classifierSize`

8.4.1.3 `size_t NppiHaarClassifier_32f::classifierStep`

8.4.1.4 `Npp32s* NppiHaarClassifier_32f::counterDevice`

8.4.1.5 `int NppiHaarClassifier_32f::numClassifiers`

number of classifiers

The documentation for this struct was generated from the following file:

- `C:/src/sw/rel/gpgpu/toolkit/r8.0/NPP/npp/include/nppdefs.h`

8.5 NppiPoint Struct Reference

2D Point

```
#include <nppdefs.h>
```

Data Fields

- `int x`
x-coordinate.
- `int y`
y-coordinate.

8.5.1 Detailed Description

2D Point

8.5.2 Field Documentation

8.5.2.1 `int NppiPoint::x`

x-coordinate.

8.5.2.2 `int NppiPoint::y`

y-coordinate.

The documentation for this struct was generated from the following file:

- `C:/src/sw/rel/gpgpu/toolkit/r8.0/NPP/npp/include/nppdefs.h`

8.6 NppiRect Struct Reference

2D Rectangle This struct contains position and size information of a rectangle in two space.

```
#include <nppdefs.h>
```

Data Fields

- `int x`
x-coordinate of upper left corner (lowest memory address).
- `int y`
y-coordinate of upper left corner (lowest memory address).
- `int width`
Rectangle width.
- `int height`
Rectangle height.

8.6.1 Detailed Description

2D Rectangle This struct contains position and size information of a rectangle in two space.

The rectangle's position is usually signified by the coordinate of its upper-left corner.

8.6.2 Field Documentation

8.6.2.1 `int NppiRect::height`

Rectangle height.

8.6.2.2 `int NppiRect::width`

Rectangle width.

8.6.2.3 `int NppiRect::x`

x-coordinate of upper left corner (lowest memory address).

8.6.2.4 `int NppiRect::y`

y-coordinate of upper left corner (lowest memory address).

The documentation for this struct was generated from the following file:

- `C:/src/sw/rel/gpgpu/toolkit/r8.0/NPP/npp/include/nppdefs.h`

8.7 NppiSize Struct Reference

2D Size This struct typically represents the size of a rectangular region in two space.

```
#include <nppdefs.h>
```

Data Fields

- `int width`
Rectangle width.
- `int height`
Rectangle height.

8.7.1 Detailed Description

2D Size This struct typically represents the size of a rectangular region in two space.

8.7.2 Field Documentation

8.7.2.1 `int NppiSize::height`

Rectangle height.

8.7.2.2 `int NppiSize::width`

Rectangle width.

The documentation for this struct was generated from the following file:

- `C:/src/sw/rel/gpgpu/toolkit/r8.0/NPP/npp/include/nppdefs.h`

8.8 NppLibraryVersion Struct Reference

```
#include <nppdefs.h>
```

Data Fields

- int `major`
Major version number.
- int `minor`
Minor version number.
- int `build`
Build number.

8.8.1 Field Documentation

8.8.1.1 int NppLibraryVersion::build

Build number.

This reflects the nightly build this release was made from.

8.8.1.2 int NppLibraryVersion::major

Major version number.

8.8.1.3 int NppLibraryVersion::minor

Minor version number.

The documentation for this struct was generated from the following file:

- `C:/src/sw/rel/gpgpu/toolkit/r8.0/NPP/npp/include/nppdefs.h`

Index

- `__align__`
 - `npp_basic_types`, 48, 49
- Basic NPP Data Types, 46
- build
 - `NppLibraryVersion`, 172
- classifiers
 - `NppiHaarClassifier_32f`, 168
- classifierSize
 - `NppiHaarClassifier_32f`, 168
- classifierStep
 - `NppiHaarClassifier_32f`, 168
- Compare Operations, 140
- core_npp
 - `nppGetGpuComputeCapability`, 28
 - `nppGetGpuDeviceProperties`, 28
 - `nppGetGpuName`, 28
 - `nppGetGpuNumSMs`, 28
 - `nppGetLibVersion`, 28
 - `nppGetMaxThreadsPerBlock`, 29
 - `nppGetMaxThreadsPerSM`, 29
 - `nppGetStream`, 29
 - `nppGetStreamMaxThreadsPerSM`, 29
 - `nppGetStreamNumSMs`, 29
 - `nppSetStream`, 29
- counterDevice
 - `NppiHaarClassifier_32f`, 168
- haarBuffer
 - `NppiHaarBuffer`, 167
- haarBufferSize
 - `NppiHaarBuffer`, 167
- height
 - `NppiRect`, 170
 - `NppiSize`, 171
- im
 - `NPP_ALIGN_16`, 163
 - `NPP_ALIGN_8`, 165
- image_compare_operations
 - `nppiCompare_16s_AC4R`, 143
 - `nppiCompare_16s_C1R`, 144
 - `nppiCompare_16s_C3R`, 144
 - `nppiCompare_16s_C4R`, 144
 - `nppiCompare_16u_AC4R`, 145
 - `nppiCompare_16u_C1R`, 145
 - `nppiCompare_16u_C3R`, 146
 - `nppiCompare_16u_C4R`, 146
 - `nppiCompare_32f_AC4R`, 147
 - `nppiCompare_32f_C1R`, 147
 - `nppiCompare_32f_C3R`, 148
 - `nppiCompare_32f_C4R`, 148
 - `nppiCompare_8u_AC4R`, 149
 - `nppiCompare_8u_C1R`, 149
 - `nppiCompare_8u_C3R`, 150
 - `nppiCompare_8u_C4R`, 150
 - `nppiCompareC_16s_AC4R`, 151
 - `nppiCompareC_16s_C1R`, 151
 - `nppiCompareC_16s_C3R`, 152
 - `nppiCompareC_16s_C4R`, 152
 - `nppiCompareC_16u_AC4R`, 153
 - `nppiCompareC_16u_C1R`, 153
 - `nppiCompareC_16u_C3R`, 153
 - `nppiCompareC_16u_C4R`, 154
 - `nppiCompareC_32f_AC4R`, 154
 - `nppiCompareC_32f_C1R`, 155
 - `nppiCompareC_32f_C3R`, 155
 - `nppiCompareC_32f_C4R`, 156
 - `nppiCompareC_8u_AC4R`, 156
 - `nppiCompareC_8u_C1R`, 156
 - `nppiCompareC_8u_C3R`, 157
 - `nppiCompareC_8u_C4R`, 157
 - `nppiCompareEqualEps_32f_AC4R`, 158
 - `nppiCompareEqualEps_32f_C1R`, 158
 - `nppiCompareEqualEps_32f_C3R`, 159
 - `nppiCompareEqualEps_32f_C4R`, 159
 - `nppiCompareEqualEpsC_32f_AC4R`, 160
 - `nppiCompareEqualEpsC_32f_C1R`, 160
 - `nppiCompareEqualEpsC_32f_C3R`, 161
 - `nppiCompareEqualEpsC_32f_C4R`, 161
- image_threshold_operations
 - `nppiThreshold_16s_AC4IR`, 65
 - `nppiThreshold_16s_AC4R`, 65
 - `nppiThreshold_16s_C1IR`, 66
 - `nppiThreshold_16s_C1R`, 66
 - `nppiThreshold_16s_C3IR`, 67
 - `nppiThreshold_16s_C3R`, 67
 - `nppiThreshold_16u_AC4IR`, 68
 - `nppiThreshold_16u_AC4R`, 68
 - `nppiThreshold_16u_C1IR`, 68

- nppiThreshold_16u_C1R, 69
 nppiThreshold_16u_C3IR, 69
 nppiThreshold_16u_C3R, 70
 nppiThreshold_32f_AC4IR, 70
 nppiThreshold_32f_AC4R, 71
 nppiThreshold_32f_C1IR, 71
 nppiThreshold_32f_C1R, 72
 nppiThreshold_32f_C3IR, 72
 nppiThreshold_32f_C3R, 72
 nppiThreshold_8u_AC4IR, 73
 nppiThreshold_8u_AC4R, 73
 nppiThreshold_8u_C1IR, 74
 nppiThreshold_8u_C1R, 74
 nppiThreshold_8u_C3IR, 75
 nppiThreshold_8u_C3R, 75
 nppiThreshold_GT_16s_AC4IR, 76
 nppiThreshold_GT_16s_AC4R, 76
 nppiThreshold_GT_16s_C1IR, 77
 nppiThreshold_GT_16s_C1R, 77
 nppiThreshold_GT_16s_C3IR, 77
 nppiThreshold_GT_16s_C3R, 78
 nppiThreshold_GT_16u_AC4IR, 78
 nppiThreshold_GT_16u_AC4R, 79
 nppiThreshold_GT_16u_C1IR, 79
 nppiThreshold_GT_16u_C1R, 79
 nppiThreshold_GT_16u_C3IR, 80
 nppiThreshold_GT_16u_C3R, 80
 nppiThreshold_GT_32f_AC4IR, 81
 nppiThreshold_GT_32f_AC4R, 81
 nppiThreshold_GT_32f_C1IR, 81
 nppiThreshold_GT_32f_C1R, 82
 nppiThreshold_GT_32f_C3IR, 82
 nppiThreshold_GT_32f_C3R, 83
 nppiThreshold_GT_8u_AC4IR, 83
 nppiThreshold_GT_8u_AC4R, 83
 nppiThreshold_GT_8u_C1IR, 84
 nppiThreshold_GT_8u_C1R, 84
 nppiThreshold_GT_8u_C3IR, 85
 nppiThreshold_GT_8u_C3R, 85
 nppiThreshold_GTVVal_16s_AC4IR, 85
 nppiThreshold_GTVVal_16s_AC4R, 86
 nppiThreshold_GTVVal_16s_C1IR, 86
 nppiThreshold_GTVVal_16s_C1R, 87
 nppiThreshold_GTVVal_16s_C3IR, 87
 nppiThreshold_GTVVal_16s_C3R, 87
 nppiThreshold_GTVVal_16u_AC4IR, 88
 nppiThreshold_GTVVal_16u_AC4R, 88
 nppiThreshold_GTVVal_16u_C1IR, 89
 nppiThreshold_GTVVal_16u_C1R, 89
 nppiThreshold_GTVVal_16u_C3IR, 90
 nppiThreshold_GTVVal_16u_C3R, 90
 nppiThreshold_GTVVal_32f_AC4IR, 90
 nppiThreshold_GTVVal_32f_AC4R, 91
 nppiThreshold_GTVVal_32f_C1IR, 91
 nppiThreshold_GTVVal_32f_C1R, 92
 nppiThreshold_GTVVal_32f_C3IR, 92
 nppiThreshold_GTVVal_32f_C3R, 92
 nppiThreshold_GTVVal_8u_AC4IR, 93
 nppiThreshold_GTVVal_8u_AC4R, 93
 nppiThreshold_GTVVal_8u_C1IR, 94
 nppiThreshold_GTVVal_8u_C1R, 94
 nppiThreshold_GTVVal_8u_C3IR, 95
 nppiThreshold_GTVVal_8u_C3R, 95
 nppiThreshold_LT_16s_AC4IR, 95
 nppiThreshold_LT_16s_AC4R, 96
 nppiThreshold_LT_16s_C1IR, 96
 nppiThreshold_LT_16s_C1R, 97
 nppiThreshold_LT_16s_C3IR, 97
 nppiThreshold_LT_16s_C3R, 97
 nppiThreshold_LT_16u_AC4IR, 98
 nppiThreshold_LT_16u_AC4R, 98
 nppiThreshold_LT_16u_C1IR, 99
 nppiThreshold_LT_16u_C1R, 99
 nppiThreshold_LT_16u_C3IR, 99
 nppiThreshold_LT_16u_C3R, 100
 nppiThreshold_LT_32f_AC4IR, 100
 nppiThreshold_LT_32f_AC4R, 101
 nppiThreshold_LT_32f_C1IR, 101
 nppiThreshold_LT_32f_C1R, 101
 nppiThreshold_LT_32f_C3IR, 102
 nppiThreshold_LT_32f_C3R, 102
 nppiThreshold_LT_8u_AC4IR, 103
 nppiThreshold_LT_8u_AC4R, 103
 nppiThreshold_LT_8u_C1IR, 103
 nppiThreshold_LT_8u_C1R, 104
 nppiThreshold_LT_8u_C3IR, 104
 nppiThreshold_LT_8u_C3R, 105
 nppiThreshold_LTVVal_16s_AC4IR, 105
 nppiThreshold_LTVVal_16s_AC4R, 105
 nppiThreshold_LTVVal_16s_C1IR, 106
 nppiThreshold_LTVVal_16s_C1R, 106
 nppiThreshold_LTVVal_16s_C3IR, 107
 nppiThreshold_LTVVal_16s_C3R, 107
 nppiThreshold_LTVVal_16u_AC4IR, 108
 nppiThreshold_LTVVal_16u_AC4R, 108
 nppiThreshold_LTVVal_16u_C1IR, 108
 nppiThreshold_LTVVal_16u_C1R, 109
 nppiThreshold_LTVVal_16u_C3IR, 109
 nppiThreshold_LTVVal_16u_C3R, 110
 nppiThreshold_LTVVal_32f_AC4IR, 110
 nppiThreshold_LTVVal_32f_AC4R, 110
 nppiThreshold_LTVVal_32f_C1IR, 111
 nppiThreshold_LTVVal_32f_C1R, 111
 nppiThreshold_LTVVal_32f_C3IR, 112
 nppiThreshold_LTVVal_32f_C3R, 112
 nppiThreshold_LTVVal_8u_AC4IR, 113
 nppiThreshold_LTVVal_8u_AC4R, 113
 nppiThreshold_LTVVal_8u_C1IR, 113

- nppiThreshold_LTVal_8u_C1R, 114
- nppiThreshold_LTVal_8u_C3IR, 114
- nppiThreshold_LTVal_8u_C3R, 115
- nppiThreshold_LTValGTVal_16s_AC4IR, 115
- nppiThreshold_LTValGTVal_16s_AC4R, 116
- nppiThreshold_LTValGTVal_16s_C1IR, 116
- nppiThreshold_LTValGTVal_16s_C1R, 117
- nppiThreshold_LTValGTVal_16s_C3IR, 117
- nppiThreshold_LTValGTVal_16s_C3R, 118
- nppiThreshold_LTValGTVal_16u_AC4IR, 118
- nppiThreshold_LTValGTVal_16u_AC4R, 119
- nppiThreshold_LTValGTVal_16u_C1IR, 119
- nppiThreshold_LTValGTVal_16u_C1R, 120
- nppiThreshold_LTValGTVal_16u_C3IR, 120
- nppiThreshold_LTValGTVal_16u_C3R, 121
- nppiThreshold_LTValGTVal_32f_AC4IR, 121
- nppiThreshold_LTValGTVal_32f_AC4R, 122
- nppiThreshold_LTValGTVal_32f_C1IR, 122
- nppiThreshold_LTValGTVal_32f_C1R, 123
- nppiThreshold_LTValGTVal_32f_C3IR, 123
- nppiThreshold_LTValGTVal_32f_C3R, 124
- nppiThreshold_LTValGTVal_8u_AC4IR, 124
- nppiThreshold_LTValGTVal_8u_AC4R, 125
- nppiThreshold_LTValGTVal_8u_C1IR, 125
- nppiThreshold_LTValGTVal_8u_C1R, 126
- nppiThreshold_LTValGTVal_8u_C3IR, 126
- nppiThreshold_LTValGTVal_8u_C3R, 127
- nppiThreshold_Val_16s_AC4IR, 127
- nppiThreshold_Val_16s_AC4R, 128
- nppiThreshold_Val_16s_C1IR, 128
- nppiThreshold_Val_16s_C1R, 129
- nppiThreshold_Val_16s_C3IR, 129
- nppiThreshold_Val_16s_C3R, 130
- nppiThreshold_Val_16u_AC4IR, 130
- nppiThreshold_Val_16u_AC4R, 131
- nppiThreshold_Val_16u_C1IR, 131
- nppiThreshold_Val_16u_C1R, 132
- nppiThreshold_Val_16u_C3IR, 132
- nppiThreshold_Val_16u_C3R, 133
- nppiThreshold_Val_32f_AC4IR, 133
- nppiThreshold_Val_32f_AC4R, 134
- nppiThreshold_Val_32f_C1IR, 134
- nppiThreshold_Val_32f_C1R, 135
- nppiThreshold_Val_32f_C3IR, 135
- nppiThreshold_Val_32f_C3R, 136
- nppiThreshold_Val_8u_AC4IR, 136
- nppiThreshold_Val_8u_AC4R, 137
- nppiThreshold_Val_8u_C1IR, 137
- nppiThreshold_Val_8u_C1R, 138
- nppiThreshold_Val_8u_C3IR, 138
- nppiThreshold_Val_8u_C3R, 139
- NppLibraryVersion, 172
- minor
 - NppLibraryVersion, 172
- NPP Core, 27
- NPP Type Definitions and Constants, 31
- Npp16s
 - npp_basic_types, 47
- Npp16sc
 - npp_basic_types, 49
- Npp16u
 - npp_basic_types, 47
- Npp16uc
 - npp_basic_types, 49
- Npp32f
 - npp_basic_types, 47
- Npp32fc
 - npp_basic_types, 47
- Npp32s
 - npp_basic_types, 47
- Npp32sc
 - npp_basic_types, 47
- Npp32u
 - npp_basic_types, 48
- Npp32uc
 - npp_basic_types, 48
- Npp64f
 - npp_basic_types, 48
- Npp64fc
 - npp_basic_types, 48
- Npp64s
 - npp_basic_types, 48
- Npp64sc
 - npp_basic_types, 48
- Npp64u
 - npp_basic_types, 48
- Npp8s
 - npp_basic_types, 48
- Npp8u
 - npp_basic_types, 48
- Npp8uc
 - npp_basic_types, 49
- NPP_AFFINE_QUAD_INCORRECT_WARNING
 - typedefs_npp, 44
- NPP_ALG_HINT_ACCURATE
 - typedefs_npp, 39
- NPP_ALG_HINT_FAST
 - typedefs_npp, 39
- NPP_ALG_HINT_NONE
 - typedefs_npp, 39
- NPP_ALIGNMENT_ERROR
 - typedefs_npp, 43
- NPP_ANCHOR_ERROR
 - typedefs_npp, 43
- major

- NPP_BAD_ARGUMENT_ERROR
typedefs_npp, 44
- NPP_BORDER_CONSTANT
typedefs_npp, 40
- NPP_BORDER_MIRROR
typedefs_npp, 40
- NPP_BORDER_NONE
typedefs_npp, 40
- NPP_BORDER_REPLICATE
typedefs_npp, 40
- NPP_BORDER_UNDEFINED
typedefs_npp, 40
- NPP_BORDER_WRAP
typedefs_npp, 40
- NPP_BOTH_AXIS
typedefs_npp, 40
- NPP_CHANNEL_ERROR
typedefs_npp, 43
- NPP_CHANNEL_ORDER_ERROR
typedefs_npp, 43
- NPP_CMP_EQ
typedefs_npp, 39
- NPP_CMP_GREATER
typedefs_npp, 39
- NPP_CMP_GREATER_EQ
typedefs_npp, 39
- NPP_CMP_LESS
typedefs_npp, 38
- NPP_CMP_LESS_EQ
typedefs_npp, 38
- NPP_COEFFICIENT_ERROR
typedefs_npp, 43
- NPP_COI_ERROR
typedefs_npp, 43
- NPP_CONTEXT_MATCH_ERROR
typedefs_npp, 44
- NPP_CORRUPTED_DATA_ERROR
typedefs_npp, 43
- NPP_CUDA_1_0
typedefs_npp, 39
- NPP_CUDA_1_1
typedefs_npp, 39
- NPP_CUDA_1_2
typedefs_npp, 39
- NPP_CUDA_1_3
typedefs_npp, 39
- NPP_CUDA_2_0
typedefs_npp, 39
- NPP_CUDA_2_1
typedefs_npp, 39
- NPP_CUDA_3_0
typedefs_npp, 39
- NPP_CUDA_3_2
typedefs_npp, 39
- NPP_CUDA_3_5
typedefs_npp, 39
- NPP_CUDA_3_7
typedefs_npp, 39
- NPP_CUDA_5_0
typedefs_npp, 39
- NPP_CUDA_5_2
typedefs_npp, 39
- NPP_CUDA_5_3
typedefs_npp, 39
- NPP_CUDA_6_0
typedefs_npp, 39
- NPP_CUDA_KERNEL_EXECUTION_ERROR
typedefs_npp, 43
- NPP_CUDA_NOT_CAPABLE
typedefs_npp, 39
- NPP_CUDA_UNKNOWN_VERSION
typedefs_npp, 39
- NPP_DATA_TYPE_ERROR
typedefs_npp, 44
- NPP_DIVIDE_BY_ZERO_ERROR
typedefs_npp, 44
- NPP_DIVIDE_BY_ZERO_WARNING
typedefs_npp, 44
- NPP_DIVISOR_ERROR
typedefs_npp, 43
- NPP_DOUBLE_SIZE_WARNING
typedefs_npp, 44
- NPP_ERROR
typedefs_npp, 44
- NPP_ERROR_RESERVED
typedefs_npp, 44
- NPP_FFT_FLAG_ERROR
typedefs_npp, 44
- NPP_FFT_ORDER_ERROR
typedefs_npp, 44
- NPP_FILTER_SCHARR
typedefs_npp, 40
- NPP_FILTER_SOBEL
typedefs_npp, 40
- NPP_HAAR_CLASSIFIER_PIXEL_MATCH_-
ERROR
typedefs_npp, 43
- NPP_HISTOGRAM_NUMBER_OF_LEVELS_-
ERROR
typedefs_npp, 43
- NPP_HORIZONTAL_AXIS
typedefs_npp, 40
- NPP_INTERPOLATION_ERROR
typedefs_npp, 44
- NPP_INVALID_DEVICE_POINTER_ERROR
typedefs_npp, 43
- NPP_INVALID_HOST_POINTER_ERROR
typedefs_npp, 43

- NPP_LUT_NUMBER_OF_LEVELS_ERROR
 typedefs_npp, 43
 NPP_LUT_PALETTE_BITSIZE_ERROR
 typedefs_npp, 43
 NPP_MASK_SIZE_11_X_11
 typedefs_npp, 41
 NPP_MASK_SIZE_13_X_13
 typedefs_npp, 41
 NPP_MASK_SIZE_15_X_15
 typedefs_npp, 41
 NPP_MASK_SIZE_1_X_3
 typedefs_npp, 41
 NPP_MASK_SIZE_1_X_5
 typedefs_npp, 41
 NPP_MASK_SIZE_3_X_1
 typedefs_npp, 41
 NPP_MASK_SIZE_3_X_3
 typedefs_npp, 41
 NPP_MASK_SIZE_5_X_1
 typedefs_npp, 41
 NPP_MASK_SIZE_5_X_5
 typedefs_npp, 41
 NPP_MASK_SIZE_7_X_7
 typedefs_npp, 41
 NPP_MASK_SIZE_9_X_9
 typedefs_npp, 41
 NPP_MASK_SIZE_ERROR
 typedefs_npp, 43
 NPP_MEMCPY_ERROR
 typedefs_npp, 43
 NPP_MEMFREE_ERROR
 typedefs_npp, 43
 NPP_MEMORY_ALLOCATION_ERR
 typedefs_npp, 44
 NPP_MEMSET_ERROR
 typedefs_npp, 43
 NPP_MIRROR_FLIP_ERROR
 typedefs_npp, 44
 NPP_MISALIGNED_DST_ROI_WARNING
 typedefs_npp, 44
 NPP_MOMENT_00_ZERO_ERROR
 typedefs_npp, 44
 NPP_NO_ERROR
 typedefs_npp, 44
 NPP_NO_MEMORY_ERROR
 typedefs_npp, 44
 NPP_NO_OPERATION_WARNING
 typedefs_npp, 44
 NPP_NOT_EVEN_STEP_ERROR
 typedefs_npp, 43
 NPP_NOT_IMPLEMENTED_ERROR
 typedefs_npp, 44
 NPP_NOT_SUFFICIENT_COMPUTE_-
 CAPABILITY
 typedefs_npp, 43
 NPP_NOT_SUPPORTED_MODE_ERROR
 typedefs_npp, 43
 NPP_NULL_POINTER_ERROR
 typedefs_npp, 44
 NPP_NUMBER_OF_CHANNELS_ERROR
 typedefs_npp, 43
 NPP_OUT_OFF_RANGE_ERROR
 typedefs_npp, 44
 NPP_OVERFLOW_ERROR
 typedefs_npp, 43
 NPP_QUADRANGLE_ERROR
 typedefs_npp, 43
 NPP_QUALITY_INDEX_ERROR
 typedefs_npp, 43
 NPP_RANGE_ERROR
 typedefs_npp, 44
 NPP_RECTANGLE_ERROR
 typedefs_npp, 43
 NPP_RESIZE_FACTOR_ERROR
 typedefs_npp, 44
 NPP_RESIZE_NO_OPERATION_ERROR
 typedefs_npp, 43
 NPP_RND_FINANCIAL
 typedefs_npp, 42
 NPP_RND_NEAR
 typedefs_npp, 42
 NPP_RND_ZERO
 typedefs_npp, 42
 NPP_ROUND_MODE_NOT_SUPPORTED_-
 ERROR
 typedefs_npp, 43
 NPP_ROUND_NEAREST_TIES_AWAY_-
 FROM_ZERO
 typedefs_npp, 42
 NPP_ROUND_NEAREST_TIES_TO_EVEN
 typedefs_npp, 42
 NPP_ROUND_TOWARD_ZERO
 typedefs_npp, 42
 NPP_SCALE_RANGE_ERROR
 typedefs_npp, 44
 NPP_SIZE_ERROR
 typedefs_npp, 44
 NPP_STEP_ERROR
 typedefs_npp, 44
 NPP_STRIDE_ERROR
 typedefs_npp, 43
 NPP_SUCCESS
 typedefs_npp, 44
 NPP_TEXTURE_BIND_ERROR
 typedefs_npp, 43
 NPP_THRESHOLD_ERROR
 typedefs_npp, 44

- NPP_THRESHOLD_NEGATIVE_LEVEL_-
ERROR
typedefs_npp, 44
- NPP_VERTICAL_AXIS
typedefs_npp, 40
- NPP_WRONG_INTERSECTION_QUAD_-
WARNING
typedefs_npp, 44
- NPP_WRONG_INTERSECTION_ROI_ERROR
typedefs_npp, 43
- NPP_WRONG_INTERSECTION_ROI_-
WARNING
typedefs_npp, 44
- NPP_ZC_MODE_NOT_SUPPORTED_ERROR
typedefs_npp, 43
- NPP_ZERO_MASK_VALUE_ERROR
typedefs_npp, 43
- NPP_ALIGN_16, 163
im, 163
re, 164
- NPP_ALIGN_8, 165
im, 165
re, 165, 166
- npp_basic_types
__align__, 48, 49
Npp16s, 47
Npp16sc, 49
Npp16u, 47
Npp16uc, 49
Npp32f, 47
Npp32fc, 47
Npp32s, 47
Npp32sc, 47
Npp32u, 48
Npp32uc, 48
Npp64f, 48
Npp64fc, 48
Npp64s, 48
Npp64sc, 48
Npp64u, 48
Npp8s, 48
Npp8u, 48
Npp8uc, 49
- NPP_MAX_16S
typedefs_npp, 37
- NPP_MAX_16U
typedefs_npp, 37
- NPP_MAX_32S
typedefs_npp, 37
- NPP_MAX_32U
typedefs_npp, 37
- NPP_MAX_64S
typedefs_npp, 37
- NPP_MAX_64U
typedefs_npp, 37
- NPP_MAX_8S
typedefs_npp, 37
- NPP_MAX_8U
typedefs_npp, 37
- NPP_MAXABS_32F
typedefs_npp, 37
- NPP_MAXABS_64F
typedefs_npp, 37
- NPP_MIN_16S
typedefs_npp, 37
- NPP_MIN_16U
typedefs_npp, 38
- NPP_MIN_32S
typedefs_npp, 38
- NPP_MIN_32U
typedefs_npp, 38
- NPP_MIN_64S
typedefs_npp, 38
- NPP_MIN_64U
typedefs_npp, 38
- NPP_MIN_8S
typedefs_npp, 38
- NPP_MIN_8U
typedefs_npp, 38
- NPP_MINABS_32F
typedefs_npp, 38
- NPP_MINABS_64F
typedefs_npp, 38
- NppCmpOp
typedefs_npp, 38
- nppGetGpuComputeCapability
core_npp, 28
- nppGetGpuDeviceProperties
core_npp, 28
- nppGetGpuName
core_npp, 28
- nppGetGpuNumSMs
core_npp, 28
- nppGetLibVersion
core_npp, 28
- nppGetMaxThreadsPerBlock
core_npp, 29
- nppGetMaxThreadsPerSM
core_npp, 29
- nppGetStream
core_npp, 29
- nppGetStreamMaxThreadsPerSM
core_npp, 29
- nppGetStreamNumSMs
core_npp, 29
- NppGpuComputeCapability
typedefs_npp, 39
- NppHintAlgorithm

- typedefs_npp, 39
- NPPI_BAYER_BGGR
 - typedefs_npp, 40
- NPPI_BAYER_GBRG
 - typedefs_npp, 40
- NPPI_BAYER_GRBG
 - typedefs_npp, 40
- NPPI_BAYER_RGGG
 - typedefs_npp, 40
- NPPI_INTER_CUBIC
 - typedefs_npp, 41
- NPPI_INTER_CUBIC2P_B05C03
 - typedefs_npp, 41
- NPPI_INTER_CUBIC2P_BSPLINE
 - typedefs_npp, 41
- NPPI_INTER_CUBIC2P_CATMULLROM
 - typedefs_npp, 41
- NPPI_INTER_LANCZOS
 - typedefs_npp, 41
- NPPI_INTER_LANCZOS3_ADVANCED
 - typedefs_npp, 41
- NPPI_INTER_LINEAR
 - typedefs_npp, 41
- NPPI_INTER_NN
 - typedefs_npp, 41
- NPPI_INTER_SUPER
 - typedefs_npp, 41
- NPPI_INTER_UNDEFINED
 - typedefs_npp, 41
- NPPI_OP_ALPHA_ATOP
 - typedefs_npp, 39
- NPPI_OP_ALPHA_ATOP_PREMUL
 - typedefs_npp, 40
- NPPI_OP_ALPHA_IN
 - typedefs_npp, 39
- NPPI_OP_ALPHA_IN_PREMUL
 - typedefs_npp, 40
- NPPI_OP_ALPHA_OUT
 - typedefs_npp, 39
- NPPI_OP_ALPHA_OUT_PREMUL
 - typedefs_npp, 40
- NPPI_OP_ALPHA_OVER
 - typedefs_npp, 39
- NPPI_OP_ALPHA_OVER_PREMUL
 - typedefs_npp, 40
- NPPI_OP_ALPHA_PLUS
 - typedefs_npp, 39
- NPPI_OP_ALPHA_PLUS_PREMUL
 - typedefs_npp, 40
- NPPI_OP_ALPHA_PREMUL
 - typedefs_npp, 40
- NPPI_OP_ALPHA_XOR
 - typedefs_npp, 39
- NPPI_OP_ALPHA_XOR_PREMUL
 - typedefs_npp, 40
- NPPI_SMOOTH_EDGE
 - typedefs_npp, 41
- nppiACTable
 - typedefs_npp, 41
- NppiAlphaOp
 - typedefs_npp, 39
- NppiAxis
 - typedefs_npp, 40
- NppiBayerGridPosition
 - typedefs_npp, 40
- NppiBorderType
 - typedefs_npp, 40
- nppiCompare_16s_AC4R
 - image_compare_operations, 143
- nppiCompare_16s_C1R
 - image_compare_operations, 144
- nppiCompare_16s_C3R
 - image_compare_operations, 144
- nppiCompare_16s_C4R
 - image_compare_operations, 144
- nppiCompare_16u_AC4R
 - image_compare_operations, 145
- nppiCompare_16u_C1R
 - image_compare_operations, 145
- nppiCompare_16u_C3R
 - image_compare_operations, 146
- nppiCompare_16u_C4R
 - image_compare_operations, 146
- nppiCompare_32f_AC4R
 - image_compare_operations, 147
- nppiCompare_32f_C1R
 - image_compare_operations, 147
- nppiCompare_32f_C3R
 - image_compare_operations, 148
- nppiCompare_32f_C4R
 - image_compare_operations, 148
- nppiCompare_8u_AC4R
 - image_compare_operations, 149
- nppiCompare_8u_C1R
 - image_compare_operations, 149
- nppiCompare_8u_C3R
 - image_compare_operations, 150
- nppiCompare_8u_C4R
 - image_compare_operations, 150
- nppiCompareC_16s_AC4R
 - image_compare_operations, 151
- nppiCompareC_16s_C1R
 - image_compare_operations, 151
- nppiCompareC_16s_C3R
 - image_compare_operations, 152
- nppiCompareC_16s_C4R
 - image_compare_operations, 152
- nppiCompareC_16u_AC4R

- image_compare_operations, 153
- nppiCompareC_16u_C1R
 - image_compare_operations, 153
- nppiCompareC_16u_C3R
 - image_compare_operations, 153
- nppiCompareC_16u_C4R
 - image_compare_operations, 154
- nppiCompareC_32f_AC4R
 - image_compare_operations, 154
- nppiCompareC_32f_C1R
 - image_compare_operations, 155
- nppiCompareC_32f_C3R
 - image_compare_operations, 155
- nppiCompareC_32f_C4R
 - image_compare_operations, 156
- nppiCompareC_8u_AC4R
 - image_compare_operations, 156
- nppiCompareC_8u_C1R
 - image_compare_operations, 156
- nppiCompareC_8u_C3R
 - image_compare_operations, 157
- nppiCompareC_8u_C4R
 - image_compare_operations, 157
- nppiCompareEqualEps_32f_AC4R
 - image_compare_operations, 158
- nppiCompareEqualEps_32f_C1R
 - image_compare_operations, 158
- nppiCompareEqualEps_32f_C3R
 - image_compare_operations, 159
- nppiCompareEqualEps_32f_C4R
 - image_compare_operations, 159
- nppiCompareEqualEpsC_32f_AC4R
 - image_compare_operations, 160
- nppiCompareEqualEpsC_32f_C1R
 - image_compare_operations, 160
- nppiCompareEqualEpsC_32f_C3R
 - image_compare_operations, 161
- nppiCompareEqualEpsC_32f_C4R
 - image_compare_operations, 161
- nppiDCTable
 - typedefs_npp, 41
- NppiDifferentialKernel
 - typedefs_npp, 40
- NppiHaarBuffer, 167
 - haarBuffer, 167
 - haarBufferSize, 167
- NppiHaarClassifier_32f, 168
 - classifiers, 168
 - classifierSize, 168
 - classifierStep, 168
 - counterDevice, 168
 - numClassifiers, 168
- NppiHuffmanTableType
 - typedefs_npp, 40
- NppiInterpolationMode
 - typedefs_npp, 41
- NppiMaskSize
 - typedefs_npp, 41
- NppiNorm
 - typedefs_npp, 41
- nppiNormInf
 - typedefs_npp, 42
- nppiNormL1
 - typedefs_npp, 42
- nppiNormL2
 - typedefs_npp, 42
- NppiPoint, 169
 - x, 169
 - y, 169
- NppiRect, 170
 - height, 170
 - width, 170
 - x, 170
 - y, 170
- NppiSize, 171
 - height, 171
 - width, 171
- nppiThreshold_16s_AC4IR
 - image_threshold_operations, 65
- nppiThreshold_16s_AC4R
 - image_threshold_operations, 65
- nppiThreshold_16s_C1IR
 - image_threshold_operations, 66
- nppiThreshold_16s_C1R
 - image_threshold_operations, 66
- nppiThreshold_16s_C3IR
 - image_threshold_operations, 67
- nppiThreshold_16s_C3R
 - image_threshold_operations, 67
- nppiThreshold_16u_AC4IR
 - image_threshold_operations, 68
- nppiThreshold_16u_AC4R
 - image_threshold_operations, 68
- nppiThreshold_16u_C1IR
 - image_threshold_operations, 68
- nppiThreshold_16u_C1R
 - image_threshold_operations, 69
- nppiThreshold_16u_C3IR
 - image_threshold_operations, 69
- nppiThreshold_16u_C3R
 - image_threshold_operations, 70
- nppiThreshold_32f_AC4IR
 - image_threshold_operations, 70
- nppiThreshold_32f_AC4R
 - image_threshold_operations, 71
- nppiThreshold_32f_C1IR
 - image_threshold_operations, 71
- nppiThreshold_32f_C1R

- image_threshold_operations, 72
- nppiThreshold_32f_C3IR
 - image_threshold_operations, 72
- nppiThreshold_32f_C3R
 - image_threshold_operations, 72
- nppiThreshold_8u_AC4IR
 - image_threshold_operations, 73
- nppiThreshold_8u_AC4R
 - image_threshold_operations, 73
- nppiThreshold_8u_C1IR
 - image_threshold_operations, 74
- nppiThreshold_8u_C1R
 - image_threshold_operations, 74
- nppiThreshold_8u_C3IR
 - image_threshold_operations, 75
- nppiThreshold_8u_C3R
 - image_threshold_operations, 75
- nppiThreshold_GT_16s_AC4IR
 - image_threshold_operations, 76
- nppiThreshold_GT_16s_AC4R
 - image_threshold_operations, 76
- nppiThreshold_GT_16s_C1IR
 - image_threshold_operations, 77
- nppiThreshold_GT_16s_C1R
 - image_threshold_operations, 77
- nppiThreshold_GT_16s_C3IR
 - image_threshold_operations, 77
- nppiThreshold_GT_16s_C3R
 - image_threshold_operations, 78
- nppiThreshold_GT_16u_AC4IR
 - image_threshold_operations, 78
- nppiThreshold_GT_16u_AC4R
 - image_threshold_operations, 79
- nppiThreshold_GT_16u_C1IR
 - image_threshold_operations, 79
- nppiThreshold_GT_16u_C1R
 - image_threshold_operations, 79
- nppiThreshold_GT_16u_C3IR
 - image_threshold_operations, 80
- nppiThreshold_GT_16u_C3R
 - image_threshold_operations, 80
- nppiThreshold_GT_32f_AC4IR
 - image_threshold_operations, 81
- nppiThreshold_GT_32f_AC4R
 - image_threshold_operations, 81
- nppiThreshold_GT_32f_C1IR
 - image_threshold_operations, 81
- nppiThreshold_GT_32f_C1R
 - image_threshold_operations, 82
- nppiThreshold_GT_32f_C3IR
 - image_threshold_operations, 82
- nppiThreshold_GT_32f_C3R
 - image_threshold_operations, 83
- nppiThreshold_GT_8u_AC4IR
 - image_threshold_operations, 83
- nppiThreshold_GT_8u_AC4R
 - image_threshold_operations, 83
- nppiThreshold_GT_8u_C1IR
 - image_threshold_operations, 84
- nppiThreshold_GT_8u_C1R
 - image_threshold_operations, 84
- nppiThreshold_GT_8u_C3IR
 - image_threshold_operations, 85
- nppiThreshold_GT_8u_C3R
 - image_threshold_operations, 85
- nppiThreshold_GTVal_16s_AC4IR
 - image_threshold_operations, 85
- nppiThreshold_GTVal_16s_AC4R
 - image_threshold_operations, 86
- nppiThreshold_GTVal_16s_C1IR
 - image_threshold_operations, 86
- nppiThreshold_GTVal_16s_C1R
 - image_threshold_operations, 87
- nppiThreshold_GTVal_16s_C3IR
 - image_threshold_operations, 87
- nppiThreshold_GTVal_16s_C3R
 - image_threshold_operations, 87
- nppiThreshold_GTVal_16u_AC4IR
 - image_threshold_operations, 88
- nppiThreshold_GTVal_16u_AC4R
 - image_threshold_operations, 88
- nppiThreshold_GTVal_16u_C1IR
 - image_threshold_operations, 89
- nppiThreshold_GTVal_16u_C1R
 - image_threshold_operations, 89
- nppiThreshold_GTVal_16u_C3IR
 - image_threshold_operations, 90
- nppiThreshold_GTVal_16u_C3R
 - image_threshold_operations, 90
- nppiThreshold_GTVal_32f_AC4IR
 - image_threshold_operations, 90
- nppiThreshold_GTVal_32f_AC4R
 - image_threshold_operations, 91
- nppiThreshold_GTVal_32f_C1IR
 - image_threshold_operations, 91
- nppiThreshold_GTVal_32f_C1R
 - image_threshold_operations, 92
- nppiThreshold_GTVal_32f_C3IR
 - image_threshold_operations, 92
- nppiThreshold_GTVal_32f_C3R
 - image_threshold_operations, 92
- nppiThreshold_GTVal_8u_AC4IR
 - image_threshold_operations, 93
- nppiThreshold_GTVal_8u_AC4R
 - image_threshold_operations, 93
- nppiThreshold_GTVal_8u_C1IR
 - image_threshold_operations, 94
- nppiThreshold_GTVal_8u_C1R
 - image_threshold_operations, 94

- image_threshold_operations, 94
- nppiThreshold_GTVal_8u_C3IR
 - image_threshold_operations, 95
- nppiThreshold_GTVal_8u_C3R
 - image_threshold_operations, 95
- nppiThreshold_LT_16s_AC4IR
 - image_threshold_operations, 95
- nppiThreshold_LT_16s_AC4R
 - image_threshold_operations, 96
- nppiThreshold_LT_16s_C1IR
 - image_threshold_operations, 96
- nppiThreshold_LT_16s_C1R
 - image_threshold_operations, 97
- nppiThreshold_LT_16s_C3IR
 - image_threshold_operations, 97
- nppiThreshold_LT_16s_C3R
 - image_threshold_operations, 97
- nppiThreshold_LT_16u_AC4IR
 - image_threshold_operations, 98
- nppiThreshold_LT_16u_AC4R
 - image_threshold_operations, 98
- nppiThreshold_LT_16u_C1IR
 - image_threshold_operations, 99
- nppiThreshold_LT_16u_C1R
 - image_threshold_operations, 99
- nppiThreshold_LT_16u_C3IR
 - image_threshold_operations, 99
- nppiThreshold_LT_16u_C3R
 - image_threshold_operations, 100
- nppiThreshold_LT_32f_AC4IR
 - image_threshold_operations, 100
- nppiThreshold_LT_32f_AC4R
 - image_threshold_operations, 101
- nppiThreshold_LT_32f_C1IR
 - image_threshold_operations, 101
- nppiThreshold_LT_32f_C1R
 - image_threshold_operations, 101
- nppiThreshold_LT_32f_C3IR
 - image_threshold_operations, 102
- nppiThreshold_LT_32f_C3R
 - image_threshold_operations, 102
- nppiThreshold_LT_8u_AC4IR
 - image_threshold_operations, 103
- nppiThreshold_LT_8u_AC4R
 - image_threshold_operations, 103
- nppiThreshold_LT_8u_C1IR
 - image_threshold_operations, 103
- nppiThreshold_LT_8u_C1R
 - image_threshold_operations, 104
- nppiThreshold_LT_8u_C3IR
 - image_threshold_operations, 104
- nppiThreshold_LT_8u_C3R
 - image_threshold_operations, 105
- nppiThreshold_LTVal_16s_AC4IR
 - image_threshold_operations, 105
- nppiThreshold_LTVal_16s_AC4R
 - image_threshold_operations, 105
- nppiThreshold_LTVal_16s_C1IR
 - image_threshold_operations, 106
- nppiThreshold_LTVal_16s_C1R
 - image_threshold_operations, 106
- nppiThreshold_LTVal_16s_C3IR
 - image_threshold_operations, 107
- nppiThreshold_LTVal_16s_C3R
 - image_threshold_operations, 107
- nppiThreshold_LTVal_16u_AC4IR
 - image_threshold_operations, 108
- nppiThreshold_LTVal_16u_AC4R
 - image_threshold_operations, 108
- nppiThreshold_LTVal_16u_C1IR
 - image_threshold_operations, 108
- nppiThreshold_LTVal_16u_C1R
 - image_threshold_operations, 109
- nppiThreshold_LTVal_16u_C3IR
 - image_threshold_operations, 109
- nppiThreshold_LTVal_16u_C3R
 - image_threshold_operations, 110
- nppiThreshold_LTVal_32f_AC4IR
 - image_threshold_operations, 110
- nppiThreshold_LTVal_32f_AC4R
 - image_threshold_operations, 110
- nppiThreshold_LTVal_32f_C1IR
 - image_threshold_operations, 111
- nppiThreshold_LTVal_32f_C1R
 - image_threshold_operations, 111
- nppiThreshold_LTVal_32f_C3IR
 - image_threshold_operations, 112
- nppiThreshold_LTVal_32f_C3R
 - image_threshold_operations, 112
- nppiThreshold_LTVal_8u_AC4IR
 - image_threshold_operations, 113
- nppiThreshold_LTVal_8u_AC4R
 - image_threshold_operations, 113
- nppiThreshold_LTVal_8u_C1IR
 - image_threshold_operations, 113
- nppiThreshold_LTVal_8u_C1R
 - image_threshold_operations, 114
- nppiThreshold_LTVal_8u_C3IR
 - image_threshold_operations, 114
- nppiThreshold_LTVal_8u_C3R
 - image_threshold_operations, 115
- nppiThreshold_LTValGTVal_16s_AC4IR
 - image_threshold_operations, 115
- nppiThreshold_LTValGTVal_16s_AC4R
 - image_threshold_operations, 116
- nppiThreshold_LTValGTVal_16s_C1IR
 - image_threshold_operations, 116
- nppiThreshold_LTValGTVal_16s_C1R
 - image_threshold_operations, 116

- image_threshold_operations, 117
- nppiThreshold_LTValGTVal_16s_C3IR
 - image_threshold_operations, 117
- nppiThreshold_LTValGTVal_16s_C3R
 - image_threshold_operations, 118
- nppiThreshold_LTValGTVal_16u_AC4IR
 - image_threshold_operations, 118
- nppiThreshold_LTValGTVal_16u_AC4R
 - image_threshold_operations, 119
- nppiThreshold_LTValGTVal_16u_C1IR
 - image_threshold_operations, 119
- nppiThreshold_LTValGTVal_16u_C1R
 - image_threshold_operations, 120
- nppiThreshold_LTValGTVal_16u_C3IR
 - image_threshold_operations, 120
- nppiThreshold_LTValGTVal_16u_C3R
 - image_threshold_operations, 121
- nppiThreshold_LTValGTVal_32f_AC4IR
 - image_threshold_operations, 121
- nppiThreshold_LTValGTVal_32f_AC4R
 - image_threshold_operations, 122
- nppiThreshold_LTValGTVal_32f_C1IR
 - image_threshold_operations, 122
- nppiThreshold_LTValGTVal_32f_C1R
 - image_threshold_operations, 123
- nppiThreshold_LTValGTVal_32f_C3IR
 - image_threshold_operations, 123
- nppiThreshold_LTValGTVal_32f_C3R
 - image_threshold_operations, 124
- nppiThreshold_LTValGTVal_8u_AC4IR
 - image_threshold_operations, 124
- nppiThreshold_LTValGTVal_8u_AC4R
 - image_threshold_operations, 125
- nppiThreshold_LTValGTVal_8u_C1IR
 - image_threshold_operations, 125
- nppiThreshold_LTValGTVal_8u_C1R
 - image_threshold_operations, 126
- nppiThreshold_LTValGTVal_8u_C3IR
 - image_threshold_operations, 126
- nppiThreshold_LTValGTVal_8u_C3R
 - image_threshold_operations, 127
- nppiThreshold_Val_16s_AC4IR
 - image_threshold_operations, 127
- nppiThreshold_Val_16s_AC4R
 - image_threshold_operations, 128
- nppiThreshold_Val_16s_C1IR
 - image_threshold_operations, 128
- nppiThreshold_Val_16s_C1R
 - image_threshold_operations, 129
- nppiThreshold_Val_16s_C3IR
 - image_threshold_operations, 129
- nppiThreshold_Val_16s_C3R
 - image_threshold_operations, 130
- nppiThreshold_Val_16u_AC4IR
 - image_threshold_operations, 130
- nppiThreshold_Val_16u_AC4R
 - image_threshold_operations, 131
- nppiThreshold_Val_16u_C1IR
 - image_threshold_operations, 131
- nppiThreshold_Val_16u_C1R
 - image_threshold_operations, 132
- nppiThreshold_Val_16u_C3IR
 - image_threshold_operations, 132
- nppiThreshold_Val_16u_C3R
 - image_threshold_operations, 133
- nppiThreshold_Val_32f_AC4IR
 - image_threshold_operations, 133
- nppiThreshold_Val_32f_AC4R
 - image_threshold_operations, 134
- nppiThreshold_Val_32f_C1IR
 - image_threshold_operations, 134
- nppiThreshold_Val_32f_C1R
 - image_threshold_operations, 135
- nppiThreshold_Val_32f_C3IR
 - image_threshold_operations, 135
- nppiThreshold_Val_32f_C3R
 - image_threshold_operations, 136
- nppiThreshold_Val_8u_AC4IR
 - image_threshold_operations, 136
- nppiThreshold_Val_8u_AC4R
 - image_threshold_operations, 137
- nppiThreshold_Val_8u_C1IR
 - image_threshold_operations, 137
- nppiThreshold_Val_8u_C1R
 - image_threshold_operations, 138
- nppiThreshold_Val_8u_C3IR
 - image_threshold_operations, 138
- nppiThreshold_Val_8u_C3R
 - image_threshold_operations, 139
- NppLibraryVersion, 172
 - build, 172
 - major, 172
 - minor, 172
- NppRoundMode
 - typedefs_npp, 42
- nppSetStream
 - core_npp, 29
- NppStatus
 - typedefs_npp, 42
- NppsZCType
 - typedefs_npp, 44
- nppZCC
 - typedefs_npp, 45
- nppZCR
 - typedefs_npp, 45
- nppZCXor
 - typedefs_npp, 45
- numClassifiers

- NppiHaarClassifier_32f, 168
- re
 - NPP_ALIGN_16, 164
 - NPP_ALIGN_8, 165, 166
- Threshold and Compare Operations, 50
- Threshold Operations, 51
- typedefs_npp
 - NPP_AFFINE_QUAD_INCORRECT_ -
WARNING, 44
 - NPP_ALG_HINT_ACCURATE, 39
 - NPP_ALG_HINT_FAST, 39
 - NPP_ALG_HINT_NONE, 39
 - NPP_ALIGNMENT_ERROR, 43
 - NPP_ANCHOR_ERROR, 43
 - NPP_BAD_ARGUMENT_ERROR, 44
 - NPP_BORDER_CONSTANT, 40
 - NPP_BORDER_MIRROR, 40
 - NPP_BORDER_NONE, 40
 - NPP_BORDER_REPLICATE, 40
 - NPP_BORDER_UNDEFINED, 40
 - NPP_BORDER_WRAP, 40
 - NPP_BOTH_AXIS, 40
 - NPP_CHANNEL_ERROR, 43
 - NPP_CHANNEL_ORDER_ERROR, 43
 - NPP_CMP_EQ, 39
 - NPP_CMP_GREATER, 39
 - NPP_CMP_GREATER_EQ, 39
 - NPP_CMP_LESS, 38
 - NPP_CMP_LESS_EQ, 38
 - NPP_COEFFICIENT_ERROR, 43
 - NPP_COI_ERROR, 43
 - NPP_CONTEXT_MATCH_ERROR, 44
 - NPP_CORRUPTED_DATA_ERROR, 43
 - NPP_CUDA_1_0, 39
 - NPP_CUDA_1_1, 39
 - NPP_CUDA_1_2, 39
 - NPP_CUDA_1_3, 39
 - NPP_CUDA_2_0, 39
 - NPP_CUDA_2_1, 39
 - NPP_CUDA_3_0, 39
 - NPP_CUDA_3_2, 39
 - NPP_CUDA_3_5, 39
 - NPP_CUDA_3_7, 39
 - NPP_CUDA_5_0, 39
 - NPP_CUDA_5_2, 39
 - NPP_CUDA_5_3, 39
 - NPP_CUDA_6_0, 39
 - NPP_CUDA_KERNEL_EXECUTION_ -
ERROR, 43
 - NPP_CUDA_NOT_CAPABLE, 39
 - NPP_CUDA_UNKNOWN_VERSION, 39
 - NPP_DATA_TYPE_ERROR, 44
 - NPP_DIVIDE_BY_ZERO_ERROR, 44
 - NPP_DIVIDE_BY_ZERO_WARNING, 44
 - NPP_DIVISOR_ERROR, 43
 - NPP_DOUBLE_SIZE_WARNING, 44
 - NPP_ERROR, 44
 - NPP_ERROR_RESERVED, 44
 - NPP_FFT_FLAG_ERROR, 44
 - NPP_FFT_ORDER_ERROR, 44
 - NPP_FILTER_SCHARR, 40
 - NPP_FILTER_SOBEL, 40
 - NPP_HAAR_CLASSIFIER_PIXEL_ -
MATCH_ERROR, 43
 - NPP_HISTOGRAM_NUMBER_OF_ -
LEVELS_ERROR, 43
 - NPP_HORIZONTAL_AXIS, 40
 - NPP_INTERPOLATION_ERROR, 44
 - NPP_INVALID_DEVICE_POINTER_ -
ERROR, 43
 - NPP_INVALID_HOST_POINTER_ERROR,
43
 - NPP_LUT_NUMBER_OF_LEVELS_ -
ERROR, 43
 - NPP_LUT_PALETTE_BITSIZE_ERROR, 43
 - NPP_MASK_SIZE_11_X_11, 41
 - NPP_MASK_SIZE_13_X_13, 41
 - NPP_MASK_SIZE_15_X_15, 41
 - NPP_MASK_SIZE_1_X_3, 41
 - NPP_MASK_SIZE_1_X_5, 41
 - NPP_MASK_SIZE_3_X_1, 41
 - NPP_MASK_SIZE_3_X_3, 41
 - NPP_MASK_SIZE_5_X_1, 41
 - NPP_MASK_SIZE_5_X_5, 41
 - NPP_MASK_SIZE_7_X_7, 41
 - NPP_MASK_SIZE_9_X_9, 41
 - NPP_MASK_SIZE_ERROR, 43
 - NPP_MEMCPY_ERROR, 43
 - NPP_MEMFREE_ERROR, 43
 - NPP_MEMORY_ALLOCATION_ERR, 44
 - NPP_MEMSET_ERROR, 43
 - NPP_MIRROR_FLIP_ERROR, 44
 - NPP_MISALIGNED_DST_ROI_WARNING,
44
 - NPP_MOMENT_00_ZERO_ERROR, 44
 - NPP_NO_ERROR, 44
 - NPP_NO_MEMORY_ERROR, 44
 - NPP_NO_OPERATION_WARNING, 44
 - NPP_NOT_EVEN_STEP_ERROR, 43
 - NPP_NOT_IMPLEMENTED_ERROR, 44
 - NPP_NOT_SUFFICIENT_COMPUTE_ -
CAPABILITY, 43
 - NPP_NOT_SUPPORTED_MODE_ERROR,
43
 - NPP_NULL_POINTER_ERROR, 44

- NPP_NUMBER_OF_CHANNELS_ERROR, 43
- NPP_OUT_OFF_RANGE_ERROR, 44
- NPP_OVERFLOW_ERROR, 43
- NPP_QUADRANGLE_ERROR, 43
- NPP_QUALITY_INDEX_ERROR, 43
- NPP_RANGE_ERROR, 44
- NPP_RECTANGLE_ERROR, 43
- NPP_RESIZE_FACTOR_ERROR, 44
- NPP_RESIZE_NO_OPERATION_ERROR, 43
- NPP_RND_FINANCIAL, 42
- NPP_RND_NEAR, 42
- NPP_RND_ZERO, 42
- NPP_ROUND_MODE_NOT_SUPPORTED_ERROR, 43
- NPP_ROUND_NEAREST_TIES_AWAY_FROM_ZERO, 42
- NPP_ROUND_NEAREST_TIES_TO_EVEN, 42
- NPP_ROUND_TOWARD_ZERO, 42
- NPP_SCALE_RANGE_ERROR, 44
- NPP_SIZE_ERROR, 44
- NPP_STEP_ERROR, 44
- NPP_STRIDE_ERROR, 43
- NPP_SUCCESS, 44
- NPP_TEXTURE_BIND_ERROR, 43
- NPP_THRESHOLD_ERROR, 44
- NPP_THRESHOLD_NEGATIVE_LEVEL_ERROR, 44
- NPP_VERTICAL_AXIS, 40
- NPP_WRONG_INTERSECTION_QUAD_WARNING, 44
- NPP_WRONG_INTERSECTION_ROI_ERROR, 43
- NPP_WRONG_INTERSECTION_ROI_WARNING, 44
- NPP_ZC_MODE_NOT_SUPPORTED_ERROR, 43
- NPP_ZERO_MASK_VALUE_ERROR, 43
- NPPI_BAYER_BGGR, 40
- NPPI_BAYER_GBRG, 40
- NPPI_BAYER_GRBG, 40
- NPPI_BAYER_RRGB, 40
- NPPI_INTER_CUBIC, 41
- NPPI_INTER_CUBIC2P_B05C03, 41
- NPPI_INTER_CUBIC2P_BSPLINE, 41
- NPPI_INTER_CUBIC2P_CATMULLROM, 41
- NPPI_INTER_LANCZOS, 41
- NPPI_INTER_LANCZOS3_ADVANCED, 41
- NPPI_INTER_LINEAR, 41
- NPPI_INTER_NN, 41
- NPPI_INTER_SUPER, 41
- NPPI_INTER_UNDEFINED, 41
- NPPI_OP_ALPHA_ATOP, 39
- NPPI_OP_ALPHA_ATOP_PREMUL, 40
- NPPI_OP_ALPHA_IN, 39
- NPPI_OP_ALPHA_IN_PREMUL, 40
- NPPI_OP_ALPHA_OUT, 39
- NPPI_OP_ALPHA_OUT_PREMUL, 40
- NPPI_OP_ALPHA_OVER, 39
- NPPI_OP_ALPHA_OVER_PREMUL, 40
- NPPI_OP_ALPHA_PLUS, 39
- NPPI_OP_ALPHA_PLUS_PREMUL, 40
- NPPI_OP_ALPHA_PREMUL, 40
- NPPI_OP_ALPHA_XOR, 39
- NPPI_OP_ALPHA_XOR_PREMUL, 40
- NPPI_SMOOTH_EDGE, 41
- nppiACTable, 41
- nppiDCTable, 41
- nppiNormInf, 42
- nppiNormL1, 42
- nppiNormL2, 42
- nppZCC, 45
- nppZCR, 45
- nppZCXor, 45
- typedefs_npp
 - NPP_MAX_16S, 37
 - NPP_MAX_16U, 37
 - NPP_MAX_32S, 37
 - NPP_MAX_32U, 37
 - NPP_MAX_64S, 37
 - NPP_MAX_64U, 37
 - NPP_MAX_8S, 37
 - NPP_MAX_8U, 37
 - NPP_MAXABS_32F, 37
 - NPP_MAXABS_64F, 37
 - NPP_MIN_16S, 37
 - NPP_MIN_16U, 38
 - NPP_MIN_32S, 38
 - NPP_MIN_32U, 38
 - NPP_MIN_64S, 38
 - NPP_MIN_64U, 38
 - NPP_MIN_8S, 38
 - NPP_MIN_8U, 38
 - NPP_MINABS_32F, 38
 - NPP_MINABS_64F, 38
 - NppCmpOp, 38
 - NppGpuComputeCapability, 39
 - NppHintAlgorithm, 39
 - NppiAlphaOp, 39
 - NppiAxis, 40
 - NppiBayerGridPosition, 40
 - NppiBorderType, 40
 - NppiDifferentialKernel, 40
 - NppiHuffmanTableType, 40
 - NppiInterpolationMode, 41

NppiMaskSize, [41](#)
NppiNorm, [41](#)
NppRoundMode, [42](#)
NppStatus, [42](#)
NppsZCType, [44](#)

width

NppiRect, [170](#)
NppiSize, [171](#)

x

NppiPoint, [169](#)
NppiRect, [170](#)

y

NppiPoint, [169](#)
NppiRect, [170](#)